OPA1692 低消費電力、低ノイズ、低歪みの SoundPlus™オーディオ・オペアンプ

1 特長

- 低ノイズ: 1kHz時に4.2nV/√Hz
- 低歪: 1kHz時に-127dB
- 低い静止電流: チャネルごとに650µA
- スルー・レート: 23V/µs
- 広いゲイン帯域幅: 5.1MHz
- ユニティ・ゲインで安定
- レール・ツー・レール出力
- 広い電源電圧範囲:
  ±1.75V～±18V、または3.5V～36V

2 アプリケーション

- ワイヤレス・マイク
- ワイヤレス・オーディオ・モニタリング・システム
- ポータブル無線およびヘッドセット
- ポータブル・オーディオ・エフェクト・プロセッサ
- ポータブル・レコーディング・システム
- USBオーディオ・ペリフェラル

3 概要

OPA169xオペアンプは、4.2nV/√Hzの低いノイズ密度と、1kHzで-127dBの歪みを実現し、低消費電力アンプとして革新的な性能を達成します。このオペアンプは、2kΩ負荷で電源の200mV以内までのレール・ツー・レール出力が可能なため、ヘッドルームが増大し、ダイナミックレンジが最大化します。これらのデバイスは、±50mAの高い出力駆動能力を持ちます。

OPA169xオペアンプは、±1.75V～±18Vまたは3.5V～36Vの広い電源電圧範囲で動作し(チャネルごとに消費電流650µA)、ユニティ・ゲイン安定で、広い範囲の負荷条件で非常に優れた動的な動作を行います。

OPA169xオペアンプは、-40℃～125℃の温度範囲で動作が規定されています。

製品情報(1)

型番	パッケージ	本体サイズ(公称)
OPA1692	VSSOP (8)	3.00mm×3.00mm
	SOIC (8)	4.90mm×3.91mm

(1) 利用可能なすべてのパッケージについては、このデータシートの末尾にあるパッケージ・オプションについての付録を参照してください。

3線式エレクトレット・マイク用のプリアンプ



Copyright © 2017, Texas Instruments Incorporated

THD+Nと周波数との関係(3V_{RMS}、2kΩの負荷)



英語版のTI製品についての情報を翻訳したこの資料は、製品の概要を確認する目的で便宜的に提供しているものです。該当する正式な英語版の最新情報は、www.ti.comで閲覧でき、その内容が常に優先されます。TIでは翻訳の正確性および妥当性につきましては一切保証いたしません。実際の設計などの前には、必ず最新版の英語版をご参照くださいますようお願いいたします。

目次

1 特長 ... 1
2 アプリケーション ... 1
3 概要 ... 1
4 改訂履歴 ... 2
5 **Pin Configuration and Functions** ... 3
6 **Specifications** ... 4
6.1 Absolute Maximum Ratings ... 4
6.2 ESD Ratings ... 4
6.3 Recommended Operating Conditions ... 4
6.4 Thermal Information: OPA1692 ... 4
6.5 Electrical Characteristics ... 5
6.6 Typical Characteristics ... 7
7 **Detailed Description** ... 16
7.1 Overview ... 16
7.2 Functional Block Diagram ... 16
7.3 Feature Description ... 16
7.4 Device Functional Modes ... 19
8 **Application and Implementation** ... 20
8.1 Application Information ... 20
8.2 Typical Application ... 24
8.3 Other Application Examples ... 27
9 **Power Supply Recommendations** ... 29
10 **Layout** ... 29
10.1 Layout Guidelines ... 29
10.2 Layout Example ... 30
10.3 Power Dissipation ... 30
11 デバイスおよびドキュメントのサポート ... 31
11.1 デバイス・サポート ... 31
11.2 ドキュメントのサポート ... 32
11.3 関連リンク ... 32
11.4 ドキュメントの更新通知を受け取る方法 ... 32
11.5 コミュニティ・リソース ... 32
11.6 商標 ... 32
11.7 静電気放電に関する注意事項 ... 32
11.8 Glossary ... 33
12 メカニカル、パッケージ、および注文情報 ... 33

4 改訂履歴

資料番号末尾の英字は改訂を表しています。その改訂履歴は英語版に準じています。

Revision B (September 2018) から **Revision C** に変更 **Page**

- Changed -40℃ to 125℃ Iq to 975 µA ... 6

Revision A (December 2017) から **Revision B** に変更 **Page**

- Changed I_{OS} VCM = 0 MAX from "±10" to "±15" nA ... 5
- Changed I_{OS} TA = –40°C to 125°C MAX from "±15" to "±20" nA ... 5

2017年6月 発行のものから更新 **Page**

- データシートの状態を「事前情報」から「量産データ」に 変更 ... 1

Copyright © 2017–2018, Texas Instruments Incorporated

5 Pin Configuration and Functions

OPA1692 D and DGK Packages
8-Pin SOIC and VSSOP
Top View



Not to scale

Pin Functions: OPA1692

PIN		I/O	DESCRIPTION
NAME	NO.		
–IN A	2	I	Inverting input, channel A
+IN A	3	I	Noninverting input, channel A
–IN B	6	I	Inverting input, channel B
+IN B	5	I	Noninverting input, channel B
OUT A	1	O	Output, channel A
OUT B	7	O	Output, channel B
V–	4	—	Negative (lowest) power supply
V+	8	—	Positive (highest) power supply

Copyright © 2017–2018, Texas Instruments Incorporated

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

		MIN	MAX	UNIT
Voltage	Supply voltage, V_S = (V+) – (V–)		40	V
	Input	(V–) – 0.5	(V+) + 0.5	
Current	Input (all pins except power-supply pins)	–10	10	mA
	Output short-circuit(2)	Continuous	Continuous	
Temperature	Operating, T_A	–55	125	°C
	Junction, T_J		200	
	Storage, T_{stg}	–65	150	

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions* . Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) Short-circuit to V_S/2 (ground in symmetrical dual supply setups), one amplifier per package.

6.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001(1)	±3000	V
		Charged-device model (CDM), per JEDEC specification JESD22-C101(2)	±1000	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

			MIN	NOM	MAX	UNIT
V_S	Supply voltage	Single supply	3.5		36	V
		Split supply	±1.75		±18	
T_A	Operating temperature		–40		85	°C

6.4 Thermal Information: OPA1692

THERMAL METRIC(1)		OPA1692		UNIT
		D (SOIC)	DGK (VSSOP)	
		8 PINS	8 PINS	
$R_{\theta JA}$	Junction-to-ambient thermal resistance	123.6	162.2	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	63.4	56.9	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	67.0	83.2	°C/W
ψ_{JT}	Junction-to-top characterization parameter	16.0	6.3	°C/W
ψ_{JB}	Junction-to-board characterization parameter	66.3	81.6	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	N/A	N/A	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report.

Copyright © 2017–2018, Texas Instruments Incorporated

6.5 Electrical Characteristics

at T_A = 25°C, V_S = ±18 V, R_L = 2 kΩ, and V_{CM} = V_{OUT} = midsupply (unless otherwise noted)

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
AUDIO PERFORMANCE							
THD+N	Total harmonic distortion + noise	G = 1, f = 20 kHz, RL = 2kΩ, VO = 3 VRMS			-118		dB
		G = 1, f = 1 kHz, R_L = 2kΩ, V_O = 3 V_{RMS}			–127		dB
IMD	Intermodulation distortion	G = 1, V_O = 3 V_{RMS}	SMPTE/DIN two-tone, 4:1 (60 Hz and 7 kHz)		0.00005%		
	Intermodulation distortion	G = 1, V_O = 3 V_{RMS}			-126		dB
	Intermodulation distortion	G = 1, V_O = 3 V_{RMS}	CCIF twin-tone (19 kHz and 20 kHz)		0.0002		
	Intermodulation distortion	G = 1, V_O = 3 V_{RMS}	CCIF twin-tone (19 kHz and 20 kHz)		-114		dB
FREQUENCY RESPONSE							
GBW	Gain-bandwidth product	G = 100			5.1		MHz
SR	Slew rate	G = –1			23		V/µs
	Full power bandwidth(1)	V_O = 1 V_P			3.66		MHz
	Overload recovery time	G = –10			250		ns
	Channel separation (dual and quad)	f = 1 kHz			–145		dB
NOISE							
e_n	Input voltage noise	f = 0.1 to 10 Hz			130		nV_{PP}
e_n	Input voltage noise	f = 20 Hz to 20 kHz			3.9		μV_{PP}
	Input voltage noise density	f = 1 kHz			4.2		nV/rtHz
		f = 100 Hz			4.5		
I_n	Input current noise density	f = 1 kHz			0.37		pA/rtHz
		f = 100 Hz			0.4		
OFFSET VOLTAGE							
V_{OS}	Input offset voltage	V_S = ±1.75 V to ±18 V			±0.25	±0.8	mV
V_{OS}	Input offset voltage	V_S = ±1.75 V to ±18 V				±1.0	mV
		V_S = ±1.75 V to ±18 V, T_A = –40°C to +125°C(2)			0.5	5	µV/°C
PSRR	Power-supply rejection ratio	V_S = ±1.75 V to ±18 V			0.1	1.5	µV/V
PSRR	Power-supply rejection ratio	T_A = –40°C to +125°C(2)				2.25	µV/V
INPUT BIAS CURRENT							
I_B	Input bias current	V_{CM} = 0 V			300	550	nA
		T_A = –40°C to +125°C				600	nA
I_{OS}	Input offset current	V_{CM} = 0 V			±2	±15	nA
		TA = –40°C to +125°C				±20	nA
INPUT VOLTAGE RANGE							
V_{CM}	Common-mode voltage range			(V–) + 1.5		(V+) – 0.5	V
CMRR	Common-mode rejection ratio	(V–) + 1.5 V ≤ V_{CM} ≤ (V+) – 0.5 V			0.1	1	uV/V
CMRR	Common-mode rejection ratio	TA = –40°C to +125°C				4	uV/V
INPUT IMPEDANCE							
	Differential Resistance				350		kΩ
	Differential Capacitance				1.5		pF
	Common-Mode Resistance				350		MΩ
	Common-Mode Capacitance				1.6		pF
OPEN-LOOP GAIN							
A_{OL}	Open-loop voltage gain	TA = –40°C to +125°C		110	140		dB
A_{OL}	Open-loop voltage gain	(V–) + 0.2 V ≤ V_O ≤ (V+) – 0.2 V, R_L = 2 kΩ		120	140		dB

(1) Full-power bandwidth = SR / (2π × V_P), where SR = slew rate.
(2) Specified by design and characterization.

Copyright © 2017–2018, Texas Instruments Incorporated

Electrical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, R_L = 2 kΩ, and V_{CM} = V_{OUT} = midsupply (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
OUTPUT						
V_{OUT}	Voltage output	R_L = 2 kΩ	-17.8		17.8	V
I_{OUT}	Output current			See *Figure 46* , *Figure 47*		mA
Z_O	Open-loop output impedance			See *Figure 14*		Ω
I_{SC}	Short-circuit current(3)			±50		mA
C_{LOAD}	Capacitive load drive			200		pF
POWER SUPPLY						
I_Q	Quiescent current (per channel)	I_{OUT} = 0 A		650	750	µA
		I_{OUT} = 0 A, T_A = –40°C to +125°C(2)		650	975	µA

(3) One channel at a time.

Copyright © 2017–2018, Texas Instruments Incorporated

6.6 Typical Characteristics

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 1. Input Offset Voltage Distribution



図 2. Input Offset Voltage Matching (Ch. A – Ch. B)



図 3. Offset Voltage Drift Distribution



図 4. Input Bias Current Distribution



図 5. Input Offset Current Distribution



図 6. Power Supply Current Distribution

Copyright © 2017–2018, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 7. Open-Loop Gain and Phase vs Frequency



図 8. Closed-Loop Gain vs Frequency



図 9. CMRR and PSRR vs Frequency (Referred to Input)



図 10. Input Voltage Noise Spectral Density



図 11. Voltage Noise vs Source Resistance



図 12. 0.1-Hz to 10-Hz Voltage Noise

Copyright © 2017–2018, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 13. Maximum Output Voltage vs Frequency



図 14. Open-Loop Output Impedance vs Frequency



G = 1

図 15. Phase Margin vs Capacitive Load



G = 1 10-mV input step

図 16. Overshoot vs Capacitive Load



G = –1 10-mV input step

図 17. Overshoot vs Capacitive Load



V_{OUT} = 3 V_{RMS} 80-kHz bandwidth

図 18. THD + N Ratio vs Frequency

Copyright © 2017–2018, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



V_{OUT} = 3 V_{RMS} R_L = 600 Ω 80-kHz bandwidth

図 19. THD + N Ratio vs Frequency



V_{OUT} = 3 V_{RMS} 500-kHz bandwidth

図 20. THD + N Ratio vs Frequency



V_{OUT} = 3 V_{RMS} G = 1 80-kHz bandwidth

図 21. Distortion Harmonics vs Frequency



V_{OUT} = 3 V_{RMS} G = –1 80-kHz bandwidth

図 22. Distortion Harmonics vs Frequency



f = 1 kHz 80-kHz bandwidth

図 23. THD + N Ratio vs Output Amplitude



f = 1 kHz R_L = 600 Ω 80-kHz bandwidth

図 24. THD + N Ratio vs Output Amplitude

Copyright © 2017–2018, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 25. Intermodulation Distortion vs Output Amplitude



図 26. Channel Separation vs Frequency



図 27. 1-kHz Output Spectrum



図 28. 20-kHz Output Spectrum



図 29. Small-Signal Step Response



図 30. Small-Signal Step Response

Copyright © 2017–2018, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 31. Large-Signal Step Response



図 32. Large-Signal Step Response



図 33. Settling Time



図 34. Input Offset Voltage vs Temperature



図 35. Input Offset Voltage vs Common-Mode Voltage



図 36. CMRR vs Temperature

Copyright © 2017–2018, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 37. PSRR vs Temperature



図 38. Open-Loop Gain vs Temperature



図 39. Input Bias and Offset Current vs Temperature



図 40. I_B vs Common-Mode Voltage



図 41. I_B vs Common-Mode Voltage



図 42. Supply Current vs Temperature

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 43. Supply Current vs Supply Voltage



図 44. Open-Loop Gain vs Output Voltage



図 45. Open-Loop Gain vs Output Voltage



図 46. Output Voltage vs Output Current



図 47. Output Voltage vs Output Current



図 48. Short-Circuit Current vs Temperature

Copyright © 2017–2018, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±18 V, and R_L = 2 kΩ (unless otherwise noted)



図 49. Negative Overload Recovery



図 50. Positive Overload Recovery



図 51. No Phase Reversal

Copyright © 2017–2018, Texas Instruments Incorporated

7 Detailed Description

7.1 Overview

The OPA169x amplifiers are unity-gain stable, dual and quad op amps with low noise. The *Functional Block Diagram* shows a simplified schematic of the OPA169x (one channel shown). The device consists of a very low noise input stage with a folded cascode and a rail-to-rail output stage. A proprietary distortion reduction technology allows the OPA169x family of amplifiers to achieve significantly lower distortion than other op amps that consume the equal or greater power supply current.

7.2 Functional Block Diagram



7.3 Feature Description

7.3.1 Distortion Reduction

Amplifiers use feedback to reduce the amount of distortion they introduce to the signal path. Increasing the amount of feedback available for distortion reduction typically requires an increase in the power supply current of the amplifier. This is not acceptable in low-power amplifiers targeting applications that require low distortion.



図 53. Comparison of THD + N vs Frequency for Multiple Low-Power Amplifiers

Copyright © 2017–2018, Texas Instruments Incorporated

Feature Description (continued)

The OPA169x family of amplifiers uses a proprietary technology to reduce signal distortion that does not increase the power supply current. The distortion cancellation technique reduces odd-order harmonic distortion, which is produced by the input transistor pair of the amplifier. As 図 53 shows, the impact to THD + N is significant, especially at high frequencies where the OPA169x devices exhibit over 30-dB lower distortion than competitor amplifiers at similar power supply current levels.

7.3.2 Phase Reversal Protection

The OPA169x family has internal phase-reversal protection. Many op amps exhibit phase reversal when the input is driven beyond the linear common-mode range. This condition is most often encountered in noninverting circuits when the input is driven beyond the specified common-mode voltage range, reverses the output into the opposite rail. The input of the OPA169x prevents phase reversal with excessive common-mode voltage. Instead, the appropriate rail limits the output voltage. This performance is shown in 図 54.



図 54. Output Waveform Devoid of Phase Reversal During an Input Overdrive Condition

7.3.3 Electrical Overstress

Designers often ask questions about the capability of an operational amplifier to withstand electrical overstress. These questions tend to focus on the device inputs, but can involve the supply voltage pins or even the output pin. Each of these different pin functions have electrical stress limits determined by the voltage breakdown characteristics of the particular semiconductor fabrication process and specific circuits connected to the pin. Additionally, internal electrostatic discharge (ESD) protection is built into these circuits to protect them from accidental ESD events both before and during product assembly.

A good understanding of this basic ESD circuitry and the relevance to an electrical overstress event is helpful. 図 55 illustrates the ESD circuits contained in the OPA169x (indicated by the dashed line area). The ESD protection circuitry involves several current-steering diodes connected from the input and output pins and routed back to the internal power-supply lines, where the diodes meet at an absorption device internal to the operational amplifier. This protection circuitry is intended to remain inactive during normal circuit operation.

Copyright © 2017–2018, Texas Instruments Incorporated

Feature Description (continued)



Copyright © 2016, Texas Instruments Incorporated

図 55. Equivalent Internal ESD Circuitry Relative to a Typical Circuit Application

An ESD event produces a short-duration, high-voltage pulse that is transformed into a short-duration, high-current pulse when discharging through a semiconductor device. The ESD protection circuits are designed to provide a current path around the operational amplifier core to prevent damage. The energy absorbed by the protection circuitry is then dissipated as heat.

When an ESD voltage develops across two or more amplifier device pins, current flows through one or more steering diodes. Depending on the path that the current takes, the absorption device can activate. The absorption device has a trigger, or threshold voltage, that is above the normal operating voltage of the OPA169x but below the device breakdown voltage level. When this threshold is exceeded, the absorption device quickly activates and clamps the voltage across the supply rails to a safe level.

When the operational amplifier connects into a circuit (see 図 55), the ESD protection components are intended to remain inactive and are not involved in the application-circuit operation. However, circumstances may arise where an applied voltage exceeds the operating voltage range of a given pin. If this condition occurs, there is a risk that some internal ESD protection circuits can turn on and conduct current. Any such current flow occurs through steering-diode paths and rarely involves the absorption device.

図 55 shows a specific example where the input voltage (V_{IN}) exceeds the positive supply voltage (V+) by 500 mV or more. Much of what happens in the circuit depends on the supply characteristics. If V+ can sink the current, one of the upper input steering diodes conducts and directs current to V+. Excessively high current levels can flow with increasingly higher V_{IN}. As a result, the data sheet specifications recommend that applications limit the input current to 10 mA.

If the supply is not capable of sinking the current, V_{IN} can begin sourcing current to the operational amplifier and then take over as the source of positive supply voltage. The danger in this case is that the voltage can rise to levels that exceed the operational amplifier absolute maximum ratings.

Copyright © 2017–2018, Texas Instruments Incorporated

Feature Description (continued)

Another common question involves what happens to the amplifier if an input signal is applied to the input when the power supplies (V+ or V–) are at 0 V. This question depends on the supply characteristic when at 0 V, or at a level below the input signal amplitude. If the supplies appear as high impedance, then the input source supplies the operational amplifier current through the current-steering diodes. This state is not a normal bias condition; most likely, the amplifier does not operate normally. If the supplies are low impedance, then the current through the steering diodes can become quite high. The current level depends on the ability of the input source to deliver current and any resistance in the input path.

If there is any uncertainty about the ability of the supply to absorb this current, add external Zener diodes to the supply pins; see 図 55. Select the Zener voltage so that the diode does not turn on during normal operation. However, the Zener voltage must be low enough so that the Zener diode conducts if the supply pin begins to rise above the safe operating, supply voltage level.

7.4 Device Functional Modes

7.4.1 Operating Voltage

The OPA169x series op amps operate from ±1.75 V to ±18 V supplies while maintaining excellent performance. The OPA169x series operates with as little as 3.5 V between the supplies and with up to 36 V between the supplies. However, some applications do not require equal positive and negative output voltage swing. With the OPA169x series, power-supply voltages are not required to be equal. For example, the positive supply can be set to 25 V with the negative supply at –5 V.

In all cases, the common-mode voltage must be maintained within the specified range. Key parameters are assured over the specified temperature range of T_A = –40°C to 125°C. Parameters that vary significantly with operating voltage or temperature are shown in the *Typical Characteristics*.

Copyright © 2017–2018, Texas Instruments Incorporated

8 Application and Implementation

注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

8.1.1 Capacitive Loads

The dynamic characteristics of the OPA169x amplifiers are optimized for commonly encountered gains, loads, and operating conditions. The combination of low closed-loop gain and high capacitive loads decreases the phase margin of the amplifier and can lead to gain peaking or oscillations. As a result, heavier capacitive loads must be isolated from the output. Add a small resistor (R_S equal to 50 Ω, for example) in series with the output to isolate heavier capacitive loads.

8.1.2 Noise Performance

図 56 shows the total circuit noise for varying source impedances with the operational amplifier in a unity-gain configuration (with no feedback resistor network and therefore no additional noise contributions). The op amp itself contributes a voltage noise component and a current noise component. The voltage noise is commonly modeled as a time-varying component of the offset voltage. The current noise is modeled as the time-varying component of the input bias current and reacts with the source resistance to create a voltage component of noise. Therefore, the lowest noise op amp for a given application depends on the source impedance. For low source impedance, current noise is negligible, and voltage noise generally dominates. The OPA169x has low voltage noise and low current noise. As a result, the current noise contribution of the OPA169x series is negligible for source impedances less than 100 kΩ.

図 56 shows the calculation of the total circuit noise, with these parameters:

- e_n = voltage noise
- I_n = current noise
- R_S = source impedance
- k = Boltzmann's constant = 1.38×10^{-23} J/K
- T = temperature in degrees Kelvin (K)

For more details on calculating noise, see *Basic Noise Calculations*.



図 56. Noise Performance of the OPA169x in a Unity-Gain Buffer Configuration

Copyright © 2017–2018, Texas Instruments Incorporated

Application Information (continued)

8.1.3 Basic Noise Calculations

Low-noise circuit design requires careful analysis of all noise sources. External noise sources can dominate in many cases; consider the effect of source resistance on overall op amp noise performance. Total noise of the circuit is the root-sum-square combination of all noise components.

The resistive portion of the source impedance produces thermal noise proportional to the square root of the resistance. This function is plotted in 図 56. The source impedance is typically fixed; consequently, select the op amp and the feedback resistors to minimize the respective contributions to the total noise.

図 57 shows noninverting **(A)** and inverting **(B)** op amp circuit configurations with gain. In circuit configurations with gain, the feedback network resistors contribute noise. In general, the current noise of the op amp reacts with the feedback resistors to create additional noise components.

The selected feedback resistor values make these noise sources negligible. Low impedance feedback resistors load the output of the amplifier. The equations for total noise are shown for both configurations.

(A) Noise in Noninverting Gain Configuration



Noise at the output is given as E_O, where

$$(1)\quad E_O = \left(1+\frac{R_2}{R_1}\right)\cdot\sqrt{(e_S)^2+(e_N)^2+\left(e_{R_1\|R_2}\right)^2+(i_N\cdot R_S)^2+\left(i_N\cdot\left[\frac{R_1\cdot R_2}{R_1+R_2}\right]\right)^2}\quad [\,V_{RMS}\,]$$

$$(2)\quad e_S = \sqrt{4\cdot k_B\cdot T(K)\cdot R_S}\quad \left[\frac{V}{\sqrt{Hz}}\right]$$ Thermal noise of R_S

$$(3)\quad e_{R_1\|R_2} = \sqrt{4\cdot k_B\cdot T(K)\cdot\left[\frac{R_1\cdot R_2}{R_1+R_2}\right]}\quad \left[\frac{V}{\sqrt{Hz}}\right]$$ Thermal noise of $R_1 \| R_2$

$$(4)\quad k_B = 1.38065\cdot 10^{-23}\quad \left[\frac{J}{K}\right]$$ Boltzmann Constant

$$(5)\quad T(K) = 237.15 + T(°C)\quad [\,K\,]$$ Temperature in kelvins

(B) Noise in Inverting Gain Configuration



Noise at the output is given as E_O, where

$$(6)\quad E_O = \left(1+\frac{R_2}{R_S+R_1}\right)\cdot\sqrt{(e_N)^2+\left(e_{R_1+R_S\|R_2}\right)^2+\left(i_N\cdot\left[\frac{(R_S+R_1)\cdot R_2}{R_S+R_1+R_2}\right]\right)^2}\quad [\,V_{RMS}\,]$$

$$(7)\quad e_{R_1+R_S\|R_2} = \sqrt{4\cdot k_B\cdot T(K)\cdot\left[\frac{(R_S+R_1)\cdot R_2}{R_S+R_1+R_2}\right]}\quad \left[\frac{V}{\sqrt{Hz}}\right]$$ Thermal noise of $(R_1 + R_S) \| R_2$

$$(8)\quad k_B = 1.38065\cdot 10^{-23}\quad \left[\frac{J}{K}\right]$$ Boltzmann Constant

$$(9)\quad T(K) = 237.15 + T(°C)\quad [\,K\,]$$ Temperature in kelvins

Copyright © 2017, Texas Instruments Incorporated

(1) e_N is the voltage noise of the amplifier. For the OPAx169x series of operational amplifiers, e_N = 4.2 nV/√Hz at 1 kHz.
(2) i_N is the current noise of the amplifier. For the OPA169x series of operational amplifiers, i_N = 370 fA/√Hz at 1 kHz.
(3) For additional resources on noise calculations, see *TI's Precision Labs Series*.

図 57. Noise Calculation in Gain Configurations

Application Information (continued)

8.1.4 EMI Rejection

The electromagnetic interference (EMI) rejection ratio, or EMIRR, describes the EMI immunity of operational amplifiers. An adverse effect that is common to many op amps is a change in the offset voltage as a result of RF signal rectification. An op amp that is more efficient at rejecting this change in offset as a result of EMI has a higher EMIRR and is quantified by a decibel value. Measuring EMIRR can be performed in many ways, but this section provides the EMIRR IN+, which specifically describes the EMIRR performance when the RF signal is applied to the noninverting input pin of the op amp. In general, only the noninverting input is tested for EMIRR for the following three reasons:

- Op amp input pins are known to be the most sensitive to EMI, and typically rectify RF signals better than the supply or output pins.
- The noninverting and inverting op amp inputs have symmetrical physical layouts and exhibit approximately matching EMIRR performance
- EMIRR is easier to measure on noninverting pins than on other pins because the noninverting input pin can be isolated on a PCB. This isolation allows the RF signal to be applied directly to the noninverting input terminal with no complex interactions from other components or connecting PCB traces.

  High-frequency signals conducted or radiated to any pin of the operational amplifier result in adverse effects, as the amplifier does not have sufficient loop gain to correct for signals with spectral content outside its bandwidth. Conducted or radiated EMI on inputs, power supply, or output may result in unexpected DC offsets, transient voltages, or other unknown behavior. Take care to properly shield and isolate sensitive analog nodes from noisy radio signals and digital clocks and interfaces.

  The EMIRR IN+ of the OPA169x amplifiers is plotted versus frequency as shown in 図 58. If available, any dual and quad op amp device versions have nearly similar EMIRR IN+ performance. The OPA169x unity-gain bandwidth is 5.1 MHz. EMIRR performance below this frequency denotes interfering signals that fall within the op amp bandwidth.

See *EMI Rejection Ratio of Operational Amplifiers*, available for download from www.ti.com.



図 58. OPA169x EMIRR IN+

Copyright © 2017–2018, Texas Instruments Incorporated

表 1 lists the EMIRR IN+ values for the OPA169x at particular frequencies commonly encountered in real-world applications. Applications listed in 表 1 may be centered on or operated near the particular frequency shown. This information may be of special interest to designers working with these types of applications, or working in other fields likely to encounter RF interference from broad sources, such as the industrial, scientific, and medical (ISM) radio band.

表 1. OPA169x EMIRR IN+ for Frequencies of Interest

FREQUENCY	APPLICATION OR ALLOCATION	EMIRR IN+
400 MHz	Mobile radio, mobile satellite, space operation, weather, radar, ultra-high frequency (UHF) applications	45.9 dB
900 MHz	Global system for mobile communications (GSM) applications, radio communication, navigation, GPS (to 1.6 GHz), GSM, aeronautical mobile, UHF applications	50.2 dB
1.8 GHz	GSM applications, mobile personal communications, broadband, satellite, L-band (1 GHz to 2 GHz)	70.7 dB
2.4 GHz	802.11b, 802.11g, 802.11n, Bluetooth®, mobile personal communications, industrial, scientific and medical (ISM) radio band, amateur radio and satellite, S-band (2 GHz to 4 GHz)	76.1 dB
3.6 GHz	Radiolocation, aero communication and navigation, satellite, mobile, S-band	94.1 dB
5 GHz	802.11a, 802.11n, aero communication and navigation, mobile communication, space and satellite operation, C-band (4 GHz to 8 GHz)	104.5 dB

8.1.5 EMIRR +IN Test Configuration

図 59 shows the circuit configuration for testing the EMIRR IN+. An RF source connects to the op amp noninverting input pin using a transmission line. The op amp is configured in a unity-gain buffer topology with the output connected to a low-pass filter (LPF) and a digital multimeter (DMM). A large impedance mismatch at the op amp input causes a voltage reflection; however, this effect is characterized and accounted for when determining the EMIRR IN+. A multimeter samples and measures the resulting DC offset voltage. The LPF isolates the multimeter from residual RF signals that may interfere with multimeter accuracy.



図 59. EMIRR +IN Test Configuration

8.2 Typical Application

The low power consumption, noise, and distortion of the OPA169x family of audio operational amplifiers make the family a viable option for a number of analog audio circuits. 図 60 shows one circuit example, which shows a preamplifier circuit that is designed for high-performance electret microphones that use a 3-wire interface.



Copyright © 2017, Texas Instruments Incorporated

図 60. Low-Noise Preamplifier for 3-Wire Electret Microphones

8.2.1 Design Requirements

- Maximum Input Sound Pressure Level (SPL): 120 dB
- –3-dB Bandwidth: 20 Hz to 20 kHz
- Signal-to-Noise Ratio: > 75 dB
- Power Supply Voltage: ± 5 V
- Power Supply Current: < 1.5 mA

8.2.2 Detailed Design Procedure

The selected design requirements represent a high-performance wireless microphone application. Wireless microphones typically use an electret microphone element, an analog pre-amplifier circuit, and transmit circuitry which may use analog or digital methods of transmission. Because these devices are battery-powered, all circuitry must be designed to consume as little power as possible, while still achieving very high audio performance. The performance specifications for the microphone used in this design are shown in 表 2. This microphone element uses a 3-wire connection scheme with separate connections for power, ground, and signal. The microphone data sheet specifies that the signal line is terminated with a recommended 5.6-kΩ resistance and a 5-V supply.

表 2. Primo EM-173 Microphone Specifications

PARAMETER	VALUE
Sensitivity	–37 dBV
Output impedance	600 Ω
Signal-to-noise ratio (SNR)	80 dB
Maximum input sound pressure level	135 dB
Operating voltage	5 V (3 V – 10 V)
Operating current	600 µA

R1, C1, and R2 provide the correct termination impedance for the microphone and AC-couple the microphone signal to the amplifier input. R2 is selected with a large value (100 kΩ) so that a smaller AC-coupling capacitor can be used (C1). The high-pass corner frequency produced by C1 and R2 must be set to 20 Hz using 式 1:

$$20\ \text{Hz} = \frac{1}{2 \cdot \pi \cdot R_2 \cdot C_1} = \frac{1}{2 \cdot \pi \cdot 100\ \text{k}\Omega \cdot C_1} \rightarrow C_1 = 79.6\ \text{nF} \rightarrow 100\ \text{nF} \quad (1)$$

Copyright © 2017–2018, Texas Instruments Incorporated

R1 and R2 are in parallel for frequencies above 20 Hz. Therefore, select the value of R1 so that when in parallel with R2, the combination results in a 5.6-kΩ resistance as specified in the microphone data sheet. 式 2 calculates R1.

$$5.6\ \text{k}\Omega = \frac{R_1 \cdot R_2}{R_1 + R_2} = \frac{R_1 \cdot 100\ \text{k}\Omega}{R_1 + 100\ \text{k}\Omega} \rightarrow R_1 = 5.9\ \text{k}\Omega \tag{2}$$

R3 and C2 form a low-pass filter to prevent the amplification of electromagnetic interference (EMI) signals. 式 3 shows the corner frequency of this EMI filter.

$$f_{-3\text{dB}} = \frac{1}{2 \cdot \pi \cdot R_3 \cdot C_2} = \frac{1}{2 \cdot \pi \cdot 100\ \Omega \cdot 100\ \text{pF}} = 15.9\ \text{MHz} \tag{3}$$

The input bias current of the OPA1692 through the 100-kΩ input resistor (R2) and can potentially cause a large offset voltage to appear at the output of the amplifier. One solution to this problem is to match the DC resistance of the circuit at each input of the amplifier. R4 and C3 accomplish this goal by providing a DC-feedback path for the amplifier (R4) which has the same resistance as the input resistor (R2). Capacitor C3 serves two functions. First, at low-frequencies this capacitor is effectively an open circuit and therefore the gain of the amplifier is 1, which reduces DC offsets at the output. At high frequencies where the impedance of the capacitor is low, the feedback network of R5, R6, and C4 determine the gain of the amplifier.

The nominal gain of the preamplifier circuit is calculated by considering the output of the microphone at the maximum input SPL. For this design, a maximum input SPL of 120 dB or [20 pascals (Pa)] is specified. The microphone sensitivity is shown as –37 dBV, measured at 1-Pa air pressure. The output signal of the microphone at 20-Pa air pressure can be calculated by converting the –37 dBV sensitivity specification to mV per pascal of air pressure as shown in 式 4:

$$V_{\text{OUT(MIC)}} = 20\ \text{Pa} \times 10^{\left(\frac{-37\ \text{dBV}}{20}\right)} = 282.5\ \text{mV}_{\text{RMS}} = 399.5\ \text{mVp} \tag{4}$$

The linear output voltage range of the OPA1692 extends to within 200 mV of each power supply. Therefore, on a ±5-V power supply, the linear output voltage range is ±4.8 V. The linear output voltage range of the amplifier and the maximum output signal level of the microphone determine the gain of the amplifier, as shown in 式 5:

$$G = \frac{V_{\text{OUT(OPA1692)}}}{V_{\text{OUT(MIC)}}} = \frac{4.8\ V_P}{399.5\ \text{mV}_P} = 12.015\ (21.6\ \text{dB}) = 1 + \frac{R_5}{R_6} \tag{5}$$

Selecting values of 1.1 kΩ and 100 Ω for R5 and R6, respectively, produce a nominal gain of 12 for the circuit, allowing the full linear output swing of the amplifier to be used for the maximum input SPL. The feedback capacitor (C4) limits the gain of the circuit at high frequencies beyond the range of human hearing. 式 6 shows the high-pass corner frequency that capacitor C4 produces:

$$20\ \text{kHz} = \frac{1}{2 \cdot \pi \cdot R_5 \cdot C_4} = \frac{1}{2 \cdot \pi \cdot 1.1\ \text{k}\Omega \cdot C_4} \rightarrow C_4 = 7.23\ \text{nF} \rightarrow 6.8\ \text{nF} \tag{6}$$

Lastly, by the low-frequency bandwidth requirement for the design and the gain determines the value of C3. The high-pass corner frequency produced by this capacitor is affected by resistors R5 and R6 as shown in 式 7:

$$C_3 = \left(1 + \frac{R_5}{R_6}\right) \frac{1}{2 \cdot \pi \cdot R_4 \cdot f_{-3\text{dB}}} = (12) \frac{1}{2 \cdot \pi \cdot 100\ \text{k}\Omega \cdot 20\ \text{Hz}} \rightarrow C_3 = 955\ \text{nF} \rightarrow 1\ \mu\text{F} \tag{7}$$

8.2.3 Application Curves

表 3 lists the performance of the preamplifier circuit in 図 60. The total power supply current of the circuit is a combination of the 600 µA consumed by the microphone element itself and the 650 µA power-supply current of the OPA1692. 図 61 shows the frequency response of the circuit. Comparing the output signal level of the microphone for a 1-Pa input signal level to the A-weighted noise of the preamplifier circuit and microphone determines the SNR of the circuit. For a 1-Pa input sound level, the microphone produces a 14.13 mV_{RMS} signal. The microphone has an SNR of 80 dB, which results in a RMS noise voltage of 1.41 μV_{RMS}. The input-referred A-weighted noise voltage of the preamplifier circuit is 600.6 nV_{RMS}. The microphone and preamplifier noise must be combined as a root sum of squares, which results in a total RMS noise voltage of 1.53 μV_{RMS} and a total circuit SNR of 79.3 dB. By selecting the OPA1692 for this design, this circuit achieves a high level of performance with low power consumption.

Copyright © 2017–2018, Texas Instruments Incorporated

表 3. Comparison of Design Requirements and Results

SPECIFICATION	DESIGN REQUIREMENT	DESIGN RESULT
Gain	12 V/V or 21.6 dB (120 dB Maximum Input SPL)	11.79 V/V or 21.43 dB
–3-dB bandwidth	20 Hz to 20 kHz	24 Hz to 21 kHz
Signal-to-noise ratio	> 75 dB	79.3 dB
Power supply current (microphone and amplifier circuit)	< 1.5 mA	1.25 mA



図 61. Frequency Response of the Low-Noise Preamplifier for 3-Wire Electret Microphones

Copyright © 2017–2018, Texas Instruments Incorporated

8.3 Other Application Examples

8.3.1 Two-Wire Electret Microphone Preamplifier

The circuit in 図 60 can be modified to accommodate two-wire electret microphones, as shown in 図 62. In two-wire configurations, there is no resistor in series with the source of the internal JFET of the microphone. The audio signal is output as a varying voltage across the biasing resistor (2.2 kΩ in 図 62) of the capsule. The preamplifier input is AC-coupled to the biasing resistor through a 0.1-µF capacitor and 47-kΩ input resistor.



図 62. Two-Wire Electret Microphone Preamplifier

Other Application Examples (continued)

8.3.2 Battery-Powered Preamplifier for Professional Microphones

図 63 shows a preamplifier designed for portable applications that require low-noise, high common-mode rejection, and long battery life. Both channels of the OPA1692 are configured as a two-op amp instrumentation amplifier with a variable gain from 6 to 40 dB. An array of 1-kΩ resistors is recommended for the feedback network because the excellent matching of these resistors ensure high common-mode rejection in the circuit. An OPA171 is configured as a buffered power supply divider to provide a biasing voltage to the circuit, allowing the system to operate properly on a single 9-V battery. The additional components at the OPA1692 inputs are for phantom power, EMI, and ESD protection. The circuit consumes approximately 2 mA of quiescent power supply current.



図 63. Preamplifier for Professional Microphones Powered from a 9-V Battery

Copyright © 2017–2018, Texas Instruments Incorporated

9 Power Supply Recommendations

The OPA169x are specified for operation from 3.5 V to 36 V (±1.75 V to ±18 V); many specifications apply from –40°C to 125°C. Parameters that can exhibit significant variance with regard to operating voltage or temperature are shown in the *Typical Characteristics* section. Applications with noisy or high-impedance power supplies require decoupling capacitors close to the device pins. In most cases, 0.1-µF capacitors are adequate.

10 Layout

10.1 Layout Guidelines

For best operational performance of the device, use good printed-circuit board (PCB) layout practices, including:

- Noise can propagate into analog circuitry through the power pins of the circuit as a whole and of op amp itself. Bypass capacitors are used to reduce the coupled noise by providing low-impedance power sources local to the analog circuitry.
  - Connect low-ESR, 0.1-µF ceramic bypass capacitors between each supply pin and ground, placed as close as possible to the device. A single bypass capacitor from V+ to ground is applicable for single-supply applications.
- Separate grounding for analog and digital portions of circuitry is one of the simplest and most-effective methods of noise suppression. One or more layers on multilayer PCBs are usually devoted to ground planes. A ground plane helps distribute heat and reduces electromagnetic interference (EMI) noise pickup. Physically separate digital and analog grounds, observing the flow of the ground current.
- To reduce parasitic coupling, run the input traces as far away as possible from the supply or output traces. If these traces cannot be kept separate, crossing the sensitive trace perpendicular is much better as opposed to in parallel with the noisy trace.
- Place the external components as close as possible to the device. As shown in 図 64, keeping R_F and R_G close to the inverting input minimizes parasitic capacitance.
- Keep the length of input traces as short as possible. Always remember that the input traces are the most sensitive part of the circuit.
- Consider a driven, low-impedance guard ring around the critical traces. A guard ring can significantly reduce leakage currents from nearby traces that are at different potentials.
- For best performance, TI recommends cleaning the PCB following assembly.
- Any precision integrated circuit can experience performance shifts resulting from moisture ingress into the plastic package. Following any aqueous PCB cleaning process, TI recommends baking the PCB assembly to remove moisture introduced into the device packaging during the cleaning process. A low-temperature, post-cleaning bake at 85°C for 30 minutes is sufficient for most circumstances.

Copyright © 2017–2018, Texas Instruments Incorporated

10.2 Layout Example



(Schematic Representation)



図 64. Operational Amplifier Board Layout for Noninverting Configuration

10.3 Power Dissipation

The OPA169x series op amps are capable of driving 2-kΩ loads with a power-supply voltage up to ±18 V and full operating temperature range. Internal power dissipation increases when operating at high supply voltages. Copper leadframe construction used in the OPA169x series op amps improves heat dissipation compared to conventional materials. Circuit board layouts minimize junction temperature rise. Wide copper traces help dissipate the heat by acting as an additional heat sink. Temperature rise is further minimized by soldering the devices to the circuit board rather than using a socket.

Copyright © 2017–2018, Texas Instruments Incorporated

11 デバイスおよびドキュメントのサポート

11.1 デバイス・サポート

11.1.1 開発サポート

11.1.1.1 TINA-TI™ (無料のダウンロード・ソフトウェア)

TINA™は、SPICEエンジンをベースにした単純かつ強力な、使いやすい回路シミュレーション・プログラムです。また、TINA-TI™は、TINAソフトウェアの完全な機能を持つ無償バージョンで、パッシブ・モデルとアクティブ・モデルに加えて、マクロ・モデルのライブラリがプリロードされています。TINA-TIには従来型のDC、過渡、および周波数ドメインのSPICEによる分析と、追加の設計機能が搭載されています。

TINA-TIはAnalog eLab Design Centerから無料でダウンロードでき、ユーザーが結果をさまざまな方法でフォーマットできる、広範な後処理機能を備えています。仮想計測器により、入力波形を選択し、回路ノード、電圧、および波形をプローブして、動的なクイック・スタート・ツールを作成できます。

注

これらのファイルを使用するには、TINA ソフトウェア (DesignSoft™製) またはTINA-TIソフトウェアがインストールされている必要があります。TINA-TIフォルダから、無料のTINA-TIソフトウェアをダウンロードしてください。

11.1.1.2 DIPアダプタ評価モジュール

DIPアダプタ評価モジュール・ツールを使用すると、小さな表面実装ICのプロトタイプを簡単に、低コストで作成できます。この評価ツールは、DまたはU(SOIC-8)、PW(TSSOP-8)、DGK(VSSOP-8)、DBV(SOT23-6、SOT23-5、およびSOT23-3)、DCK(SC70-6およびSC70-5)、およびDRL(SOT563-6)のTIパッケージに対応しています。DIPアダプタ評価モジュールは、ターミナル・ストリップとともに使用することも、既存の回路へ直接接続することもできます。

11.1.1.3 ユニバーサル・オペアンプ評価モジュール

ユニバーサル・オペアンプ評価モジュールは一連の汎用のブランクアウト回路基板で、各種のICパッケージ・タイプ向けの回路のプロトタイプ作成を容易にします。この評価モジュール基板は、多くの異なる回路を簡単かつ迅速に構築できるように設計されています。5つのモデルが提供されており、それぞれのモデルは特定のパッケージ・タイプを対象としています。PDIP、SOIC、VSSOP、TSSOP、SOT-23パッケージがすべてサポートされています。

注

これらの基板には部品が搭載されていないため、ユーザーが独自のICを実装する必要があります。ユニバーサル・オペアンプ評価モジュールを注文するときに、オペアンプ・デバイスのサンプルをいくつか要求することをお勧めします。

11.1.1.4 スマートアンプ・スピーカーの特性付け基板評価モジュール

スマートアンプ・スピーカーの特性付け基板を、対応のTIスマートアンプおよびPurePathコンソール・ソフトウェアと組み合わせて使用すると、TIスマートアンプ製品使用中に、スピーカーの可動域、温度、その他のパラメータを測定できます。

11.1.1.5 TI Precision Designs

TI Precision Designsは、TIの高精度アナログ・アプリケーションの専門家により作成されたアナログ・ソリューションで、多くの有用な回路に関して、動作理論、コンポーネント選択、シミュレーション、完全なPCB回路図とレイアウト、部品表、性能測定結果を提供します。TI Precision Designsは、http://www.ti.com/ww/en/analog/precision-designs/からオンラインで入手できます。

11.1.1.6 WEBENCH® Filter Designer

WEBENCH® Filter Designerは単純で強力な、使いやすいアクティブ・フィルタ設計プログラムです。WEBENCH Filter Designerを使用すると、TIのベンダ・パートナーからのTI製オペアンプやパッシブ・コンポーネントを使用して、最適なフィルタ設計を作成できます。

Copyright © 2017–2018, Texas Instruments Incorporated

デバイス・サポート (continued)

WEBENCH® Filter Designerは、WEBENCH® Design CenterからWebベースのツールとして利用でき、包括的な複数段アクティブ・フィルタ・ソリューションをわずか数分で設計、最適化、シミュレーションできます。

11.2 ドキュメントのサポート

11.2.1 関連資料

以下に示すドキュメントはOPA169xの使用に関連しており、参照用にお勧めします。すべてのドキュメントは、特に記述のない限りwww.ti.comからダウンロードできます。

- *『アンプにおけるソース抵抗とノイズの考慮事項』*
- *『オペアンプの単一電源動作』*
- *『オペアンプの性能分析』*
- *『アンプのチューニング』*
- *『フィードバック・プロットによるオペアンプAC性能の定義』*
- *『業務用オーディオ向けのアクティブ・ボリューム・コントロール』*

11.3 関連リンク

表 4 に、クイック・アクセス・リンクの一覧を示します。カテゴリには、技術資料、サポートおよびコミュニティ・リソース、ツールとソフトウェア、およびサンプル注文またはご購入へのクイック・アクセスが含まれます。

表 4. 関連リンク

製品	プロダクト・フォルダ	ご注文はこちら	技術資料	ツールとソフトウェア	サポートとコミュニティ
OPA1692	ここをクリック	ここをクリック	ここをクリック	ここをクリック	ここをクリック

11.4 ドキュメントの更新通知を受け取る方法

ドキュメントの更新についての通知を受け取るには、ti.comのデバイス製品フォルダを開いてください。右上の隅にある「*通知を受け取る*」をクリックして登録すると、変更されたすべての製品情報に関するダイジェストを毎週受け取れます。変更の詳細については、修正されたドキュメントに含まれている改訂履歴をご覧ください。

11.5 コミュニティ・リソース

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™オンライン・コミュニティ ***TIのE2E (Engineer-to-Engineer) コミュニティ。エンジニア間の共同作業を促進するために開設されたものです。e2e.ti.comでは、他のエンジニアに質問し、知識を共有し、アイディアを検討して、問題解決に役立てることができます。***

設計サポート ***TIの設計サポート*** **役に立つE2Eフォーラムや、設計サポート・ ツールをすばやく見つけることができます。技術サポート用の連絡先情報も参照できます。**

11.6 商標

SoundPlus, TINA-TI, E2E are trademarks of Texas Instruments.
WEBENCH is a registered trademark of Texas Instruments.
Bluetooth is a registered trademark of Bluetooth SIG, Inc.
TINA, DesignSoft are trademarks of DesignSoft, Inc.
All other trademarks are the property of their respective owners.

11.7 静電気放電に関する注意事項

これらのデバイスは、限定的なESD（静電破壊）保護機能を内 蔵しています。保存時または取り扱い時は、MOSゲートに対す る静電破壊を防止するために、リード線同士をショートさせて おくか、デバイスを導電フォームに入れる必要があります。

Copyright © 2017–2018, Texas Instruments Incorporated

11.8 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

12 メカニカル、パッケージ、および注文情報

以降のページには、メカニカル、パッケージ、および注文に関する情報が記載されています。この情報は、そのデバイスについて利用可能な最新のデータです。このデータは予告なく変更されることがあり、ドキュメントが改訂される場合もあります。本データシートのブラウザ版を使用されている場合は、画面左側の説明をご覧ください。

Copyright © 2017–2018, Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
OPA1692ID	ACTIVE	SOIC	D	8	75	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	OP1692	Samples
OPA1692IDGKR	ACTIVE	VSSOP	DGK	8	2500	RoHS & Green	NIPDAUAG | SN	Level-2-260C-1 YEAR	-40 to 125	1692	Samples
OPA1692IDGKT	ACTIVE	VSSOP	DGK	8	250	RoHS & Green	NIPDAUAG | SN	Level-2-260C-1 YEAR	-40 to 125	1692	Samples
OPA1692IDR	ACTIVE	SOIC	D	8	2500	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	OP1692	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) **RoHS:** TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".
RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.
Green: TI defines "Green" to mean the content of Chlorine (Cl) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and

continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals.
TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
OPA1692IDGKR	VSSOP	DGK	8	2500	330.0	12.4	5.3	3.4	1.4	8.0	12.0	Q1
OPA1692IDGKT	VSSOP	DGK	8	250	330.0	12.4	5.3	3.4	1.4	8.0	12.0	Q1
OPA1692IDR	SOIC	D	8	2500	330.0	12.4	6.4	5.2	2.1	8.0	12.0	Q1

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
OPA1692IDGKR	VSSOP	DGK	8	2500	366.0	364.0	50.0
OPA1692IDGKT	VSSOP	DGK	8	250	366.0	364.0	50.0
OPA1692IDR	SOIC	D	8	2500	356.0	356.0	35.0

TUBE



*All dimensions are nominal

Device	Package Name	Package Type	Pins	SPQ	L (mm)	W (mm)	T (µm)	B (mm)
OPA1692ID	D	SOIC	8	75	506.6	8	3940	4.32



PACKAGE OUTLINE

D0008A

SOIC - 1.75 mm max height

SMALL OUTLINE INTEGRATED CIRCUIT



NOTES:

1. Linear dimensions are in inches [millimeters]. Dimensions in parenthesis are for reference only. Controlling dimensions are in inches. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed .006 [0.15] per side.
4. This dimension does not include interlead flash.
5. Reference JEDEC registration MS-012, variation AA.



LAND PATTERN EXAMPLE
EXPOSED METAL SHOWN
SCALE:8X



SOLDER MASK DETAILS

4214825/C 02/2019

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.

EXAMPLE STENCIL DESIGN

D0008A

SOIC - 1.75 mm max height

SMALL OUTLINE INTEGRATED CIRCUIT



SOLDER PASTE EXAMPLE
BASED ON .005 INCH [0.125 MM] THICK STENCIL
SCALE:8X

4214825/C 02/2019

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

DGK (S–PDSO–G8) PLASTIC SMALL–OUTLINE PACKAGE



4073329/E 05/06

NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 per end.
D. Body width does not include interlead flash. Interlead flash shall not exceed 0.50 per side.
E. Falls within JEDEC MO–187 variation AA, except interlead flash.

DGK (S–PDSO–G8) PLASTIC SMALL OUTLINE PACKAGE



NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Publication IPC–7351 is recommended for alternate designs.
D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC–7525 for other stencil recommendations.
E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.

重要なお知らせと免責事項

TI は、技術データと信頼性データ (データシートを含みます)、設計リソース (リファレンス· デザインを含みます)、アプリケーションや設計に関する各種アドバイス、Web ツール、安全性情報、その他のリソースを、欠陥が存在する可能性のある「現状のまま」提供しており、商品性および特定目的に対する適合性の黙示保証、第三者の知的財産権の非侵害保証を含むいかなる保証も、明示的または黙示的にかかわらず拒否します。

これらのリソースは、TI 製品を使用する設計の経験を積んだ開発者への提供を意図したものです。(1) お客様のアプリケーションに適した TI 製品の選定、(2) お客様のアプリケーションの設計、検証、試験、(3) お客様のアプリケーションに該当する各種規格や、その他のあらゆる安全性、セキュリティ、規制、または他の要件への確実な適合に関する責任を、お客様のみが単独で負うものとします。

上記の各種リソースは、予告なく変更される可能性があります。これらのリソースは、リソースで説明されている TI 製品を使用するアプリケーションの開発の目的でのみ、TI はその使用をお客様に許諾します。これらのリソースに関して、他の目的で複製することや掲載することは禁止されています。TI や第三者の知的財産権のライセンスが付与されている訳ではありません。お客様は、これらのリソースを自身で使用した結果発生するあらゆる申し立て、損害、費用、損失、責任について、TI およびその代理人を完全に補償するものとし、TI は一切の責任を拒否します。

TI の製品は、TI の販売条件、または ti.com やかかる TI 製品の関連資料などのいずれかを通じて提供する適用可能な条項の下で提供されています。TI がこれらのリソースを提供することは、適用される TI の保証または他の保証の放棄の拡大や変更を意味するものではありません。

お客様がいかなる追加条項または代替条項を提案した場合でも、TI はそれらに異議を唱え、拒否します。

郵送先住所：Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2023, Texas Instruments Incorporated