TPS784 300mA、低 I_Q、高 PSRR、高精度、低ドロップアウト電圧レギュレータ、イネーブル付き

1 特長

- 出力精度：
  - ±0.5% (標準値)、±0.75% (–40℃～+85℃)
- デバイスの接合部温度：–40℃～+150℃、T_J
- 入力電圧範囲：1.65V～6.0V
- 可変出力電圧範囲：1.2V～5.5V
- 低 I_Q：25µA (標準値)
- 非常に低いドロップアウト：
  - 3.3V_{OUT}、300mA 時に 115mV (最大値)
- 350µs の内部ソフトスタートにより突入電流を低減
- アクティブ出力放電
- パッケージ：5 ピン SOT-23

2 アプリケーション

- ホーム・シアターおよびエンターテインメント
- ネットワーク接続の周辺機器とプリンタ
- TV アプリケーション
- ビル・オートメーション
- 医療用アプリケーション

3 概要

TPS784 は、静止電流が小さい可変 300mA 超低ドロップアウト・レギュレータ (LDO) です。このデバイスは、小型の 5 ピン、2.9mm × 1.6mm、SOT-23 パッケージで供給され、優れたラインおよび負荷過渡性能を備えています。

出力ノイズが小さく PSRR 特性が優れているため、このデバイスは電力の制約が厳しいアナログ負荷に適しています。TPS784 は、1.65V～6.0V の入力電圧範囲に対応し、出力範囲を 1.2V～5.5V に可変できるため、柔軟なポスト・レギュレーションに対応できます。

TPS784 は、過電流条件の際に消費電力を低減するため、フォールドバック電流制限機能を備えています。EN 入力は、システムの電源シーケンス要件を満たすのに役立ちます。内部ソフトスタートにより、突入電流が小さい制御された起動を実現できるため、小さな入力容量を使用できます。

TPS784 は、ディセーブル時に出力負荷を迅速に放電するため、アクティブ・プルダウン回路を備えています。

製品情報

部品番号(1) (1 ページ)	パッケージ	本体サイズ (公称)
TPS784	SOT-23 (5)	2.90mm × 1.60mm

(1) 利用可能なすべてのパッケージについては、このデータシートの末尾にある注文情報を参照してください。



ドロップアウトと I_{OUT} との関係



5.0V での出力精度と I_{OUT} との関係

英語版の TI 製品についての情報を翻訳したこの資料は、製品の概要を確認する目的で便宜的に提供しているものです。該当する正式な英語版の最新情報は、www.ti.com で閲覧でき、その内容が常に優先されます。TI では翻訳の正確性および妥当性につきましては一切保証いたしません。実際の設計などの前には、必ず最新版の英語版をご参照くださいますようお願いいたします。

Table of Contents

1 特長.....1
2 アプリケーション.....1
3 概要.....1
4 Revision History.....2
5 Pin Configuration and Functions.....3
6 Specifications.....4
6.1 Absolute Maximum Ratings.....4
6.2 ESD Ratings.....4
6.3 Recommended Operating Conditions.....5
6.4 Thermal Information.....5
6.5 Electrical Characteristics.....6
6.6 Typical Characteristics.....8
7 Detailed Description.....14
7.1 Overview.....14
7.2 Functional Block Diagram.....14
7.3 Feature Description.....14
7.4 Device Functional Modes.....17
8 Application and Implementation.....18
8.1 Application Information.....18
8.2 Typical Application.....24
9 Power Supply Recommendations.....25
10 Layout.....26
10.1 Layout Guidelines.....26
10.2 Layout Example.....26
11 Device and Documentation Support.....27
11.1 Device Support.....27
11.2 Documentation Support.....27
11.3 Receiving Notification of Documentation Updates.....27
11.4 Support Resources.....27
11.5 Trademarks.....27
11.6 Electrostatic Discharge Caution.....27
11.7 Glossary.....27
12 Mechanical, Packaging, and Orderable Information.....27

4 Revision History

資料番号末尾の英字は改訂を表しています。その改訂履歴は英語版に準じています。

Changes from Revision * (August 2020) to Revision A (October 2020)	Page
• ドキュメントのタイトルを変更	1
• 文書全体にわたって表と図の採番方法を更新	1

DRAFT ONLY
TI Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

5 Pin Configuration and Functions



図 5-1. DBV Package, 5-Pin SOT-23, Top View

表 5-1. Pin Functions

PIN		I/O	DESCRIPTION
NAME	NO.		
EN	3	Input	Enable pin. Driving this pin to logic high enables the device; driving this pin to logic low disables the device. Do not float this pin. If not used, connect EN to IN.
FB	4	Input	Feedback pin. Input to the control-loop error amplifier. This pin is used to set the output voltage of the device with the use of external resistors. Do not float this pin.
GND	2	—	Ground pin. This pin must be connected to ground on the board.
IN	1	Input	Input pin. For best transient response and to minimize input impedance, use the recommended value or larger ceramic capacitor from IN to ground; see the *Recommended Operating Conditions* table. Place the input capacitor as close to the input of the device as possible.
OUT	5	Output	A 0.47-µF or greater effective capacitance is required from OUT to ground for stability. For best transient response, use a 1-µF or larger ceramic capacitor from OUT to ground. Place the output capacitor as close to output of the device as possible; see the *Recommended Operating Conditions* table.

DRAFT ONLY
TI Confidential – NDA Restrictions

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

	MIN	MAX	UNIT
Supply voltage, V_{IN}	–0.3	6.5	V
Enable voltage, V_{EN}	–0.3	6.5	
Output voltage, V_{OUT}	–0.3	V_{IN} + 0.3(2)	
Feedback voltage, V_{FB}	-0.3	2	
Output current, I_{OUT}	Internally limited		mA
Operating junction temperature, T_J	–40	150	°C
Storage temperature, T_{stg}	–65	150	

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

(2) The absolute maximum rating is V_{IN} + 0.3 V or 6.5 V, whichever is smaller.

6.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human body model (HBM), per ANSI/ESDA/JEDEC JS-001, all pins(1)	±2000	V
		Charged device model (CDM), per JEDEC specification JESD22-C101, all pins(2)	±500	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.

(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

DRAFT ONLY
TI Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	NOM	MAX	UNIT
V_{IN}	Input voltage	1.65		6.0	V
V_{OUT}	Output voltage	1.2		5.5	V
C_{IN}	Input capacitor	1			µF
C_{OUT}	Output capacitor	1[(1)]		200	µF
I_{OUT}	Output current	0		300	mA
$C_{OUT,ESR}$	Output capacitor ESR	0.001		1	Ω
V_{EN}	Enable voltage	0		6	V
F_{EN}	Enable toggle frequency			10	kHz
T_J	Junction temperature	–40		150	°C

(1) The minimum effective capacitance is 0.47 µF.

6.4 Thermal Information

THERMAL METRIC[(1)]		TPS784 DBV (SOT-23) 5 PINS	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance	170.8	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	93.1	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	10.2	°C/W
ψ_{JT}	Junction-to-top characterization parameter	17.5	°C/W
ψ_{JB}	Junction-to-board characterization parameter	40	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	n/a	°C/W

(1) For more information about traditional and new thermal metrics, see the Semiconductor and IC Package Thermal Metrics application report.

DRAFT ONLY
TI Confidential – NDA Restrictions

6.5 Electrical Characteristics

at operating temperature range (T_J = –40°C to +150°C), V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), I_{OUT} = 1 mA, V_{EN} = V_{IN}, C_{IN} = C_{OUT} = 1 µF, and C_{FF} = open, unless otherwise noted. All typical values at T_J = 25°C.

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
V_{IN}	Input voltage			1.65		6.0	V
V_{OUT}	Output voltage			1.2		5.5	V
V_{OUT}	Output accuracy(1)	1 mA ≤ I_{OUT} ≤ 300 mA, $V_{OUT(NOM)}$ + 0.5 V ≤ V_{IN} ≤ 6.0 V	T_J = 25°C	–0.5		0.5	%
			–40°C ≤ TJ ≤ 85°C	–0.75		0.75	
			85°C ≤ TJ ≤ 150°C	–1		1	
	Line regulation	$V_{OUT(NOM)}$ + 0.5 V ≤ V_{IN} ≤ 6.0 V			0.3		mV
	Load regulation	0.1 mA ≤ I_{OUT} ≤ 300 mA	T_J = 25°C	–5		5	
			–40°C ≤ T_J ≤ 85°C				
			–40°C ≤ T_J ≤ 150°C	–5		10	
I_{GND}	Ground current	T_J = 25°C, I_{OUT} = 0 mA		15	25	30	µA
		I_{OUT} = 0 mA				35	
I_{SHDN}	Shutdown current	V_{EN} ≤ 0.3 V, 1.65 V ≤ V_{IN} ≤ 6.0 V, T_J = 25°C			0.15	1	
		V_{EN} ≤ 0.3 V, 1.65 V ≤ V_{IN} ≤ 6.0 V, –40°C ≤ T_J ≤ 85°C				1	
		V_{EN} ≤ 0.3 V, 1.65 V ≤ V_{IN} ≤ 6.0 V, –40°C ≤ T_J ≤ 150°C				3	
V_{FB}	Feedback voltage			1.182	1.2	1.218	V
I_{FB}	Feedback pin current			–0.1	0.01	0.05	µA
I_{CL}	Output current limit	V_{IN} = $V_{OUT(NOM)}$ + 1 V, V_{OUT} = 0.9 x $V_{OUT(NOM)}$ (2)		320		460	mA
I_{SC}	Short-circuit current limit	V_{OUT} = 0 V			175		
V_{DO}	Dropout voltage	I_{OUT} = 300 mA, V_{OUT} = 0.95 x $V_{OUT(NOM)}$	1.2 V ≤ V_{OUT} < 1.5 V			300	mV
			1.5 V ≤ V_{OUT} < 1.8 V			175	
			1.8 V ≤ V_{OUT} < 2.5 V			140	
			2.5 V ≤ V_{OUT} ≤ 5.0 V			115	
PSRR	Power-supply rejection ratio	V_{OUT} = 3.3 V, I_{OUT} = 300 mA, V_{IN} = $V_{OUT(NOM)}$ + 1 V	f = 1 kHz		52		dB
			f = 100 kHz		49		
			f = 1 MHz		30		
V_n	Output noise voltage	BW = 10 Hz to 100 kHz, V_{OUT} = 1.2 V			30		$µV_{RMS}$
$V_{UVLO,rising}$	Undervoltage lockout	V_{IN} rising		1.32	1.42	1.6	V
$V_{UVLO,falling}$		V_{IN} falling		1.17	1.29	1.42	
$V_{UVLO,HYST}$	Undervoltage lockout hysteresis	V_{IN} hysteresis			130		mV
t_{STR}	Startup time	From EN low-to-high transition to V_{OUT} = $V_{OUT(NOM)}$ x 95%(3)			500	780	µs
$V_{EN(HI)}$	EN pin high voltage (enabled)			0.85			V
$V_{EN(LO)}$	EN pin low voltage (enabled)					0.425	
I_{EN}	Enable pin current	V_{IN} = V_{EN} = 6.0 V			10		nA
$R_{PULLDOWN}$	Pulldown resistance	V_{IN} = 3.3 V			100		Ω

DRAFT ONLY
TI Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

6.5 Electrical Characteristics (continued)

at operating temperature range (T_J = –40°C to +150°C), V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), I_{OUT} = 1 mA, V_{EN} = V_{IN}, C_{IN} = C_{OUT} = 1 µF, and C_{FF} = open, unless otherwise noted. All typical values at T_J = 25°C.

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$T_{SD(shutdown)}$	Thermal shutdown temperature	Shutdown, temperature increasing		170		°C
$T_{SD(reset)}$	Thermal shutdown reset temperature	Reset, temperature decreasing		160		

(1) Feedback resistors tolerance is not included in overall accuracy.
(2) The output is being forced to 90% of the nominal V_{OUT} value.
(3) Startup time = time from EN assertion to 0.95×$V_{OUT(NOM)}$.

DRAFT ONLY
TI Confidential – NDA Restrictions

6.6 Typical Characteristics

at operating temperature T_J = 25°C, I_{OUT} = 1 mA, V_{EN} = 1.0 V, C_{IN} = 1.0 µF, C_{OUT} = 1.0 µF, and V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), unless otherwise noted; typical values are at T_J = 25°C



V_{OUT} = 1.2 V

図 6-1. Output Accuracy vs I_{OUT}



V_{OUT} = 5.0 V

図 6-2. Output Accuracy vs I_{OUT}



V_{OUT} = 3.3 V

図 6-3. Output Accuracy vs V_{IN}



V_{OUT} = 5.0 V

図 6-4. Output Accuracy vs V_{IN}



V_{OUT} = 1.8 V

図 6-5. Dropout Voltage vs I_{OUT}



V_{OUT} = 3.3 V

図 6-6. Dropout Voltage vs I_{OUT}

DRAFT
TI Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

6.6 Typical Characteristics (continued)

at operating temperature T_J = 25°C, I_{OUT} = 1 mA, V_{EN} = 1.0 V, C_{IN} = 1.0 µF, C_{OUT} = 1.0 µF, and V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), unless otherwise noted; typical values are at T_J = 25°C



V_{OUT} = 5.0 V

図 6-7. Dropout Voltage vs I_{OUT}



図 6-8. I_{GND} vs I_{OUT}



I_{OUT} = 100 µA

図 6-9. I_{GND} vs V_{IN}



V_{EN} = 0.3 V

図 6-10. I_{SHDV} vs V_{IN}



V_{EN} = 0.3 V

図 6-11. V_{IN} vs Pulldown Resistor



V_{IN} = 2 V

図 6-12. $V_{EN(HI)}$ and $V_{EV(LO)}$ Threshold vs Temperature

DRAFT
TI Confidential – NDA Restrictions

6.6 Typical Characteristics (continued)

at operating temperature T_J = 25°C, I_{OUT} = 1 mA, V_{EN} = 1.0 V, C_{IN} = 1.0 µF, C_{OUT} = 1.0 µF, and V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), unless otherwise noted; typical values are at T_J = 25°C



V_{IN} = 6 V

図 6-13. $V_{EN(HI)}$ and $V_{EV(LO)}$ Threshold vs Temperature



V_{OUT} = 1.2 V

図 6-14. Foldback Current Limit vs I_{OUT} and Temperature



V_{OUT} = 5.0 V

図 6-15. Foldback Current Limit vs I_{OUT} and Temperature



V_{OUT} = 3.3 V, I_{OUT} = 1 mA, slew rate = 1 V/µs

図 6-16. Line Transient



V_{OUT} = 3.3 V, I_{OUT} = 300 mA, slew rate = 1 V/µs

図 6-17. Line Transient



V_{IN} = 5.5 V, V_{OUT} = 5.0 V, I_{OUT} slew rate = 1 A/µs

図 6-18. I_{OUT} Transient From 1 mA to 300 mA

DRAFT
TI confidential - NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

6.6 Typical Characteristics (continued)

at operating temperature T_J = 25°C, I_{OUT} = 1 mA, V_{EN} = 1.0 V, C_{IN} = 1.0 µF, C_{OUT} = 1.0 µF, and V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), unless otherwise noted; typical values are at T_J = 25°C



V_{IN} = 5.5 V, V_{OUT} = 5.0 V, I_{OUT} slew rate = 1 A/µs

図 6-19. I_{OUT} Transient From 1 mA to 300 mA



V_{IN} = 5.5 V, V_{OUT} = 5.0 V, I_{OUT} slew rate = 1 A/µs

図 6-20. I_{OUT} Transient From 300 mA to 1 mA



V_{IN} = 3.8 V, V_{OUT} = 3.3 V, I_{OUT} slew rate = 1 A/µs

図 6-21. I_{OUT} Transient From 1 mA to 300 mA



V_{IN} = 3.8 V, V_{OUT} = 3.3 V, I_{OUT} slew rate = 1 A/µs

図 6-22. I_{OUT} Transient From 1-mA to 300-mA Rising Edge



V_{IN} = 3.8 V, V_{OUT} = 3.3 V, I_{OUT} slew rate = 0.5 A/µs

図 6-23. I_{OUT} Transient From 1-mA to 300-mA Falling Edge



V_{IN} = 2.2 V, C_{IN} = 0 µF, V_{OUT} = 1.2 V

図 6-24. PSRR vs Frequency and I_{OUT}

DRAFT
TI Confidential – NDA Restrictions

6.6 Typical Characteristics (continued)

at operating temperature T_J = 25°C, I_{OUT} = 1 mA, V_{EN} = 1.0 V, C_{IN} = 1.0 µF, C_{OUT} = 1.0 µF, and V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), unless otherwise noted; typical values are at T_J = 25°C



V_{IN} = 4.3 V, C_{IN} = 0 µF, V_{OUT} = 3.3 V

図 6-25. PSRR vs Frequency and I_{OUT}



V_{IN} = 6 V, C_{IN} = 0 µF, V_{OUT} = 5.0 V

図 6-26. PSRR vs Frequency and I_{OUT}



V_{IN} = 4.3 V, C_{IN} = 0 µF, V_{OUT} = 3.3 V, I_{OUT} = 300 mA

図 6-27. PSRR vs Frequency and C_{OUT}



V_{IN} = 6 V, C_{IN} = 0 µF, V_{OUT} = 5.0 V, I_{OUT} = 300 mA

図 6-28. PSRR vs Frequency and C_{OUT}



V_{IN} = $V_{OUT(nom)}$ + 1 V, I_{OUT} = 300 mA, V_{RMS} BW = 10 Hz to 100 kHz

図 6-29. Output Noise vs Frequency and V_{OUT}



V_{IN} = 4.3 V, V_{OUT} = 3.3 V, I_{OUT} = 300 mA, V_{RMS} BW = 10 Hz to 100 kHz

図 6-30. Output Noise vs Frequency and C_{FF}

DRAFT
Texas Instruments Confidential - NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

6.6 Typical Characteristics (continued)

at operating temperature T_J = 25°C, I_{OUT} = 1 mA, V_{EN} = 1.0 V, C_{IN} = 1.0 µF, C_{OUT} = 1.0 µF, and V_{IN} = $V_{OUT(NOM)}$ + 0.5 V or 1.65 V (whichever is greater), unless otherwise noted; typical values are at T_J = 25°C



V_{IN} = 6 V, V_{OUT} = 5.0 V, I_{OUT} = 300 mA,
V_{RMS} BW = 10 Hz to 100 kHz

図 6-31. Output Noise vs Frequency and C_{FF}



V_{IN} = 5.5 V, C_{IN} = 0 µF, V_{OUT} = 5.0 V, I_{OUT} = 0 mA

図 6-32. Startup Inrush Current With C_{OUT} = 1 µF



V_{IN} = 5.5 V, C_{IN} = 0 µF, V_{OUT} = 5.0 V, I_{OUT} = 0 mA

図 6-33. Startup Inrush Current With C_{OUT} = 4.7 µF

DRAFT ONLY
TI Confidential – NDA Restrictions

7 Detailed Description

7.1 Overview

The TPS784 is an ultra low-dropout, high PSRR, high-accuracy linear voltage regulator that is optimized for excellent transient performance. These characteristics make the device ideal for vast range of linear voltage regulator (LDO) applications.

This device offers foldback current limit, output enable, active discharge, undervoltage lockout (UVLO), and thermal protection.

7.2 Functional Block Diagram



7.3 Feature Description

7.3.1 Foldback Current Limit

The device has an internal current limit circuit that protects the regulator during transient high-load current faults or shorting events. The current limit is a hybrid brickwall-foldback scheme. The current limit transitions from a brickwall scheme to a foldback scheme at the foldback voltage ($V_{FOLDBACK}$). In a high-load current fault with the output voltage above $V_{FOLDBACK}$, the brickwall scheme limits the output current to the current limit (I_{CL}). When the voltage drops below $V_{FOLDBACK}$, a foldback current limit activates that scales back the current as the output voltage approaches GND. When the output is shorted, the device supplies a typical current called the short-circuit current limit (I_{SC}). I_{CL} and I_{SC} are listed in the *Electrical Characteristics* table.

For this device, $V_{FOLDBACK} = 0.4 \times V_{OUT(NOM)}$ (V)

The output voltage is not regulated when the device is in current limit. When a current limit event occurs, the device begins to heat up because of the increase in power dissipation. When the device is in brickwall current limit, the pass transistor dissipates power $[(V_{IN} – V_{OUT}) \times I_{CL}]$. When the device output is shorted and the output is below $V_{FOLDBACK}$, the pass transistor dissipates power $[(V_{IN} – V_{OUT}) \times I_{SC}]$. If thermal shutdown is triggered, the device turns off. After the device cools down, the internal thermal shutdown circuit turns the device back on. If the output current fault condition continues, the device cycles between current limit and thermal shutdown. For more information on current limits, see the *Know Your Limits* application report.

DRAFT ONLY
Texas Instruments Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

図 7-1 shows a diagram of the foldback current limit.



図 7-1. Foldback Current Limit

7.3.2 Output Enable

The enable pin (EN) is active high. Enable the device by forcing the voltage of the enable pin to exceed the minimum EN pin high-level input voltage (see the *Electrical Characteristics* table). Turn off the device by forcing the voltage of the enable pin to drop below the maximum EN pin low-level input voltage (see the *Electrical Characteristics* table). If shutdown capability is not required, connect EN to IN.

This device has an internal pulldown circuit that activates when the device is disabled to actively discharge the output voltage.

7.3.3 Active Discharge

The device has an internal pulldown MOSFET that connects an $R_{PULLDOWN}$ resistor to ground when the device is disabled to actively discharge the output voltage. The active discharge circuit is activated by the enable pin.

Do not rely on the active discharge circuit to discharge the output voltage after the input supply has collapsed because reverse current can possibly flow from the output to the input. This reverse current flow can cause damage to the device especially when a large output capacitor is used. Limit reverse current to no more than 5% of the device rated current for a short period of time.

DRAFT ONLY
TI Confidential – NDA Restrictions

7.3.4 Undervoltage Lockout (UVLO) Operation

The UVLO circuit ensures that the device stays disabled before its input supply reaches the minimum operational voltage range, and ensures that the device shuts down when the input supply collapses. 図 7-2 shows the UVLO circuit response to various input voltage events. The diagram can be separated into the following parts:

- Region A: The device does not start until the input reaches the UVLO rising threshold.
- Region B: Normal operation, regulating device.
- Region C: Brownout event above the UVLO falling threshold (UVLO rising threshold – UVLO hysteresis). The output may fall out of regulation but the device remains enabled.
- Region D: Normal operation, regulating device.
- Region E: Brownout event below the UVLO falling threshold. The device is disabled in most cases and the output falls because of the load and active discharge circuit. The device is reenabled when the UVLO rising threshold is reached by the input voltage and a normal start-up follows.
- Region F: Normal operation followed by the input falling to the UVLO falling threshold.
- Region G: The device is disabled when the input voltage falls below the UVLO falling threshold to 0 V. The output falls because of the load and active discharge circuit.



図 7-2. Typical UVLO Operation

7.3.5 Dropout Voltage

Dropout voltage (V_{DO}) is defined as the input voltage minus the output voltage ($V_{IN} – V_{OUT}$) at the rated output current (I_{RATED}), where the pass transistor is fully on. I_{RATED} is the maximum I_{OUT} listed in the *Recommended Operating Conditions* table. The pass transistor is in the ohmic or triode region of operation, and acts as a switch. The dropout voltage indirectly specifies a minimum input voltage greater than the nominal programmed output voltage at which the output voltage is expected to stay in regulation. If the input voltage falls to less than the nominal output regulation, then the output voltage falls as well.

For a CMOS regulator, the dropout voltage is determined by the drain-source on-state resistance ($R_{DS(ON)}$) of the pass transistor. Therefore, if the linear regulator operates at less than the rated current, the dropout voltage for that current scales accordingly. Use Equation 1 to calculate the $R_{DS(ON)}$ of the device.

$$R_{DS(ON)} = \frac{V_{DO}}{I_{RATED}} \quad (1)$$

7.3.6 Thermal Shutdown

The device contains a thermal shutdown protection circuit to disable the device when the junction temperature (T_J) of the pass transistor rises to $T_{SD(shutdown)}$ (typical). Thermal shutdown hysteresis assures that the device resets (turns on) when the temperature falls to $T_{SD(reset)}$ (typical).

The thermal time-constant of the semiconductor die is fairly short, thus the device may cycle on and off when thermal shutdown is reached until power dissipation is reduced. Power dissipation during startup can be high from large $V_{IN} – V_{OUT}$ voltage drops across the device or from high inrush currents charging large output

DRAFT ONLY
TI Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

capacitors. Under some conditions, the thermal shutdown protection disables the device before startup completes.

For reliable operation, limit the junction temperature to the maximum listed in the *Recommended Operating Conditions* table. Operation above this maximum temperature causes the device to exceed its operational specifications. Although the internal protection circuitry of the device is designed to protect against thermal overall conditions, this circuitry is not intended to replace proper heat sinking. Continuously running the device into thermal shutdown or above the maximum recommended junction temperature reduces long-term reliability.

7.4 Device Functional Modes

7.4.1 Device Functional Mode Comparison

The *Device Functional Mode Comparison* table shows the conditions that lead to the different modes of operation. See the *Electrical Characteristics* table for parameter values.

表 7-1. Device Functional Mode Comparison

OPERATING MODE	PARAMETER			
	V_{IN}	V_{EN}	I_{OUT}	T_J
Normal operation	$V_{IN} > V_{OUT(nom)} + V_{DO}$ and $V_{IN} > V_{IN(min)}$	$V_{EN} > V_{EN(HI)}$	$I_{OUT} < I_{OUT(max)}$	$T_J < T_{SD(shutdown)}$
Dropout operation	$V_{IN(min)} < V_{IN} < V_{OUT(nom)} + V_{DO}$	$V_{EN} > V_{EN(HI)}$	$I_{OUT} < I_{OUT(max)}$	$T_J < T_{SD(shutdown)}$
Disabled (any true condition disables the device)	$V_{IN} < V_{UVLO}$	$V_{EN} < V_{EN(LOW)}$	Not applicable	$T_J > T_{SD(shutdown)}$

7.4.2 Normal Operation

The device regulates to the nominal output voltage when the following conditions are met:

- The input voltage is greater than the nominal output voltage plus the dropout voltage ($V_{OUT(nom)} + V_{DO}$)
- The output current is less than the current limit ($I_{OUT} < I_{CL}$)
- The device junction temperature is less than the thermal shutdown temperature ($T_J < T_{SD}$)
- The enable voltage has previously exceeded the enable rising threshold voltage and has not yet decreased to less than the enable falling threshold

7.4.3 Dropout Operation

If the input voltage is lower than the nominal output voltage plus the specified dropout voltage, but all other conditions are met for normal operation, the device operates in dropout mode. In this mode, the output voltage tracks the input voltage. During this mode, the transient performance of the device becomes significantly degraded because the pass transistor is in the ohmic or triode region, and acts as a switch. Line or load transients in dropout can result in large output-voltage deviations.

When the device is in a steady dropout state (defined as when the device is in dropout, $V_{IN} < V_{OUT(NOM)} + V_{DO}$, directly after being in a normal regulation state, but *not* during startup), the pass transistor is driven into the ohmic or triode region. When the input voltage returns to a value greater than or equal to the nominal output voltage plus the dropout voltage ($V_{OUT(NOM)} + V_{DO}$), the output voltage can overshoot for a short period of time while the device pulls the pass transistor back into the linear region.

7.4.4 Disabled

The output of the device can be shutdown by forcing the voltage of the enable pin to less than the maximum EN pin low-level input voltage (see the *Electrical Characteristics* table). When disabled, the pass transistor is turned off, internal circuits are shutdown, and the output voltage is actively discharged to ground by an internal discharge circuit from the output to ground.

PREVIEW ONLY
TI Confidential – NDA Restrictions

8 Application and Implementation

Note

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

8.1.1 Recommended Capacitor Types

The device is designed to be stable using low equivalent series resistance (ESR) ceramic capacitors at the input and output. Multilayer ceramic capacitors have become the industry standard for these types of applications and are recommended, but must be used with good judgment. Ceramic capacitors that employ X7R-, X5R-, and C0G-rated dielectric materials provide relatively good capacitive stability across temperature, whereas the use of Y5V-rated capacitors is discouraged because of large variations in capacitance.

Regardless of the ceramic capacitor type selected, the effective capacitance varies with operating voltage and temperature. As a rule of thumb, expect the effective capacitance to decrease by as much as 50%. The input and output capacitors recommended in the *Recommended Operating Conditions* table account for an effective capacitance of approximately 50% of the nominal value.

8.1.2 Input and Output Capacitor Requirements

The device requires an input capacitor of 1.0 µF or larger as specified in the *Recommended Operating Conditions* table for stability. A higher value capacitor may be necessary if large, fast rise-time load or line transients are anticipated or if the device is located several inches from the input power source.

The device also requires an output capacitor of 1.0 µF or larger as specified in the *Recommended Operating Conditions* table for stability. Dynamic performance of the device is improved by using a higher capacitor than the minimum output capacitor.

8.1.3 Output Voltage Setting (Feedback Resistors)

The device requires external feedback divider resistors to set the output voltage. 図 8-1 shows how the output voltage can be configured from 1.2 V to 5.5 V by using a resistor divider network.



図 8-1. Output Voltage Setting

Equation 2 calculates how the R_1 and R_2 resistors are used to set the output voltage:

$$V_{OUT} = V_{FB} \times (1 + R_1 / R_2) + I_{FB} \times R_1 \quad (2)$$

DRAFT ONLY
TI Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

To disregard the effect of the FB pin current error term in Equation 2 and to achieve best accuracy, choose R_2 to be smaller than 550 kΩ so that the current flowing through R_1 and R_2 is at least 100 times larger than the I_{FB} current listed in the *Electrical Characteristics* table. Lowering the value of R_2 increases the immunity against noise injection. Increasing the value of R_2 reduces the quiescent current for achieving higher efficiency at low load currents. Equation 3 calculates the setting that provides the maximum feedback divider series resistance.

$$(R_1 + R_2) \leq V_{OUT} / (I_{FB} \times 100) \quad (3)$$

8.1.4 Load Transient Response

The load-step transient response is the output voltage response by the LDO to a step in load current, whereby output voltage regulation is maintained. There are two key transitions during a load transient response: the transition from a light to a heavy load and the transition from a heavy to a light load. The regions shown in 図 8-2 are broken down as follows. Regions A, E, and H are where the output voltage is in steady-state.



図 8-2. Load Transient Waveform

During transitions from a light load to a heavy load, the:

- Initial voltage dip is a result of the depletion of the output capacitor charge and parasitic impedance to the output capacitor (region B)
- Recovery from the dip results from the LDO increasing its sourcing current, and leads to output voltage regulation (region C)
- Initial voltage rise results from the LDO sourcing a large current, and leads to the output capacitor charge to increase (region F)
- Recovery from the rise results from the LDO decreasing its sourcing current in combination with the load discharging the output capacitor (region G)

A larger output capacitance reduces the peaks during a load transient but slows down the response time of the device. A larger DC load also reduces the peaks because the amplitude of the transition is lowered and a higher current discharge path is provided for the output capacitor.

DRAFT ONLY
TI Confidential – NDA Restrictions

8.1.5 Exiting Dropout

Some applications have transients that place the LDO into dropout, such as slower ramps on V_{IN} during start-up. As with other LDOs, the output can overshoot on recovery from these conditions. A ramping input supply causes an LDO to overshoot on start-up, as shown in 図 8-3, when the slew rate and voltage levels are in the correct range. Use an enable signal to avoid this condition.



図 8-3. Start-Up Into Dropout

Line transients out of dropout can also cause overshoot on the output of the regulator. These overshoots are caused by the error amplifier having to drive the gate capacitance of the pass element and bring the gate back to the correct voltage for proper regulation. 図 8-4 illustrates what is happening internally with the gate voltage and how overshoot can be caused during operation. When the LDO is placed in dropout, the gate voltage (V_{GS}) is pulled all the way down to ground to give the pass device the lowest on-resistance as possible. However, if a line transient occurs when the device is in dropout, the loop is not in regulation and can cause the output to overshoot until the loop responds and the output current pulls the output voltage back down into regulation. If these transients are not acceptable, then continue to add input capacitance in the system until the transient is slow enough to reduce the overshoot.

DRAFT ONLY
TI Confidential - NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated



図 8-4. Line Transients From Dropout

8.1.6 Dropout Voltage

The device uses a PMOS pass transistor to achieve low dropout. When (V_{IN} – V_{OUT}) is less than the dropout voltage (V_{DO}), the PMOS pass device is in the linear region of operation and the input-to-output resistance is the $R_{DS(ON)}$ of the PMOS pass element. V_{DO} scales approximately with output current because the PMOS device behaves like a resistor in dropout mode. As with any linear regulator, PSRR and transient response degrade as (V_{IN} – V_{OUT}) approaches dropout operation.

8.1.7 Reverse Current

As with most LDOs, excessive reverse current can damage this device.

Reverse current flows through the body diode on the pass element instead of the normal conducting channel. At high magnitudes, this current flow degrades the long-term reliability of the device, as a result of one of the following conditions:

- Degradation caused by electromigration
- Excessive heat dissipation
- Potential for a latch-up condition

DRAFT ONLY
TI confidential – NDA Restrictions

Conditions where reverse current can occur are outlined in this section, all of which can exceed the absolute maximum rating of $V_{OUT} > V_{IN} + 0.3$ V:

- If the device has a large C_{OUT} and the input supply collapses with little or no load current
- The output is biased when the input supply is not established
- The output is biased above the input supply

If reverse current flow is expected in the application, external protection must be used to protect the device. 図 8-5 shows one approach of protecting the device.



図 8-5. Example Circuit for Reverse Current Protection Using a Schottky Diode

8.1.8 Feed-Forward Capacitor (C_{FF})

The optional feed-forward capacitor (C_{FF}) can be connected from the OUT pin to the FB pin. C_{FF} improves transient, noise, and PSRR performance, but is not required for regulator stability. Recommended C_{FF} values are listed in the *Recommended Operating Conditions* table. A higher capacitance C_{FF} can be used; however, the startup time increases. For a detailed description of C_{FF} tradeoffs, see the *Pros and Cons of Using a Feedforward Capacitor with a Low-Dropout Regulator* application report.

8.1.9 Power Dissipation (P_D)

Circuit reliability demands that proper consideration be given to device power dissipation, location of the circuit on the printed circuit board (PCB), and correct sizing of the thermal plane. The PCB area around the regulator must be as free as possible of other heat-generating devices that cause added thermal stresses.

As a first-order approximation, power dissipation in the regulator depends on the input-to-output voltage difference and load conditions. Use Equation 4 to approximate P_D:

$$P_D = (V_{IN} – V_{OUT}) \times I_{OUT} \quad (4)$$

Power dissipation can be minimized, and thus greater efficiency achieved, by proper selection of the system voltage rails. Proper selection allows the minimum input-to-output voltage differential to be obtained. The low dropout of the TPS784 allows for maximum efficiency across a wide range of output voltages.

The main heat conduction path for the device is through the thermal pad on the package. As such, the thermal pad must be soldered to a copper pad area under the device. This pad area contains an array of plated vias that conduct heat to any inner plane areas or to a bottom-side copper plane.

The maximum power dissipation determines the maximum allowable junction temperature (T_J) for the device. According to Equation 5, power dissipation and junction temperature are most often related by the junction-to-ambient thermal resistance ($R_{\theta JA}$) of the combined PCB and device package and the temperature of the ambient air (T_A). Equation 6 rearranges Equation 5 for output current.

$$T_J = T_A + (R_{\theta JA} \times P_D) \quad (5)$$

$$I_{OUT} = (T_J – T_A) / [R_{\theta JA} \times (V_{IN} – V_{OUT})] \quad (6)$$

DRAFT ONLY
Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

Unfortunately, this thermal resistance ($R_{\theta JA}$) is highly dependent on the heat-spreading capability built into the particular PCB design, and therefore varies according to the total copper area, copper weight, and location of the planes. The $R_{\theta JA}$ recorded in the *Recommended Operating Conditions* table is determined by the JEDEC standard, PCB, and copper-spreading area, and is only used as a relative measure of package thermal performance.

8.1.9.1 Estimating Junction Temperature

The JEDEC standard now recommends the use of psi (Ψ) thermal metrics to estimate the junction temperatures of the LDO when in-circuit on a typical PCB board application. These metrics are not strictly speaking thermal resistances, but rather offer practical and relative means of estimating junction temperatures. These psi metrics are determined to be significantly independent of the copper-spreading area. The key thermal metrics (Ψ_{JT} and Ψ_{JB}) are used in accordance with Equation 7 and are given in the *Recommended Operating Conditions* table.

$$\Psi_{JT} : T_J = T_T + \Psi_{JT} \times P_D \text{ and } \Psi_{JB} : T_J = T_B + \Psi_{JB} \times P_D \quad (7)$$

where:

- P_D is the power dissipated as explained in Equation 4
- T_T is the temperature at the center-top of the device package, and
- T_B is the PCB surface temperature measured 1 mm from the device package and centered on the package edge

8.1.9.2 Recommended Area for Continuous Operation

The operational area of an LDO is limited by the dropout voltage, output current, junction temperature, and input voltage. The recommended area for continuous operation for a linear regulator is given in 図 8-6 and can be separated into the following parts:

- Dropout voltage limits the minimum differential voltage between the input and the output ($V_{IN} – V_{OUT}$) at a given output current level. See the *Dropout Voltage* section for more details.
- The rated output currents limits the maximum recommended output current level. Exceeding this rating causes the device to fall out of specification.
- The rated junction temperature limits the maximum junction temperature of the device. Exceeding this rating causes the device to fall out of specification and reduces long-term reliability.
  - The shape of the slope is given by Equation 6. The slope is nonlinear because the maximum rated junction temperature of the LDO is controlled by the power dissipation across the LDO; thus when $V_{IN} – V_{OUT}$ increases the output current must decrease.
- The rated input voltage range governs both the minimum and maximum of $V_{IN} – V_{OUT}$.

DRAFT ONLY
TI Confidential - NDA Restrictions

図 8-6 shows the recommended area of operation for this device on a JEDEC-standard high-K board with a $R_{\theta JA}$ as given in the *Recommended Operating Conditions* table.



図 8-6. Region Description of Continuous Operation Regime

8.2 Typical Application



図 8-7. Operation From a DC/DC Converter

8.2.1 Design Requirements

表 8-1 summarizes the design requirement for this application.

表 8-1. Design Parameters

PARAMETER	DESIGN REQUIREMENT
Input voltage	3.8 V
Output voltage	3.3 V, ±1.5%
R_2	Chosen to be 550 kΩ
R_1	Calculated to be 976 kΩ
Output load	100 mA
Output capacitor	10 µF
Maximum ambient temperature	85°C

8.2.2 Detailed Design Procedure

For this design example, a 3.3-V rail is needed to power the application with 100-mA of load current. The device is powered off a DC/DC converter connected to a battery. A 500-mV headroom between V_{IN} and V_{OUT} is used to keep the device within the dropout voltage specification and to make sure the device stays in regulation under all load and temperature conditions for this design.

DRAFT ONLY
TI Confidential – NDA restrictions

Copyright © 2020 Texas Instruments Incorporated

8.2.3 Application Curves

A 10-µF capacitor is used to achieve lower overshoot and undershoot of output voltage during load transients with ramp rates greater than 0.5 A/µs, 図 8-8 and 図 8-9 show captures of load transient behavior for this application.



V_{IN} = 3.8 V, V_{OUT} = 3.3 V, C_{OUT} = 10 µF,
I_{OUT} slew rate = 1 A/µs

図 8-8. I_{OUT} Transient From 0 mA to 100 mA



V_{IN} = 3.8 V, V_{OUT} = 3.3 V, C_{OUT} = 10 µF,
I_{OUT} slew rate = 1 A/µs

図 8-9. I_{OUT} Transient From 1 mA to 100 mA

9 Power Supply Recommendations

This device is designed to operate from an input supply voltage range of 1.65 V to 6.0 V. The input supply must be well regulated and free of spurious noise. To ensure that the output voltage is well regulated and dynamic performance is optimum, the input supply must be at least $V_{OUT(nom)}$ + 0.5 V. TI requires using a 1-µF or greater input capacitor to reduce the impedance of the input supply, especially during transients.

DRAFT ONLY
TI Confidential – NDA Restrictions

10 Layout

10.1 Layout Guidelines

- Place input and output capacitors as close to the device as possible.
- Use copper planes for device connections, in order to optimize thermal performance.
- Place thermal vias around the device to distribute the heat.

10.1.1 Additional Layout Considerations

The high impedance of the FB pin makes the regulator sensitive to parasitic capacitances that may couple undesirable signals from nearby components (especially from logic and digital devices, such as microcontrollers and microprocessors); these capacitively-coupled signals may produce undesirable output voltage transients. In these cases, TI recommends isolating the FB node by placing a copper ground plane on the layer directly underneath the LDO circuitry and FB pin to minimize any undesirable signal coupling.

10.2 Layout Example



図 10-1. Layout Example

DRAFT ONLY
TI Confidential – NDA Restrictions

Copyright © 2020 Texas Instruments Incorporated

11 Device and Documentation Support

11.1 Device Support

11.1.1 Device Nomenclature

表 11-1. Ordering Information

PRODUCT	DESCRIPTION
TPS78401YYYZ	YYY is the package designator. Z is the package quantity.

11.2 Documentation Support

11.2.1 Related Documentation

For related documentation see the following:

- Texas Instruments, *Universal Low-Dropout (LDO) Linear Voltage Regulator MultiPkgLDOEVM-823 Evaluation Module* user guide
- Texas Instruments, *Pros and Cons of Using a Feedforward Capacitor with a Low-Dropout Regulator* application report
- Texas Instruments, *Using New Thermal Metrics* application report
- Texas Instruments, *An empirical analysis of the impact of board layout on LDO thermal performance* application report

11.3 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. Click on *Subscribe to updates* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

11.4 Support Resources

TI E2E™ support forums are an engineer's go-to source for fast, verified answers and design help — straight from the experts. Search existing answers or ask your own question to get the quick design help you need.

Linked content is provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

11.5 Trademarks

TI E2E™ is a trademark of Texas Instruments.
すべての商標は、それぞれの所有者に帰属します。

11.6 Electrostatic Discharge Caution

This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

11.7 Glossary

TI Glossary This glossary lists and explains terms, acronyms, and definitions.

12 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

DRAFT ONLY
TI Confidential – NDA Restrictions

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
TPS78401DBVR	ACTIVE	SOT-23	DBV	5	3000	RoHS & Green	NIPDAU	Level-1-260C-UNLIM	-40 to 125	2DZF	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) **RoHS:** TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".
RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.
Green: TI defines "Green" to mean the content of Chlorine (Cl) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF TPS784 :

- Automotive : TPS784-Q1

NOTE: Qualified Version Definitions:

- Automotive - Q100 devices qualified for high-reliability automotive applications targeting zero defects

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TPS78401DBVR	SOT-23	DBV	5	3000	180.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TPS78401DBVR	SOT-23	DBV	5	3000	210.0	185.0	35.0

PACKAGE OUTLINE

DBV0005A

SOT-23 - 1.45 mm max height

SMALL OUTLINE TRANSISTOR



ALTERNATIVE PACKAGE SINGULATION VIEW

4214839/J 02/2024

NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. Refernce JEDEC MO-178.
4. Body dimensions do not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.25 mm per side.
5. Support pin may differ or may not be present.



LAND PATTERN EXAMPLE
EXPOSED METAL SHOWN
SCALE:15X



SOLDER MASK DETAILS

4214839/J 02/2024

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SOLDER PASTE EXAMPLE
BASED ON 0.125 mm THICK STENCIL
SCALE:15X

4214839/J 02/2024

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

重要なお知らせと免責事項

TI は、技術データと信頼性データ (データシートを含みます)、設計リソース (リファレンス· デザインを含みます)、アプリケーションや設計に関する各種アドバイス、Web ツール、安全性情報、その他のリソースを、欠陥が存在する可能性のある「現状のまま」提供しており、商品性および特定目的に対する適合性の黙示保証、第三者の知的財産権の非侵害保証を含むいかなる保証も、明示的または黙示的にかかわらず拒否します。

これらのリソースは、TI 製品を使用する設計の経験を積んだ開発者への提供を意図したものです。(1) お客様のアプリケーションに適した TI 製品の選定、(2) お客様のアプリケーションの設計、検証、試験、(3) お客様のアプリケーションに該当する各種規格や、その他のあらゆる安全性、セキュリティ、規制、または他の要件への確実な適合に関する責任を、お客様のみが単独で負うものとします。

上記の各種リソースは、予告なく変更される可能性があります。これらのリソースは、リソースで説明されている TI 製品を使用するアプリケーションの開発の目的でのみ、TI はその使用をお客様に許諾します。これらのリソースに関して、他の目的で複製することや掲載することは禁止されています。TI や第三者の知的財産権のライセンスが付与されている訳ではありません。お客様は、これらのリソースを自身で使用した結果発生するあらゆる申し立て、損害、費用、損失、責任について、TI およびその代理人を完全に補償するものとし、TI は一切の責任を拒否します。

TI の製品は、TI の販売条件、または ti.com やかかる TI 製品の関連資料などのいずれかを通じて提供する適用可能な条項の下で提供されています。TI がこれらのリソースを提供することは、適用される TI の保証または他の保証の放棄の拡大や変更を意味するものではありません。

お客様がいかなる追加条項または代替条項を提案した場合でも、TI はそれらに異議を唱え、拒否します。

郵送先住所：Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2024, Texas Instruments Incorporated