

Filename: PMP2277_REVA_bom.xls						
Date: 01/12/2007						
<b>PMP2277_REVA BOM</b>						
COUNT	RefDes	Value	Description	Size	Part Number	Mfr
6	C1, C2, C18, C19, C30, C31	22uF	Capacitor, Ceramic, 16V, X5R, 15%	1210	Std	Std
3	C11, C25, C37	680uF	Capacitor, POS-Cap, 680uF, 4V, 0.010 Ohms, 20%, 7343	7343	4TPD680M	Sanyo
1	C12	0.047uF	Capacitor, Ceramic, 25V, X7R, 15%	0402	Std	TDK
6	C13, C16, C26, C28, C38, C40	1.0uF	Capacitor, Ceramic, 16V, X7R, 15%	0603	Std	TDK
3	C15, C27, C39	4.7uF	Capacitor, Ceramic, 10V, X5R, 15%	0603	Std	TDK
3	C17, C29, C41	1uF	Capacitor, Ceramic, 6.3V, X5R, 15%	0402	Std	TDK
1	C3	470pF	Capacitor, Ceramic, 16V, X7R, 15%	0402	Std	TDK
2	C4, C14	0.01uF	Capacitor, Ceramic, 16V, X7R, 15%	0402	Std	TDK
1	C5	1500pF	Capacitor, Ceramic, 16V, X7R, 15%	0402	Std	TDK
3	C6, C20, C32	0.022uF	Capacitor, Ceramic, 25V, X7R, 15%	0402	Std	TDK
3	C7, C21, C33	0.22uF	Capacitor, Ceramic, 25V, X7R, 15%	0603	Std	TDK
6	C8, C9, C22, C23, C34, C35	47uF	Capacitor, Ceramic, 6.3V, X5R, 15%	1206	Std	TDK
3	D1, D2, D3	BAT64-02W	Diode, Schottky, Fast-recovery, 250mA, 40V	SCD80	BAT64-02W	Infineon
4	J1, J2, J3, J4		Lug, Solderless, #2 - #8 AWG, 1/4	ILSCO	GSLU-70	Copper"
1	J5	PTC36SAAN	Header, 2-pin, 100mil spacing, (36-pin strip)	0.100 inch x 2	PTC36SAAN	Sullins
3	L1, L2, L3	0.56uH	Inductor, SMT, 32-A, 1.55-milliohm	0.400 x 0.453 inch	IHLP4040DZERR56M11	Vishay
3	Q1, Q3, Q5	BSC042N03S	MOSFET, Nch, 30V, 89A, 4.2milliohm	TDSON-8	BSC042N03S	Infineon
3	Q2, Q4, Q6	BSC022N03S	MOSFET, Nch, 30V, 100A, 2.2milliohm	TDSON-8	BSC022N03S	Infineon
3	R1, R19, R25	4.7	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R10	32.4K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
3	R11, R22, R28	0	Resistor, Chip, 1/16W, 1%	0402	Std	Std
2	R12, R15	68.1K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R13	3.01K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R14	29.4K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R16	113K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
3	R18, R24, R30	20	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R2	15K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R23	14.7K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R29	47.5K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R3	681	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R31	10.0K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
3	R4, R20, R26	16.2K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R5	4.75K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
1	R6	49.9	Resistor, Chip, 1/16W, 1%	0402	Std	Std
3	R7, R21, R27	Open	Resistor, Chip, 1/16W, 1%	0603	Std	Std
1	R8	750K	Resistor, Chip, 1/16W, 1%	0402	Std	Std
2	R9, R17	10	Resistor, Chip, 1/16W, 1%	0402	Std	Std
5	TP1, TP2, TP4, TP7, TP9	5000	Test Point, Red, Thru Hole Color Keyed	0.100 x 0.100 inch	5000	Keystone
3	TP3, TP8, TP10	5001	Test Point, Black, Thru Hole Color Keyed	0.100 x 0.100 inch	5001	Keystone
2	TP5, TP6	5002	Test Point, White, Thru Hole Color Keyed	0.100 x 0.100 inch	5002	Keystone
3	U1, U2, U3	TPS40180RGE	IC, Single Phase Stackable Buck Controller	QFN-24	TPS40180RGE	TI

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

### Products

Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>
Clocks and Timers	<a href="http://www.ti.com/clocks">www.ti.com/clocks</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>
RFID	<a href="http://www.ti-rfid.com">www.ti-rfid.com</a>
RF/IF and ZigBee® Solutions	<a href="http://www.ti.com/lprf">www.ti.com/lprf</a>

### Applications

Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Automotive	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
Broadband	<a href="http://www.ti.com/broadband">www.ti.com/broadband</a>
Digital Control	<a href="http://www.ti.com/digitalcontrol">www.ti.com/digitalcontrol</a>
Medical	<a href="http://www.ti.com/medical">www.ti.com/medical</a>
Military	<a href="http://www.ti.com/military">www.ti.com/military</a>
Optical Networking	<a href="http://www.ti.com/opticalnetwork">www.ti.com/opticalnetwork</a>
Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
Telephony	<a href="http://www.ti.com/telephony">www.ti.com/telephony</a>
Video & Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>
Wireless	<a href="http://www.ti.com/wireless">www.ti.com/wireless</a>

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2008, Texas Instruments Incorporated