OPA1671 13MHz、低ノイズ、レール・ツー・レールのオーディオ・オペアンプ

Texas Instruments
Burr-Brown Audio

1 特長

- 低ノイズ：
  4nV/√Hz (10kHz 時)
  4.7fA/√Hz (1kHz 時)
- 低歪み：-109dB (0.00035%)
- 広いゲイン帯域幅：13MHz
- レール・ツー・レール入出力
- 低電源電圧動作：1.7V～5.5V
- 低い入力容量
  - 差動：6pF
  - 同相：2.5pF
- 低入力バイアス電流：10pA
- 低消費電流：940µA
- 業界標準パッケージ：SC-70 および SOT-23

2 アプリケーション

- マイク・プリアンプ
- 補助ライン入出力
- アクティブ・フィルタ回路
- トランスインピーダンス・アンプ
- 電圧バッファ

3 概要

OPA1671は広帯域幅、低ノイズ、低歪みのオーディオ・オペアンプで、レール・ツー・レール入出力に対応しています。電圧ノイズ、電流ノイズ、入力容量がいずれも低いため、幅広いオーディオおよび産業用途で高性能を実現します。OPA1671 の独自の内部トポロジにより、歪みが極めて小さく (–109dB)、消費電流はわずか 940µA です。帯域幅が広く (13MHz)、スルーレートが高い (5V/µs) ため、高ゲイン・オーディオおよび産業用信号コンディショニングに最適です。

OPA1671 は SC-70 および SOT-23 パッケージで供給され、産業温度範囲 (–40℃～+125℃) で仕様が規定されています。

製品情報(1)

型番	パッケージ	本体サイズ(公称)
OPA1671	SC-70 (5)	2.00mm×1.25mm
	SOT-23 (5)	2.90mm×1.60mm

(1) 利用可能なすべてのパッケージについては、このデータシートの末尾にあるパッケージ・オプションについての付録を参照してください。

エレクトレット・マイク・プリアンプ



OPA1671の電圧ノイズ密度



目次

1 特長 ... 1
2 アプリケーション ... 1
3 概要 ... 1
4 改訂履歴 ... 2
5 **Pin Configuration and Functions** ... 3
6 **Specifications** ... 4
6.1 Absolute Maximum Ratings ... 4
6.2 ESD Ratings ... 4
6.3 Recommended Operating Conditions ... 4
6.4 Thermal Information ... 4
6.5 Electrical Characteristics ... 5
6.6 Typical Characteristics ... 7
7 **Detailed Description** ... 12
7.1 Overview ... 12
7.2 Functional Block Diagram ... 12
7.3 Feature Description ... 13
7.4 Device Functional Modes ... 14
8 **Application and Implementation** ... 15
8.1 Application Information ... 15
8.2 Typical Application ... 17
9 **Power Supply Recommendations** ... 19
10 **Layout** ... 19
10.1 Layout Guidelines ... 19
10.2 Layout Example ... 19
11 デバイスおよびドキュメントのサポート ... 20
11.1 デバイス・サポート ... 20
11.2 ドキュメントのサポート ... 20
11.3 ドキュメントの更新通知を受け取る方法 ... 20
11.4 コミュニティ・リソース ... 20
11.5 商標 ... 21
11.6 静電気放電に関する注意事項 ... 21
11.7 Glossary ... 21
12 メカニカル、パッケージ、および注文情報 ... 21

4 改訂履歴

資料番号末尾の英字は改訂を表しています。その改訂履歴は英語版に準じています。

Revision A (January 2019) から Revision B に変更 **Page**

- SOT-23 (DBV) パッケージと関連情報をデータシートに 追加 ... 1
- Added input offset voltage specification for V_{CM} = (V+), (V–) ... 5

2018年11月発行のものから更新 **Page**

- 事前情報 (プレビュー) から量産データ (アクティブ) に 変更 ... 1

Copyright © 2019, Texas Instruments Incorporated

5 Pin Configuration and Functions

DBV and DCK Packages
5-Pin SOT-23 and SC-70
Top View



Pin Functions

PIN		I/O	DESCRIPTION
NAME	NO.		
–IN	4	I	Inverting input
+IN	3	I	Noninverting input
OUT	1	O	Output
V–	2	—	Negative (lowest) power supply
V+	5	—	Positive (highest) power supply

Copyright © 2019, Texas Instruments Incorporated

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

	MIN	MAX	UNIT
Supply voltage, V_S = (V+) – (V–)		6	V
Input voltage	(V–) –0.3	(V+) +0.3	V
Output short-circuit(2)	Continuous		
Operating temperature, T_A	–55	150	°C
Storage temperature, T_{stg}	–65	150	°C

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. Theseare stress ratings only, which do not imply functional operation of the device at these or anyother conditions beyond those indicated under *Recommended OperatingConditions*. Exposure to absolute-maximum-rated conditions for extended periods mayaffect device reliability.
(2) Short-circuit to ground, one amplifier per package.

6.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001(1)	2000	V
		Charged-device model (CDM), per JEDEC specification JESD22-C101(2)	500	

(1) JEDEC document JEP155 states that 500-V HBM allows safemanufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safemanufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

	MIN	NOM	MAX	UNIT
Supply voltage, V_S = (V+) – (V–)	1.7 (±0.85)		5.5 (±2.75)	V
Specified temperature, T_A	–40		125	°C

6.4 Thermal Information

THERMAL METRIC(1)		OPA1671		UNIT
		DBV (SOT-23)	DCK (SC-70)	
		5 PINS	5 PINS	
$R_{\theta JA}$	Junction-to-ambient thermal resistance	187.1	214.7	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	107.4	127.1	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	57.5	60.0	°C/W
Ψ_{JT}	Junction-to-top characterization parameter	33.5	33.4	°C/W
Ψ_{JB}	Junction-to-board characterization parameter	57.1	59.8	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	n/a	n/a	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report.

Copyright © 2019, Texas Instruments Incorporated

6.5 Electrical Characteristics

at V_S = ±0.85 V to ±2.75 V (V_S = 1.7 V to 5.5 V), T_A = 25°C, R_L = 10 kΩ connected to V_S / 2, V_{CM} = V_S / 2, and V_{OUT} = V_S / 2 (unless otherwise noted)

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
AUDIO PERFORMANCE							
THD+N	Total harmonic distortion + noise	G = 1, f = 1 kHz, V_O = 1 V_{RMS}, V_S = 5.5 V			0.00035%		
					–109		dB
IMD	Intermodulation distortion	G = 1, V_O = 1 V_{RMS}, V_S = 5.5 V	SMPTE/DIN Two-Tone, 4:1, (60 Hz and 7 kHz)		0.00158%		
					–96		dB
			CCIF Two-Tone (19 kHz and 20 kHz)		0.0005%		
					–106		dB
FREQUENCY RESPONSE							
GBW	Gain-bandwidth product				13		MHz
SR	Slew rate	4-V step, G = 1			5		V/µs
t_S	Settling time	To 0.1%, 2-V step , G = 1			0.75		µs
		To 0.01%, 2-V step , G = 1			1		
	Overload recovery time	V_{IN} × gain > V_S			0.35		µs
NOISE							
	Input voltage noise	f = 0.1 Hz to 10 Hz			2.4		μV_{PP}
e_N	Input voltage noise density	f = 10 Hz			45		$nV/\sqrt{Hz}$
		f = 1 kHz			7		
		f = 10 kHz			4.0		
i_N	Input current noise	f = 1 kHz			4.7		$fA/\sqrt{Hz}$
OFFSET VOLTAGE							
V_{OS}	Input offset voltage	V_{CM} = (V+)				±1.6	mV
		V_{CM} = (V–)				±1.6	
					±0.25	±1.25	
		T_A = –40°C to 125°C			±0.25		
dV_{OS}/dT	Input offset voltage drift	T_A = –40°C to 125°C			±0.3	±2.2	µV/°C
PSRR	Input offset voltage versus power supply	V_{CM} = (V–)			±30	±130	µV/V
INPUT BIAS CURRENT							
I_B	Input bias current				±10		pA
I_{OS}	Input offset current				±10		
INPUT VOLTAGE RANGE							
V_{CM}	Common-mode voltage range			V–		V+	V
CMRR	Common-mode rejection ratio	V_S = 1.7 V, (V–) < V_{CM} < (V+) – 1.25 V		74	91		dB
		V_S = 5.5 V, (V–) < V_{CM} < (V+) – 1.25 V		80	96		
		V_S = 1.7 V, V_{CM} = 0 V to 1.7 V		60	88		
		V_S = 5.5 V, V_{CM} = 0 V to 5.5 V		68	102		
INPUT CAPACITANCE							
Z_{ID}	Differential				10^{13} || 6		MΩ || pF
Z_{ICM}	Common-mode				10^{13} || 2.5		GΩ || pF
OPEN-LOOP GAIN							
A_{OL}	Open-loop voltage gain	(V–) + 50 mV < V_O < (V+) – 50 mV, R_L = 10 kΩ		97	113		dB
			T_A = –40°C to 125°C		106		
		(V–) + 200 mV < V_O < (V+) – 200 mV, R_L = 2 kΩ		97	112		
			T_A = –40°C to 125°C		105		

Copyright © 2019, Texas Instruments Incorporated

Electrical Characteristics (continued)

at V_S = ±0.85 V to ±2.75 V (V_S = 1.7 V to 5.5 V), T_A = 25°C, R_L = 10 kΩ connected to V_S / 2, V_{CM} = V_S / 2, and V_{OUT} = V_S / 2 (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
OUTPUT						
	Voltage output swing from rail	V_S = 5.5 V, R_L = 10 kΩ		10	20	mV
I_{SC}	Short-circuit current	Sinking, V_S = 5.5 V		–57		mA
		Sourcing, V_S = 5.5 V		66		
POWER SUPPLY						
I_Q	Quiescent current per amplifier	I_O = 0 mA		0.94	1.3	mA
		I_O = 0 mA, T_A = –40°C to 125°C			1.4	

Copyright © 2019, Texas Instruments Incorporated

6.6 Typical Characteristics

at T_A = 25°C, V_S = ±2.5 V, V_{CM} = V_S / 2, R_L = 10 kΩ connected to V_S / 2 (unless otherwise noted)



N = 9904 V_S = ±2.75 V

図 1. Offset Voltage Production Distribution



N = 9904 V_S = ±0.85 V

図 2. Offset Voltage Production Distribution



N = 65

図 3. Offset Voltage Drift Distribution



N = 5 5 typical units

図 4. Offset Voltage vs Temperature



N = 65

図 5. Offset Voltage vs Common Mode Voltage



図 6. Open-Loop Gain and Phase vs Frequency

Copyright © 2019, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±2.5 V, V_{CM} = V_S / 2, R_L = 10 kΩ connected to V_S / 2 (unless otherwise noted)



図 7. Closed-Loop Gain and Phase vs Frequency



図 8. Input Bias Current vs Temperature



図 9. Output Voltage Swing vs Sourcing Output Current (Maximum Supply)



図 10. Output Voltage Swing vs Sinking Output Current (Maximum Supply)



図 11. CMRR vs Frequency



図 12. 0.1-Hz to 10-Hz Noise

Copyright © 2019, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±2.5 V, V_{CM} = V_S / 2, R_L = 10 kΩ connected to V_S / 2 (unless otherwise noted)



図 13. Input Voltage Noise Spectral Density vs Frequency



BW = 80 kHz

V_O = 1 V_{RMS}

図 14. THD+N Ratio vs Frequency



Gain = 1 BW = 80 kHz

f_{TEST} = 1 kHz

図 15. THD+N vs Output Amplitude



Gain = –1 BW = 80 kHz

f_{TEST} = 1 kHz

図 16. THD+N vs Output Amplitude



5 typical units

図 17. Quiescent Current vs Temperature



5 typical units

図 18. Quiescent Current vs Supply

Copyright © 2019, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±2.5 V, V_{CM} = V_S / 2, R_L = 10 kΩ connected to V_S / 2 (unless otherwise noted)



図 19. Open-Loop Gain vs Temperature



図 20. Open-Loop Output Impedance vs Frequency



10-mV Step

図 21. Small-Signal Overshoot vs Capacitive Load



図 22. No Phase Reversal



図 23. Positive Overload Recovery



図 24. Negative Overload Recovery

Copyright © 2019, Texas Instruments Incorporated

Typical Characteristics (continued)

at T_A = 25°C, V_S = ±2.5 V, V_{CM} = V_S / 2, R_L = 10 kΩ connected to V_S / 2 (unless otherwise noted)



10-mV step G = +1

図 25. Small-Signal Step Response



10-mV step G = –1

図 26. Small-Signal Step Response



2-V Step

図 27. Settling Time



図 28. Short-Circuit Current vs Temperature



図 29. Maximum Output Voltage vs Frequency

Copyright © 2019, Texas Instruments Incorporated

7 Detailed Description

7.1 Overview

The OPA1671 is a rail-to-rail input, very low noise operational amplifier (op amp). The OPA1671 operates from 1.7 V to 5.5 V, is unity-gain stable, and is designed for a wide range of audio and general-purpose applications. The OPA1671 strengths also include 13-MHz bandwidth and 4.0-nV/√Hz noise spectral density, with very low input bias current (10 pA). These strengths make the OPA1671 a great choice for a preamplifier in microphone circuits, sensor modules and buffering high-fidelity, digital-to-analog converters (DACs).

7.2 Functional Block Diagram



Copyright © 2019, Texas Instruments Incorporated

7.3 Feature Description

7.3.1 Operating Voltage

The OPA1671 op amp can be used with single or dual supplies from an operating range of V_S = 1.7 V (±0.85 V) up to 5.5 V (±2.75 V).

> **注意**
>
> Supply voltages greater than 6 V can permanently damage the device (see *Absolute Maximum Ratings*)

Key parameters that vary over the supply voltage or temperature range are shown in the *Typical Characteristics* section.

7.3.2 Input Bias Current

Typically, input bias current is approximately ±10 pA. Input voltages exceeding the power supplies, however, can cause excessive current to flow into or out of the input pins. Momentary voltages greater than the power supply can be tolerated if the input current is limited to 10 mA. This limitation is easily accomplished with an input resistor, as shown in 図 30.

Unlike many operational amplifiers, there are no diodes connected between the positive and negative input terminals. As a result, differential voltages up to the full supply voltage do not cause any significantly higher current flow into the inputs.



図 30. Input Current Protection

7.3.3 Common-Mode Voltage Range

The OPA1671 features true rail-to-rail inputs, allowing full common mode operation from the negative supply voltage to the positive supply voltage. This full common mode operation is achieved with complimentary N-channel and P-channel differential input pairs. The N-channel pair is active for input voltages close to the positive rail, typically (V+) – 1.25 V to (V+) The P-channel is active for common-mode inputs from (V–) to (V+) – 1.25 V. There is a small transition region, typically from (V+) – 1.25 V to (V+) – 1 V. In this region, the offset voltage transitions between the P-channel and N-channel offset values. 図 5 shows the difference between offset in the P and N regions.

Copyright © 2019, Texas Instruments Incorporated

Feature Description (continued)

7.3.4 EMI Susceptibility and Input Filtering

Operational amplifiers vary in susceptibility to EMI. If conducted EMI enters the operational amplifier, the dc offset at the amplifier output can shift from its nominal value when EMI is present. This shift is a result of signal rectification associated with the internal semiconductor junctions. Although all operational amplifier pin functions can be affected by EMI, the input pins are likely to be the most susceptible. The OPA1671 operational amplifier incorporates an internal input low-pass filter that reduces the amplifier response to EMI. Both common-mode and differential-mode filtering are provided by the input filter. The filter is designed for a cutoff frequency of approximately 20 MHz (–3 dB), with a rolloff of 20 dB per decade.



図 31. OPA1671 EMIRR vs Frequency

表 1. OPA1671 EMIRR IN+ for Frequencies of Interest

FREQUENCY	APPLICATION OR ALLOCATION	EMIRR IN+
400 MHz	Mobile radio, mobile satellite, space operation, weather, radar, ultra-high frequency (UHF) applications	30 dB
900 MHz	Global system for mobile communications (GSM) applications, radio communication, navigation, GPS (to 1.6 GHz), GSM, aeronautical mobile, UHF applications	38 dB
1.8 GHz	GSM applications, mobile personal communications, broadband, satellite, L-band (1 GHz to 2 GHz)	60 dB
2.4 GHz	802.11b, 802.11g, 802.11n, Bluetooth®, mobile personal communications, industrial, scientific and medical (ISM) radio band, amateur radio and satellite, S-band (2 GHz to 4 GHz)	59 dB
3.6 GHz	Radiolocation, aero communication and navigation, satellite, mobile, S-band	90 dB
5 GHz	802.11a, 802.11n, aero communication and navigation, mobile communication, space and satellite operation, C-band (4 GHz to 8 GHz)	100 dB

7.4 Device Functional Modes

The OPA1671 has a single functional mode and is operational when the power-supply voltage is greater than 1.7 V (±0.85 V). The maximum specified power-supply voltage for the OPA1671 is 5.5 V (±2.75 V).

Copyright © 2019, Texas Instruments Incorporated

8 Application and Implementation

注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

The OPA1671 is a low-noise, rail-to-rail input and output operational amplifier specifically designed for portable applications. The device operates from 1.7 V to 5.5 V, is unity-gain stable, and suitable for a wide range of audio and general-purpose applications. The class AB output stage is capable of driving ≤ 10-kΩ loads connected to any point between V+ and ground. The input common-mode voltage range includes both rails, and allows the OPA1671 device to be used in virtually any single-supply application. Rail-to-rail input and output swing significantly increases dynamic range, especially in low-supply applications, and makes the device a great choice for driving sampling analog-to-digital converters (ADCs).

8.1.1 Capacitive Loads

The dynamic characteristics of the OPA1671 amplifiers are optimized for commonly encountered gains, loads, and operating conditions. The combination of low closed-loop gain and high capacitive loads decreases the phase margin of the amplifier and can lead to gain peaking or oscillations. As a result, heavier capacitive loads must be isolated from the output. Add a small resistor (for example, R_S = 50 Ω) in series with the output to isolate heavier capacitive loads.

8.1.2 Noise Performance

図 31 shows the total circuit noise for varying source impedances with the operational amplifier in a unity-gain configuration (with no feedback resistor network and therefore no additional noise contributions). The op amp itself contributes a voltage noise component and a current noise component. The voltage noise is commonly modeled as a time-varying component of the offset voltage. The current noise is modeled as the time-varying component of the input bias current and reacts with the source resistance to create a voltage component of noise. For a CMOS-input device, the noise resulting from the input current is negligible; therefore, the total noise is dominated by the voltage noise of the OPA1671 at low source resistance, and the resistor noise > 1 kΩ.

図 31 shows the calculation of the total circuit noise, with these parameters:

- e_n = voltage noise
- R_S = source impedance
- k = Boltzmann's constant = 1.38 × 10^{-23} J/K
- T = temperature in kelvins (K)

For more details on calculating noise, see *Basic Noise Calculations*.



図 32. Noise Performance of the OPA1671 in a Unity-Gain Buffer Configuration

Copyright © 2019, Texas Instruments Incorporated

Application Information (continued)

8.1.3 Basic Noise Calculations

Low-noise circuit design requires careful analysis of all noise sources. External noise sources can dominate in many cases; consider the effect of source resistance on overall op amp noise performance. Total noise of the circuit is the root-sum-square combination of all noise components.

The resistive portion of the source impedance produces thermal noise proportional to the square root of the resistance. This function is plotted in 図 31. The source impedance is typically fixed; consequently, select the op amp and the feedback resistors to minimize the respective contributions to the total noise.

図 33 shows noninverting **(A)** and inverting **(B)** op amp circuit configurations with gain. In circuit configurations with gain, the feedback network resistors contribute noise. In general, the current noise of the op amp reacts with the feedback resistors to create additional noise components.

The selected feedback resistor values make these noise sources negligible. Low impedance feedback resistors load the output of the amplifier. The equations for total noise are shown for both configurations.

(A) Noise in Noninverting Gain Configuration



Noise at the output is given as E_O, where

$$(1)\quad E_O = \left(1+\frac{R_2}{R_1}\right)\cdot\sqrt{(e_S)^2+(e_N)^2+\left(e_{R_1\|R_2}\right)^2+(i_N\cdot R_S)^2+\left(i_N\cdot\left[\frac{R_1\cdot R_2}{R_1+R_2}\right]\right)^2}\quad [\,V_{RMS}\,]$$

$$(2)\quad e_S = \sqrt{4\cdot k_B\cdot T(K)\cdot R_S}\quad \left[\frac{V}{\sqrt{Hz}}\right]$$ Thermal noise of R_S

$$(3)\quad e_{R_1\|R_2} = \sqrt{4\cdot k_B\cdot T(K)\cdot\left[\frac{R_1\cdot R_2}{R_1+R_2}\right]}\quad \left[\frac{V}{\sqrt{Hz}}\right]$$ Thermal noise of R_1 || R_2

$$(4)\quad k_B = 1.38065\cdot 10^{-23}\quad \left[\frac{J}{K}\right]$$ Boltzmann Constant

$$(5)\quad T(K) = 237.15 + T(°C)\quad [\,K\,]$$ Temperature in kelvins

(B) Noise in Inverting Gain Configuration



Noise at the output is given as E_O, where

$$(6)\quad E_O = \left(1+\frac{R_2}{R_S+R_1}\right)\cdot\sqrt{(e_N)^2+\left(e_{R_1+R_S\|R_2}\right)^2+\left(i_N\cdot\left[\frac{(R_S+R_1)\cdot R_2}{R_S+R_1+R_2}\right]\right)^2}\quad [\,V_{RMS}\,]$$

$$(7)\quad e_{R_1+R_S\|R_2} = \sqrt{4\cdot k_B\cdot T(K)\cdot\left[\frac{(R_S+R_1)\cdot R_2}{R_S+R_1+R_2}\right]}\quad \left[\frac{V}{\sqrt{Hz}}\right]$$ Thermal noise of (R_1 + R_S) || R_2

$$(8)\quad k_B = 1.38065\cdot 10^{-23}\quad \left[\frac{J}{K}\right]$$ Boltzmann Constant

$$(9)\quad T(K) = 237.15 + T(°C)\quad [\,K\,]$$ Temperature in kelvins

Copyright © 2017, Texas Instruments Incorporated

(1) e_N is the voltage noise of the amplifier. For the OPA1671 series of operational amplifiers, e_N = 4.0 nV/√Hz at 10 kHz.
(2) i_N is the current noise of the amplifier. For the OPA1671 series of operational amplifiers, i_N = 4.5 fA/√Hz at 1 kHz.
(3) For additional resources on noise calculations, see *TI's Precision Labs Series*.

図 33. Noise Calculation in Gain Configurations

Copyright © 2019, Texas Instruments Incorporated

8.2 Typical Application

This design uses an OPA1671 as a preamplifier for an electret microphone. Electret microphone types are common in many audio applications of varying performance levels. The OPA1671 offers very low noise in a tiny package, and is designed for use in electret preamplifier circuits.

図 34 shows the solution.



図 34. Electret Preamplifier Schematic

8.2.1 Design Requirements

This solution has the following requirements:

- Supply voltage: 5 V
- Gain: 100 V/V
- Frequency response: 3 dB from 20 Hz to 20 kHz
- Output: 2.5 V ±1 V
- Output noise density: < 1 µV/$\sqrt{\text{Hz}}$ at 10 kHz

Copyright © 2019, Texas Instruments Incorporated

Typical Application (continued)

8.2.2 Detailed Design Procedure

The preamplifier circuit uses a noninverting gain configuration to allow for high input impedance, with independent gain-setting resistor values. DC bypass is accomplished with C_2 and C_3, with the low frequency poles set by C_2, R_4, C_3 and R_5; see 式 1 and 式 2.

$$p_{L1} = \frac{1}{2\pi \cdot (R_3 \,||\, R_4) \cdot C_2} = 3.18 \text{ Hz} \tag{1}$$

$$p_{L2} = \frac{1}{2\pi \cdot R_5 \cdot C_2} = 3.23 \text{ Hz} \tag{2}$$

The filter cutoff frequency is determined by a higher frequency pole, set by R_5 and C_4.

$$p_H = \frac{1}{2\pi \cdot R_6 \cdot C_4} = 21.3 \text{ kHz} \tag{3}$$

The gain of the circuit in the passband is set by R_5 and R_6.

$$A(V/V) = \frac{R_6}{R_5} = 100 (40 \text{ dB}) \tag{4}$$

The ouput noise of the circuit (ignoring the electret microphone intrinsic noise and impedance) is the RSS average noise contribution from R_5 and the input voltage noise of OPA1671. R_5 was selected for minimal noise contribution without requiring a dc blocking cap. (C3) larger than 10 µF. See 式 5 for the output noise density calculation at 10 kHz.

$$e_{N_OUT} = \text{Input Referred Noise} \cdot \text{Gain} = \sqrt{(4kTR_5)^2 + V_{N_10k}{}^2} \cdot 100 = 0.96 \text{ µV}/\sqrt{\text{Hz}} \tag{5}$$

8.2.3 Application Curves



図 35. Electret Microphone Preamplifier Transfer Function



図 36. Electret Microphone Preamplifier Output Noise Density

Copyright © 2019, Texas Instruments Incorporated

9 Power Supply Recommendations

The OPA1671 device is specified for operation from 1.7 V to 5.5 V (±0.85 V to ±2.75 V).

10 Layout

10.1 Layout Guidelines

Paying attention to good layout practice is always recommended. Keep traces short and, when possible, use a printed-circuit board (PCB) ground plane with surface-mount components placed as close to the device pins as possible. Place a 0.1-µF capacitor closely across the supply pins. These guidelines must be applied throughout the analog circuit to improve performance and provide benefits such as reducing the electromagnetic interference (EMI) susceptibility.

10.2 Layout Example



図 37. OPA1671 Layout Example

Copyright © 2019, Texas Instruments Incorporated

11 デバイスおよびドキュメントのサポート

11.1 デバイス・サポート

11.1.1 開発サポート

11.1.1.1 TINA-TI™(無料のダウンロード・ソフトウェア)

TINA-TI™は、SPICEエンジンをベースにした単純かつ強力な、使いやすい回路シミュレーション・プログラムです。TINA-TI™は TINA™ソフトウェアの無料バージョンで、完全な機能を持ち、パッシブとアクティブ両方のモデルに加えて、マクロ・モデルのライブラリがプリロードされています。TINA-TI™には従来型のDC、過渡、および周波数ドメインのSPICEによる分析と、追加の設計機能が搭載されています。

TINA-TI™はAnalog eLab Design Centerから無料でダウンロードでき、ユーザーが結果をさまざまな方法でフォーマットできる、広範な後処理機能を備えています。仮想計測器により、入力波形を選択し、回路ノード、電圧、および波形をプローブして、動的なクイック・スタート・ツールを作成できます。

注

これらのファイルを使用するには、TINA ソフトウェア (DesignSoft™製) またはTINA-TI™ソフトウェアがインストールされている必要があります。TINA-TI™フォルダから、無料のTINA-TI™ソフトウェアをダウンロードしてください。

11.2 ドキュメントのサポート

11.2.1 関連資料

関連資料については、以下を参照してください。

- テキサス・インスツルメンツ、*『回路基板のレイアウト技法』*
- テキサス・インスツルメンツ、*『アナログ・エンジニア向け回路クックブック』*

11.3 ドキュメントの更新通知を受け取る方法

ドキュメントの更新についての通知を受け取るには、ti.comのデバイス製品フォルダを開いてください。右上の「アラートを受け取る」をクリックして登録すると、変更されたすべての製品情報に関するダイジェストを毎週受け取れます。変更の詳細については、修正されたドキュメントに含まれている改訂履歴をご覧ください。

11.4 コミュニティ・リソース

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™ Online Community ***TI's Engineer-to-Engineer (E2E) Community.*** Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

Design Support ***TI's Design Support*** Quickly find helpful E2E forums along with design support tools and contact information for technical support.

Copyright © 2019, Texas Instruments Incorporated

11.5 商標

TINA-TI, E2E are trademarks of Texas Instruments.
Bluetooth is a registered trademark of Bluetooth SIG, Inc.
TINA, DesignSoft are trademarks of DesignSoft, Inc.
All other trademarks are the property of their respective owners.

11.6 静電気放電に関する注意事項

すべての集積回路は、適切なESD保護方法を用いて、取扱いと保存を行うようにして下さい。

静電気放電はわずかな性能の低下から完全なデバイスの故障に至るまで、様々な損傷を与えます。高精度の集積回路は、損傷に対して敏感であり、極めてわずかなパラメータの変化により、デバイスに規定された仕様に適合しなくなる場合があります。

11.7 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

12 メカニカル、パッケージ、および注文情報

以降のページには、メカニカル、パッケージ、および注文に関する情報が記載されています。これらの情報は、指定のデバイスに対して提供されている最新のデータです。このデータは予告なく変更されることがあり、ドキュメントが改訂される場合もあります。本データシートのブラウザ版を使用されている場合は、画面左側の説明をご覧ください。

Copyright © 2019, Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
OPA1671IDBVR	ACTIVE	SOT-23	DBV	5	3000	RoHS & Green	NIPDAU | SN	Level-2-260C-1 YEAR	-40 to 125	1X6T	Samples
OPA1671IDBVT	ACTIVE	SOT-23	DBV	5	250	RoHS & Green	NIPDAU | SN	Level-2-260C-1 YEAR	-40 to 125	1X6T	Samples
OPA1671IDCKR	ACTIVE	SC70	DCK	5	3000	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	1D3	Samples
OPA1671IDCKT	ACTIVE	SC70	DCK	5	250	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	1D3	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) **RoHS:** TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".
RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.
Green: TI defines "Green" to mean the content of Chlorine (Cl) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and

continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals.
TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
OPA1671IDBVR	SOT-23	DBV	5	3000	180.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3
OPA1671IDBVT	SOT-23	DBV	5	250	180.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3
OPA1671IDCKR	SC70	DCK	5	3000	178.0	9.0	2.4	2.5	1.2	4.0	8.0	Q3
OPA1671IDCKT	SC70	DCK	5	250	178.0	9.0	2.4	2.5	1.2	4.0	8.0	Q3

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
OPA1671IDBVR	SOT-23	DBV	5	3000	210.0	185.0	35.0
OPA1671IDBVT	SOT-23	DBV	5	250	210.0	185.0	35.0
OPA1671IDCKR	SC70	DCK	5	3000	190.0	190.0	30.0
OPA1671IDCKT	SC70	DCK	5	250	190.0	190.0	30.0

PACKAGE OUTLINE

DBV0005A

SOT-23 - 1.45 mm max height

SMALL OUTLINE TRANSISTOR



ALTERNATIVE PACKAGE SINGULATION VIEW

4214839/J 02/2024

NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. Refernce JEDEC MO-178.
4. Body dimensions do not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.25 mm per side.
5. Support pin may differ or may not be present.



LAND PATTERN EXAMPLE
EXPOSED METAL SHOWN
SCALE:15X



SOLDER MASK DETAILS

4214839/J 02/2024

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SOLDER PASTE EXAMPLE
BASED ON 0.125 mm THICK STENCIL
SCALE:15X

4214839/J 02/2024

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

PACKAGE OUTLINE

DCK0005A

SOT - 1.1 max height

SMALL OUTLINE TRANSISTOR



4214834/D 07/2023

NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. Refernce JEDEC MO-203.
4. Support pin may differ or may not be present.
5. Lead width does not comply with JEDEC.



LAND PATTERN EXAMPLE
EXPOSED METAL SHOWN
SCALE:18X



SOLDER MASK DETAILS

4214834/D 07/2023

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SOLDER PASTE EXAMPLE
BASED ON 0.125 THICK STENCIL
SCALE:18X

4214834/D 07/2023

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

重要なお知らせと免責事項

TI は、技術データと信頼性データ (データシートを含みます)、設計リソース (リファレンス· デザインを含みます)、アプリケーションや設計に関する各種アドバイス、Web ツール、安全性情報、その他のリソースを、欠陥が存在する可能性のある「現状のまま」提供しており、商品性および特定目的に対する適合性の黙示保証、第三者の知的財産権の非侵害保証を含むいかなる保証も、明示的または黙示的にかかわらず拒否します。

これらのリソースは、TI 製品を使用する設計の経験を積んだ開発者への提供を意図したものです。(1) お客様のアプリケーションに適した TI 製品の選定、(2) お客様のアプリケーションの設計、検証、試験、(3) お客様のアプリケーションに該当する各種規格や、その他のあらゆる安全性、セキュリティ、規制、または他の要件への確実な適合に関する責任を、お客様のみが単独で負うものとします。

上記の各種リソースは、予告なく変更される可能性があります。これらのリソースは、リソースで説明されている TI 製品を使用するアプリケーションの開発の目的でのみ、TI はその使用をお客様に許諾します。これらのリソースに関して、他の目的で複製することや掲載することは禁止されています。TI や第三者の知的財産権のライセンスが付与されている訳ではありません。お客様は、これらのリソースを自身で使用した結果発生するあらゆる申し立て、損害、費用、損失、責任について、TI およびその代理人を完全に補償するものとし、TI は一切の責任を拒否します。

TI の製品は、TI の販売条件、または ti.com やかかる TI 製品の関連資料などのいずれかを通じて提供する適用可能な条項の下で提供されています。TI がこれらのリソースを提供することは、適用される TI の保証または他の保証の放棄の拡大や変更を意味するものではありません。

お客様がいかなる追加条項または代替条項を提案した場合でも、TI はそれらに異議を唱え、拒否します。

郵送先住所：Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2024, Texas Instruments Incorporated