TEXAS INSTRUMENTS
OPA2313-Q1
JAJSGL4 – DECEMBER 2018

OPA2313-Q1 低消費電力、レール・ツー・レール入出力、オフセット標準値500µV、低コスト・システム用1MHzオペアンプ

1 特長

- 車載アプリケーション用にAEC-Q100認定済み
  - デバイス温度グレード1
    -40°C～+125°C、T_A
- 低コストのシステム用の高精度アンプ
- 低いI_Q: 50µA/ch
- 広い電源電圧範囲: 1.8V～5.5V
- 低ノイズ：25nV/√Hz（1kHz時）
- ゲイン帯域幅: 1MHz
- レール・ツー・レール入出力
- 低い入力バイアス電流: 0.2pA
- 低いオフセット電圧: 0.5mV
- ユニティ・ゲイン安定
- 内部RFI/EMIフィルタ

2 アプリケーション

- インフォテインメント
- エンジン制御ユニット
- 車載照明
- ローサイド・センシング
- バッテリ管理システム
- パッシブ型安全運転支援システム
- 静電容量式センシング
- 燃料ポンプ

3 概要

OPA2313-Q1デュアル・チャネル・オペアンプは、低消費電力と優れた性能を両立した製品です。これによって、インフォテインメント、エンジン制御ユニット、車載用照明など広範な用途に使用できます。OPA2313-Q1はレール・ツー・レール入出力(RRIO)、低い静止電流（標準値50µA）、広い帯域幅(1MHz)、非常に低いノイズ（1kHzにおいて25nV/√Hz）が特長で、コストと性能の適切なバランスが必要な各種のアプリケーションに適しています。さらに、入力バイアス電流が小さいため、このデバイスはソース・インピーダンスがメガオーム単位のアプリケーションでも使用できます。

OPA2313-Q1は堅牢に設計されており、150pFまでの容量性負荷に対するユニティ・ゲイン安定性、RFI/EMI除去フィルタの搭載、オーバードライブ状態で位相反転が発生しない、高い静電放電(ESD)保護(4kV HBM)といった特長があるため、回路設計が容易です。

これらのデバイスは、1.8V (±0.9V)～5.5V (±2.75V)の電圧で動作するよう最適化され、拡張温度範囲の-40℃ ～+125℃での動作が規定されています。

製品情報(1)

型番	パッケージ	本体サイズ（公称）
OPA2313-Q1	SOIC (8)	4.90mm×3.91mm
	VSSOP (8)	3.00mm×3.00mm

(1) 提供されているすべてのパッケージについては、データシートの末尾にある注文情報を参照してください。

EMIRR IN+と周波数との関係



英語版のTI製品についての情報を翻訳したこの資料は、製品の概要を確認する目的で便宜的に提供しているものです。該当する正式な英語版の最新情報は、www.ti.comで閲覧でき、その内容が常に優先されます。TIでは翻訳の正確性および妥当性につきましては一切保証いたしません。実際の設計などの前には、必ず最新版の英語版をご参照くださいますようお願いいたします。

目次

1 特長 ... 1
2 アプリケーション ... 1
3 概要 ... 1
4 改訂履歴 ... 2
5 **Pin Configuration and Functions** ... 3
6 **Specifications** ... 4
6.1 Absolute Maximum Ratings ... 4
6.2 ESD Ratings ... 4
6.3 Recommended Operating Conditions ... 4
6.4 Thermal Information ... 4
6.5 Electrical Characteristics: 5.5 V ... 5
6.6 Electrical Characteristics: 1.8 V ... 7
6.7 Typical Characteristics: Tables of Graphs ... 9
6.8 Typical Characteristics ... 10
7 **Detailed Description** ... 16
7.1 Overview ... 16
7.2 Functional Block Diagram ... 16
7.3 Feature Description ... 17
7.4 Device Functional Modes ... 18
8 **Application and Implementation** ... 19
8.1 Application Information ... 19
8.2 Typical Application ... 19
8.3 System Examples ... 20
9 **Power Supply Recommendations** ... 21
10 **Layout** ... 22
10.1 Layout Guidelines ... 22
10.2 Layout Example ... 22
11 デバイスおよびドキュメントのサポート ... 23
11.1 ドキュメントのサポート ... 23
11.2 ドキュメントの更新通知を受け取る方法 ... 23
11.3 コミュニティ・リソース ... 23
11.4 商標 ... 23
11.5 静電気放電に関する注意事項 ... 23
11.6 Glossary ... 23
12 メカニカル、パッケージ、および注文情報 ... 23

4 改訂履歴

日付	リビジョン	注
2018年12月	*	初版

Copyright © 2018, Texas Instruments Incorporated

5 Pin Configuration and Functions

OPA2313-Q1 D, DGK Packages
8-Pin SOIC, VSSOP
Top View



Not to scale

Pin Functions: OPA2313-Q1

PIN		I/O	DESCRIPTION
NAME	NO.		
IN1–	2	I	Inverting input, channel 1
IN1+	3	I	Noninverting input, channel 1
IN2–	6	I	Inverting input, channel 2
IN2+	5	I	Noninverting input, channel 2
OUT1	1	O	Output, channel 1
OUT2	7	O	Output, channel 2
V–	4	—	Negative (lowest) supply or ground (for single-supply operation)
V+	8	—	Positive (highest) supply

Copyright © 2018, Texas Instruments Incorporated

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

		MIN	MAX	UNIT
Voltage	Supply voltage (V+) – (V–)	0	7	V
	Signal input terminals(2)	(V–) – (0.5)	(V+) + 0.5	
Current	Signal input terminals(2)	–10	10	mA
	Output short circuit(3)	Continuous		
Temperature	Operating, T_A	–40	150	°C
	Junction, T_J		150	
	Storage, T_{stg}	–65	150	

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) Input pins are diode-clamped to the power-supply rails. Input signals that may swing more than 0.5 V beyond the supply rails must be current limited to 10 mA or less.
(3) Short-circuit to ground, one amplifier per package.

6.2 ESD Ratings

		VALUE	UNIT
$V_{(ESD)}$ Electrostatic discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001(1) HBM ESD Classification Level 3A	±4000	V
	Charged-device model (CDM), per JEDEC specification JESD22-C101(2) CDM ESD Classification Level C6	±1000	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	MAX	UNIT
V_S	Supply voltage (V+) – (V–)	1.8	5.5	V
T_A	Specified temperature	–40	125	°C

6.4 Thermal Information

THERMAL METRIC(1)		OPA2313-Q1		UNIT
		D (SOIC)	DGK (VSSOP)	
		8 Pins	8 Pins	
$R_{\theta JA}$	Junction-to-ambient thermal resistance	138.4	191.2	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	89.5	61.9	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	78.6	111.9	°C/W
ψ_{JT}	Junction-to-top characterization parameter	29.9	5.1	°C/W
ψ_{JB}	Junction-to-board characterization parameter	78.1	110.2	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report.

Copyright © 2018, Texas Instruments Incorporated

6.5 Electrical Characteristics: 5.5 V[1]

For V_S= (V+) – (V–) = 5.5 V at T_A = 25°C, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, (unless otherwise noted)[1]

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
OFFSET VOLTAGE							
V_{OS}	Input offset voltage				0.5	2.5	mV
dV_{OS}/dT	Input offset voltage vs temperature		T_A = –40°C to 125°C		2		µV/°C
PSRR	Power-supply rejection ratio		T_A = –40°C to 125°C	74	90		dB
	Channel separation, dc	At dc			10		µV/V
INPUT VOLTAGE RANGE							
V_{CM}	Common-mode voltage range	No phase reversal, rail-to-rail input		(V–) – 0.2		(V+) + 0.2	V
CMRR	Common-mode rejection ratio	(V–) – 0.2 V < V_{CM} < (V+) – 1.3 V	T_A = –40°C to 125°C	70	85		dB
		V_{CM} = –0.2 V to 5.7 V	T_A = –40°C to 125°C	64	80		
INPUT BIAS CURRENT							
I_B	Input bias current				±0.2	±10	pA
			T_A = –40°C to 85°C[2]			±50	
			T_A = –40°C to 125°C[2]			±600	
I_{OS}	Input offset current				±0.2	±10	pA
			T_A = –40°C to 85°C[2]			±50	
			T_A = –40°C to 125°C[2]			±600	
NOISE							
	Input voltage noise (peak-to-peak)	f = 0.1 Hz to 10 Hz			6		$µV_{PP}$
e_n	Input voltage noise density	f = 10 kHz			22		$nV/\sqrt{Hz}$
		f = 1 kHz			25		
i_n	Input current noise density	f = 1 kHz			5		$fA/\sqrt{Hz}$
INPUT CAPACITANCE							
C_{IN}	Differential				1		pF
	Common-mode				5		
OPEN-LOOP GAIN							
A_{OL}	Open-loop voltage gain	0.05 V < V_O < (V+) – 0.05 V, R_L = 100 kΩ		90	104		dB
		0.3 V < V_O < (V+) – 0.3 V, R_L = 2 kΩ		100	110		
		0.1 V < V_O < (V+) – 0.1 V	T_A = –40°C to 125°C	104	116		
	Phase margin	V_S = 5 V, G = +1			65		°
FREQUENCY RESPONSE							
GBW	Gain-bandwidth product	V_S = 5 V, C_L = 10 pF			1		MHz
SR	Slew rate	V_S = 5 V, G = +1			0.5		V/µs
t_S	Settling time	To 0.1%, V_S = 5 V, 2-V step, G = +1			5		µs
		To 0.01%, V_S = 5 V, 2-V step, G = +1			6		
	Overload recovery time	V_S = 5 V, V_{IN} × Gain > V_S			3		
THD+N	Total harmonic distortion + noise[3]	V_S = 5 V, V_O = 1 V_{RMS}, G = +1, f = 1 kHz			0.0045%		
OUTPUT							
V_O	Voltage output swing from supply rails	R_L = 100 kΩ[2]			5	20	mV
		R_L = 100 kΩ[2]	T_A = –40°C to 125°C			30	
		R_L = 2 kΩ[2]			75	100	
		R_L = 2 kΩ[2]	T_A = –40°C to 125°C			125	
I_{SC}	Short-circuit current				±15		mA
			T_A = –40°C to 125°C		±12		
R_O	Open-loop output impedance				2300		Ω

(1) Parameters with minimum or maximum specification limits are 100% production tested at 25°C, unless otherwise noted. Over-temperature limits are based on characterization and statistical analysis.
(2) Specified by design and characterization; not production tested.
(3) Third-order filter; bandwidth = 80 kHz at –3 dB.

Copyright © 2018, Texas Instruments Incorporated

Electrical Characteristics: 5.5 V(1) (continued)

For V_S= (V+) – (V–) = 5.5 V at T_A = 25°C, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, (unless otherwise noted)(1)

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
POWER SUPPLY							
V_S	Specified voltage range			1.8 (±0.9)		5.5 (±2.75)	V
I_Q	Quiescent current per amplifier	V_S = 5 V, I_O = 0 mA			50	60	µA
		V_S = 5 V, I_O = 0 mA	T_A = –40°C to 125°C			85	
	Power-on time	V_S = 0 V to 5 V, to 90% I_Q level			10		µs

Copyright © 2018, Texas Instruments Incorporated

6.6 Electrical Characteristics: 1.8 V(1)

For V_S= (V+) – (V–) = 1.8 V at T_A = 25°C, R_L = 10 kΩ connected to V_S / 2, V_{CM} = V_{S+} – 1.3 V, and V_{OUT} = V_S / 2, (unless otherwise noted)(1)

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
OFFSET VOLTAGE							
V_{OS}	Input offset voltage				0.5	2.5	mV
dV_{OS}/dT	Input offset voltage vs temperature		T_A = –40°C to 125°C		2		µV/°C
PSRR	Power-supply rejection ratio		T_A = –40°C to 125°C	74	90		dB
	Channel separation, dc	At dc			10		µV/V
INPUT VOLTAGE RANGE							
V_{CM}	Common-mode voltage range	No phase reversal, rail-to-rail input		(V–) – 0.2		(V+) + 0.2	V
CMRR	Common-mode rejection ratio	(V–) – 0.2 V < V_{CM} < (V+) – 1.3 V	T_A = –40°C to 125°C	70	85		dB
		V_S= 1.8 V, V_{CM} = –0.2 V to 1.8 V		58	73		
		V_{CM} = –0.2 V to 1.6 V	T_A = –40°C to 125°C	58	70		
INPUT BIAS CURRENT							
I_B	Input bias current				±0.2	±10	pA
			T_A = –40°C to 85°C(2)			±50	
			T_A = –40°C to 125°C(2)			±600	
I_{OS}	Input offset current				±0.2	±10	pA
			T_A = –40°C to 85°C(2)			±50	
			T_A = –40°C to 125°C(2)			±600	
NOISE							
	Input voltage noise (peak-to-peak)	f = 0.1 Hz to 10 Hz			6		$µV_{PP}$
e_n	Input voltage noise density	f = 10 kHz			22		nV/√Hz
		f = 1 kHz			25		
i_n	Input current noise density	f = 1 kHz			5		fA/√Hz
INPUT CAPACITANCE							
C_{IN}	Differential				1		pF
	Common-mode				5		
OPEN-LOOP GAIN							
A_{OL}	Open-loop voltage gain	0.05 V < V_O < (V+) – 0.05 V, R_L = 100 kΩ		100	110		dB
		0.1 V < V_O < (V+) – 0.1 V	T_A = –40°C to 125°C	90	110		
FREQUENCY RESPONSE							
GBW	Gain-bandwidth product	C_L = 10 pF			0.9		MHz
SR	Slew rate	G = +1			0.45		V/µs
t_S	Settling time	To 0.1%, V_S = 5 V, 2-V step, G = +1			5		µs
		To 0.01%, V_S = 5 V, 2-V step, G = +1			6		
	Overload recovery time	V_S = 5 V, V_{IN} × Gain > V_S			3		
THD+N	Total harmonic distortion + noise(3)	V_S = 5 V, V_O = 1 V_{RMS}, G = +1, f = 1kHz			0.0045%		
OUTPUT							
V_O	Voltage output swing from supply rails	R_L = 100 kΩ(2)			5	15	mV
		R_L = 100 kΩ(2)	T_A = –40°C to 125°C			30	
		R_L = 2 kΩ(2)			25	50	
		R_L = 2 kΩ(2)	T_A = –40°C to 125°C			125	
I_{SC}	Short-circuit current				±6		mA
R_O	Open-loop output impedance				2300		Ω

(1) Parameters with minimum or maximum specification limits are 100% production tested at 25°C, unless otherwise noted. Over-temperature limits are based on characterization and statistical analysis.
(2) Specified by design and characterization; not production tested.
(3) Third-order filter; bandwidth = 80 kHz at –3 dB.

Copyright © 2018, Texas Instruments Incorporated

Electrical Characteristics: 1.8 V(1) (continued)

For V_S= (V+) – (V–) = 1.8 V at T_A = 25°C, R_L = 10 kΩ connected to V_S / 2, V_{CM} = V_{S+} – 1.3 V, and V_{OUT} = V_S / 2, (unless otherwise noted)(1)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
POWER SUPPLY						
V_S	Specified voltage range		1.8 (±0.9)		5.5 (±2.75)	V
I_Q	Quiescent current per amplifier	V_S = 5 V, I_O = 0 mA		50	60	µA
	Power-on time	V_S = 0 V to 5 V, to 90% I_Q level		10		µs

Copyright © 2018, Texas Instruments Incorporated

6.7 Typical Characteristics: Tables of Graphs

表 1. Characteristic Performance Measurements

TITLE	FIGURE
Open-Loop Gain and Phase vs Frequency	図 1
Open-Loop Gain vs Temperature	図 2
Quiescent Current vs Supply Voltage	図 3
Quiescent Current vs Temperature	図 4
Offset Voltage Production Distribution	図 5
Offset Voltage Drift Distribution	図 6
Offset Voltage vs Common-Mode Voltage (Maximum Supply)	図 7
Offset Voltage vs Temperature	図 8
CMRR and PSRR vs Frequency (RTI)	図 9
CMRR and PSRR vs Temperature	図 10
0.1-Hz to 10-Hz Input Voltage Noise (5.5 V)	図 11
Input Voltage Noise Spectral Density vs Frequency (1.8 V, 5.5 V)	図 12
Input Voltage Noise vs Common-Mode Voltage (5.5 V)	図 13
Input Bias and Offset Current vs Temperature	図 14
Open-Loop Output Impedance vs Frequency	図 15
Maximum Output Voltage vs Frequency and Supply Voltage	図 16
Output Voltage Swing vs Output Current (over Temperature)	図 17
Closed-Loop Gain vs Frequency, G = 1, –1, 10 (1.8 V)	図 18
Closed-Loop Gain vs Frequency, G = 1, –1, 10 (5.5 V)	図 19
Small-Signal Overshoot vs Load Capacitance	図 20
Phase Margin vs Capacitive Load	図 21
Small-Signal Step Response, Noninverting (1.8 V)	図 22
Small-Signal Step Response, Noninverting (5.5 V)	図 23
Large-Signal Step Response, Noninverting (1.8 V)	図 24
Large-Signal Step Response, Noninverting (5.5 V)	図 25
Positive Overload Recovery	図 26
Negative Overload Recovery	図 27
No Phase Reversal	図 28
Channel Separation vs Frequency (Dual)	図 29
THD+N vs Amplitude (G = +1, 2 kΩ, 10 kΩ)	図 30
THD+N vs Amplitude (G = –1, 2 kΩ, 10 kΩ)	図 31
THD+N vs Frequency (0.5 V_{RMS}, G = +1, 2 kΩ, 10 kΩ)	図 32
EMIRR IN+ vs Frequency	図 33

Copyright © 2018, Texas Instruments Incorporated

6.8 Typical Characteristics

At T_A = 25°C, V_S = 5 V, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, unless otherwise noted.



図 1. Open-Loop Gain and Phase vs Frequency



図 2. Open-Loop Gain vs Temperature



図 3. Quiescent Current vs Supply



図 4. Quiescent Current vs Temperature



図 5. Offset Voltage Production Distribution



図 6. Offset Voltage Drift Distribution

Copyright © 2018, Texas Instruments Incorporated

Typical Characteristics (continued)

At T_A = 25°C, V_S = 5 V, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, unless otherwise noted.



図 7. Offset Voltage vs Common-Mode Voltage



図 8. Offset Voltage vs Temperature



図 9. CMRR and PSRR vs Frequency (Referred-to-Input)



図 10. CMRR and PSRR vs Temperature



図 11. 0.1-Hz to 10-Hz Input Voltage Noise



図 12. Input Voltage Noise Spectral Density vs Frequency

Copyright © 2018, Texas Instruments Incorporated

Typical Characteristics (continued)

At T_A = 25°C, V_S = 5 V, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, unless otherwise noted.



図 13. Voltage Noise vs Common-Mode Voltage



図 14. Input Bias and Offset Current vs Temperature



図 15. Open-Loop Output Impedance vs Frequency



図 16. Maximum Output Voltage vs Frequency and Supply Voltage



図 17. Output Voltage Swing vs Output Current (Over Temperature)



図 18. Closed-Loop Gain vs Frequency (Minimum Supply)

Copyright © 2018, Texas Instruments Incorporated

Typical Characteristics (continued)

At T_A = 25°C, V_S = 5 V, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, unless otherwise noted.



図 19. Closed-Loop Gain vs Frequency (Maximum Supply)



図 20. Small-Signal Overshoot vs Load Capacitance



図 21. Phase Margin vs Capacitive Load



図 22. Small-Signal Pulse Response (Minimum Supply)



図 23. Small-Signal Pulse Response (Maximum Supply)



図 24. Large-Signal Pulse Response (Minimum Supply)

Copyright © 2018, Texas Instruments Incorporated

Typical Characteristics (continued)

At T_A = 25°C, V_S = 5 V, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, unless otherwise noted.



図 25. Large-Signal Pulse Response (Maximum Supply)



図 26. Positive Overload Recovery



図 27. Negative Overload Recovery



図 28. No Phase Reversal



図 29. Channel Separation vs Frequency



図 30. THD+N vs Output Amplitude (Minimum Supply)

Copyright © 2018, Texas Instruments Incorporated

Typical Characteristics (continued)

At T_A = 25°C, V_S = 5 V, R_L = 10 kΩ connected to V_S / 2, and V_{CM} = V_{OUT} = V_S / 2, unless otherwise noted.



図 31. THD+N vs Output Amplitude (Maximum Supply)



図 32. THD+N vs Frequency



図 33. EMIRR IN+ vs Frequency

7 Detailed Description

7.1 Overview

The OPA2313-Q1 is a low-power, rail-to-rail input and output operational amplifier designed for cost-constrained applications. This device operates from 1.8 V to 5.5 V, is unity-gain stable, and suitable for a wide range of general-purpose applications. The class AB output stage is capable of driving loads greater than 10-kΩ connected to any point between V+ and ground. The input common-mode voltage range includes both rails, and allows the OPA2313-Q1 to be used in virtually any single-supply application. Rail-to-rail input and output swing significantly increases dynamic range, especially in low-supply applications, and makes this device ideal for driving sampling analog-to-digital converters (ADCs).

The OPA2313-Q1 features 1-MHz bandwidth and 0.5-V/µs slew rate with only 50-µA supply current per channel, providing good ac performance at very low power consumption. Low frequency (dc) applications are also well served with a low input noise voltage of 25 nV/√Hz at 1 kHz, low input bias current (0.2 pA), and an input offset voltage of 0.5 mV (typical). The typical offset voltage drift is 2 µV/°C; over the full temperature range the input offset voltage changes only 200 µV (0.5 mV to 0.7 mV).

7.2 Functional Block Diagram



Copyright © 2018, Texas Instruments Incorporated

7.3 Feature Description

7.3.1 Operating Voltage

The OPA2313-Q1 device is fully specified and tested from 1.8 V to 5.5 V (±0.9 V to ±2.75 V). Parameters that vary with supply voltage are illustrated in the *Typical Characteristics* section.

7.3.2 Rail-to-Rail Input

The input common-mode voltage range of the OPA2313-Q1 device extends 200 mV beyond the supply rails. This performance is achieved with a complementary input stage: an N-channel input differential pair in parallel with a P-channel differential pair, as shown in the *Functional Block Diagram* section. The N-channel pair is active for input voltages close to the positive rail, typically (V+) – 1.3 V to 200 mV above the positive supply, while the P-channel pair is on for inputs from 200 mV below the negative supply to approximately (V+) – 1.3 V. There is a small transition region, typically (V+) – 1.4 V to (V+) – 1.2 V, in which both pairs are on. This 200-mV transition region may vary up to 300 mV with process variation. Thus, the transition region (both stages on) may range from (V+) – 1.7 V to (V+) – 1.5 V on the low end, up to (V+) – 1.1 V to (V+) – 0.9 V on the high end. Within this transition region, PSRR, CMRR, offset voltage, offset drift, and THD may be degraded compared to device operation outside this region.

7.3.3 Rail-to-Rail Output

Designed as a micro-power, low-noise operational amplifier, the OPA2313-Q1 delivers a robust output drive capability. A class AB output stage with common-source transistors is used to achieve full rail-to-rail output swing capability. For resistive loads up to 10 kΩ, the output swings typically to within 5 mV of either supply rail regardless of the power-supply voltage applied. Different load conditions change the ability of the amplifier to swing close to the rails, as shown in 図 17.

7.3.4 Common-Mode Rejection Ratio (CMRR)

CMRR for the OPA2313-Q1 device is specified in several ways so the best match for a given application may be used; see the *Electrical Characteristics*. First, the CMRR of the device in the common-mode range below the transition region (V_{CM} < (V+) – 1.3 V) is given. This specification is the best indicator of the capability of the device when the application requires use of one of the differential input pairs. Second, the CMRR over the entire common-mode range is specified at (V_{CM} = –0.2 V to 5.7 V). This last value includes the variations seen through the transition region, as shown in 図 7.

7.3.5 Capacitive Load and Stability

The OPA2313-Q1 device is designed to be used in applications where driving a capacitive load is required. As with all op amps, there may be specific instances where the OPA2313-Q1 device may become unstable. The particular op amp circuit configuration, layout, gain, and output loading are some of the factors to consider when establishing whether or not an amplifier is stable in operation. An op amp in the unity-gain (+1-V/V) buffer configuration that drives a capacitive load exhibits a greater tendency to be unstable than an amplifier operated at a higher noise gain. The capacitive load, in conjunction with the op amp output resistance, creates a pole within the feedback loop that degrades the phase margin. The degradation of the phase margin increases as the capacitive loading increases. When operating in the unity-gain configuration, the OPA2313-Q1 device remains stable with a pure capacitive load up to approximately 1 nF. The equivalent series resistance (ESR) of some capacitors (C_L greater than 1 µF) is sufficient to alter the phase characteristics in the feedback loop such that the amplifier remains stable. Increasing the amplifier closed-loop gain allows the amplifier to drive increasingly larger capacitance. This increased capability is evident when observing the overshoot response of the amplifier at higher voltage gains. See the typical characteristic graph, 図 20.

Copyright © 2018, Texas Instruments Incorporated

Feature Description (continued)

One technique for increasing the capacitive load drive capability of the amplifier when it operates in a unity-gain configuration is to insert a small resistor, typically 10 Ω to 20 Ω, in series with the output, as shown in 図 34. This resistor significantly reduces the overshoot and ringing associated with large capacitive loads. One possible problem with this technique is that a voltage divider is created with the added series resistor and any resistor connected in parallel with the capacitive load. The voltage divider introduces a gain error at the output that reduces the output swing.



図 34. Improving Capacitive Load Drive

7.3.6 EMI Susceptibility and Input Filtering

Operational amplifiers vary with regard to the susceptibility of the device to electromagnetic interference (EMI). If conducted EMI enters the op amp, the DC offset observed at the amplifier output may shift from the nominal value while EMI is present. This shift is a result of signal rectification associated with the internal semiconductor junctions. While all op amp pin functions may be affected by EMI, the signal input pins are likely to be the most susceptible. The OPA2313-Q1 device incorporates an internal input low-pass filter that reduces the amplifiers response to EMI. Both common-mode and differential mode filtering are provided by this filter. The filter is designed for a common-mode cutoff frequency of approximately 35 MHz (–3 dB), with a rolloff of 20 dB per decade.

Texas Instruments has developed the ability to accurately measure and quantify the immunity of an operational amplifier over a broad frequency spectrum extending from 10 MHz to 6 GHz. The EMI rejection ratio (EMIRR) metric allows op amps to be directly compared by the EMI immunity. 図 33 illustrates the results of this testing on the OPA2313-Q1 device. Detailed information may be found in *EMI Rejection Ratio of Operational Amplifiers*, available for download from www.ti.com.

7.3.7 Input and ESD Protection

The OPA2313-Q1 device incorporates internal electrostatic discharge (ESD) protection circuits on all pins. In the case of input and output pins, this protection primarily consists of current-steering diodes connected between the input and power-supply pins. The ESD protection diodes also provide in-circuit, input overdrive protection, as long as the current is limited to 10 mA as stated in the *Absolute Maximum Ratings*. 図 35 shows how a series input resistor may be added to the driven input to limit the input current. The added resistor contributes thermal noise at the amplifier input and the value must be kept to a minimum in noise-sensitive applications.



図 35. Input Current Protection

7.4 Device Functional Modes

The OPA2313-Q1 device has a single functional mode. The device is powered on as long as the power-supply voltage is between 1.8 V (±0.9 V) and 5.5 V (±2.75 V).

Copyright © 2018, Texas Instruments Incorporated

8 Application and Implementation

注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

The OPA2313-Q1 device is a low-power, rail-to-rail input and output operational amplifier. The device operates from 1.8 V to 5.5 V, is unity-gain stable, and is designed for a wide range of general-purpose applications. The class AB output stage is capable of driving loads greater than 10 kΩ connected to any point between V+ and ground. The input common-mode voltage range includes both rails, and allows the OPA2313-Q1 to be used in virtually any single-supply application.

8.2 Typical Application

A typical application for an operational amplifier is an inverting amplifier, as shown in 図 36. An inverting amplifier takes a positive voltage on the input and outputs a signal inverted to the input, making a negative voltage of the same magnitude. In the same manner, the amplifier also makes negative input voltages positive on the output. In addition, amplification may be added by selecting the input resistor (R_I) and the feedback resistor (R_F.)



図 36. Inverting Amplifier Application

8.2.1 Design Requirements

The supply voltage must be chosen to be larger than the input voltage range and the desired output range. The limits of the input common-mode range (V_{CM}) and the output voltage swing to the rails (V_O) must also be considered. For instance, this application scales a signal of ±0.5 V (1 V) to ±1.8 V (3.6 V). Setting the supply at ±2.5 V is sufficient to accommodate this application.

8.2.2 Detailed Design Procedure

Determine the gain required by the inverting amplifier using 式 1 and 式 2:

$$A_V = \frac{V_{OUT}}{V_{IN}} \quad (1)$$

$$A_V = \frac{1.8}{-0.5} = -3.6 \quad (2)$$

Copyright © 2018, Texas Instruments Incorporated

Typical Application (continued)

When the desired gain is determined, choose a value for R_I or R_F. Choosing a value in the kilohm range is desirable for general-purpose applications because the amplifier circuit uses currents in the milliamp range. This milliamp current range ensures the device does not draw too much current. The trade-off is that very large resistors (100s of kilohms) draw the smallest current but generate the highest noise. Small resistors (100s of ohms) generate low noise but draw high current. This example uses 10 kΩ for R_I, resulting in a 36-kΩ resistor being used for R_F. The values are determined by 式 3:

$$A_V = -\frac{R_F}{R_I} \tag{3}$$

8.2.3 Application Curve



図 37. Inverting Amplifier Input and Output

8.3 System Examples

When receiving low-level signals, limiting the bandwidth of the incoming signals into the system is often required. The simplest way to establish this limited bandwidth is to place an RC filter at the noninverting terminal of the amplifier, as shown in 図 38.



$$\frac{V_{OUT}}{V_{IN}} = \left(1 + \frac{R_F}{R_G}\right)\left(\frac{1}{1 + sR_1C_1}\right)$$

図 38. Single-Pole Low-Pass Filter

Copyright © 2018, Texas Instruments Incorporated

System Examples (continued)

If even more attenuation is needed, a multiple pole filter is required. The Sallen-Key filter may be used for this task, as shown in 図 39. For best results, the amplifier must have a bandwidth that is 8 to 10 times the filter frequency bandwidth. Failure to follow this guideline may result in phase shift of the amplifier.



図 39. Two-Pole, Low-Pass, Sallen-Key Filter

9 Power Supply Recommendations

The OPA2313-Q1 device is specified for operation from 1.8 V to 5.5 V (±0.9 V to ±2.75 V); many specifications apply from –40°C to +125°C. The *Typical Characteristics* section presents parameters that may exhibit significant variance with regard to operating voltage or temperature.

注意

Supply voltages larger than 7 V can permanently damage the device (see the *Absolute Maximum Ratings* table).

Place 0.1-µF bypass capacitors close to the power-supply pins to reduce errors coupling in from noisy or high-impedance power supplies. For more detailed information on bypass capacitor placement, refer to the *Layout Guidelines* section.

Copyright © 2018, Texas Instruments Incorporated

10 Layout

10.1 Layout Guidelines

For best operational performance of the device, use good printed circuit board (PCB) layout practices, including:

- Noise may propagate into analog circuitry through the power pins of the circuit and the operational amplifier. Use bypass capacitors to reduce the coupled noise by providing low-impedance power sources local to the analog circuitry.
  - Connect low-ESR, 0.1-µF ceramic bypass capacitors between each supply pin and ground, placed as close to the device as possible. A single bypass capacitor from V+ to ground is applicable for single-supply applications.
- Separate grounding for analog and digital portions of the circuitry is one of the simplest and most effective methods of noise suppression. One or more layers on multilayer PCBs are usually devoted to ground planes. A ground plane helps distribute heat and reduces EMI noise pickup. Take care to physically separate digital and analog grounds, paying attention to the flow of the ground current. For more detailed information, see *Circuit Board Layout Techniques*.
- To reduce parasitic coupling, run the input traces as far away from the supply or output traces as possible. If the traces cannot be kept separate, crossing the sensitive trace perpendicularly is much better than crossing in parallel with the noisy trace.
- Place the external components as close to the device as possible. Keep R_F and R_G close to the inverting input to minimize parasitic capacitance, as shown in 図 40.
- Keep the length of input traces as short as possible. Remember that the input traces are the most sensitive part of the circuit.
- Consider a driven, low-impedance guard ring around the critical traces. A guard ring may significantly reduce leakage currents from nearby traces that are at different potentials.

10.2 Layout Example



図 40. Schematic Representation for 図 41



図 41. Layout Example

Copyright © 2018, Texas Instruments Incorporated

11 デバイスおよびドキュメントのサポート

11.1 ドキュメントのサポート

11.1.1 関連資料

関連資料については、以下を参照してください。

- *『オペアンプのEMI除去率』*
- *『基板のレイアウト技法』*

11.2 ドキュメントの更新通知を受け取る方法

ドキュメントの更新についての通知を受け取るには、ti.comのデバイス製品フォルダを開いてください。右上の隅にある「*通知を受け取る*」をクリックして登録すると、変更されたすべての製品情報に関するダイジェストを毎週受け取れます。変更の詳細については、修正されたドキュメントに含まれている改訂履歴をご覧ください。

11.3 コミュニティ・リソース

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™オンライン・コミュニティ ***TIのE2E（Engineer-to-Engineer）コミュニティ。*** **エンジニア間の共同作業を促進するために開設されたものです。e2e.ti.comでは、他のエンジニアに質問し、知識を共有し、アイディアを検討して、問題解決に役立てることができます。**

設計サポート ***TIの設計サポート*** **役に立つE2Eフォーラムや、設計サポート・ツールをすばやく見つけることができます。技術サポート用の連絡先情報も参照できます。**

11.4 商標

E2E is a trademark of Texas Instruments.

11.5 静電気放電に関する注意事項

すべての集積回路は、適切なESD保護方法を用いて、取扱いと保存を行うようにして下さい。

静電気放電はわずかな性能の低下から完全なデバイスの故障に至るまで、様々な損傷を与えます。高精度の集積回路は、損傷に対して敏感であり、極めてわずかなパラメータの変化により、デバイスに規定された仕様に適合しなくなる場合があります。

11.6 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

12 メカニカル、パッケージ、および注文情報

以降のページには、メカニカル、パッケージ、および注文に関する情報が記載されています。この情報は、そのデバイスについて利用可能な最新のデータです。このデータは予告なく変更されることがあり、ドキュメントが改訂される場合もあります。本データシートのブラウザ版を使用されている場合は、画面左側の説明をご覧ください。

Copyright © 2018, Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
OPA2313QDGKRQ1	ACTIVE	VSSOP	DGK	8	2500	RoHS & Green	NIPDAUAG	Level-2-260C-1 YEAR	-40 to 125	23131	Samples
OPA2313QDRQ1	ACTIVE	SOIC	D	8	2500	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	O2313Q	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) **RoHS:** TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".
RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.
Green: TI defines "Green" to mean the content of Chlorine (Cl) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
OPA2313QDGKRQ1	VSSOP	DGK	8	2500	330.0	12.4	5.3	3.4	1.4	8.0	12.0	Q1
OPA2313QDRQ1	SOIC	D	8	2500	330.0	12.4	6.4	5.2	2.1	8.0	12.0	Q1

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
OPA2313QDGKRQ1	VSSOP	DGK	8	2500	366.0	364.0	50.0
OPA2313QDRQ1	SOIC	D	8	2500	340.5	336.1	25.0



PACKAGE OUTLINE

D0008A

SOIC - 1.75 mm max height

SMALL OUTLINE INTEGRATED CIRCUIT



NOTES:

1. Linear dimensions are in inches [millimeters]. Dimensions in parenthesis are for reference only. Controlling dimensions are in inches. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed .006 [0.15] per side.
4. This dimension does not include interlead flash.
5. Reference JEDEC registration MS-012, variation AA.



LAND PATTERN EXAMPLE
EXPOSED METAL SHOWN
SCALE:8X



SOLDER MASK DETAILS

4214825/C 02/2019

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.

EXAMPLE STENCIL DESIGN

D0008A

SOIC - 1.75 mm max height

SMALL OUTLINE INTEGRATED CIRCUIT



SOLDER PASTE EXAMPLE
BASED ON .005 INCH [0.125 MM] THICK STENCIL
SCALE:8X

4214825/C 02/2019

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

DGK (S–PDSO–G8) PLASTIC SMALL–OUTLINE PACKAGE



4073329/E 05/06

NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 per end.
D. Body width does not include interlead flash. Interlead flash shall not exceed 0.50 per side.
E. Falls within JEDEC MO–187 variation AA, except interlead flash.

DGK (S–PDSO–G8) PLASTIC SMALL OUTLINE PACKAGE



NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Publication IPC–7351 is recommended for alternate designs.
D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC–7525 for other stencil recommendations.
E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.

重要なお知らせと免責事項

TI は、技術データと信頼性データ (データシートを含みます)、設計リソース (リファレンス・デザインを含みます)、アプリケーションや設計に関する各種アドバイス、Web ツール、安全性情報、その他のリソースを、欠陥が存在する可能性のある「現状のまま」提供しており、商品性および特定目的に対する適合性の黙示保証、第三者の知的財産権の非侵害保証を含むいかなる保証も、明示的または黙示的にかかわらず拒否します。

これらのリソースは、TI 製品を使用する設計の経験を積んだ開発者への提供を意図したものです。(1) お客様のアプリケーションに適した TI 製品の選定、(2) お客様のアプリケーションの設計、検証、試験、(3) お客様のアプリケーションが適用される各種規格や、その他のあらゆる安全性、セキュリティ、またはその他の要件を満たしていることを確実にする責任を、お客様のみが単独で負うものとします。上記の各種リソースは、予告なく変更される可能性があります。これらのリソースは、リソースで説明されている TI 製品を使用するアプリケーションの開発の目的でのみ、TI はその使用をお客様に許諾します。これらのリソースに関して、他の目的で複製することや掲載することは禁止されています。TI や第三者の知的財産権のライセンスが付与されている訳ではありません。お客様は、これらのリソースを自身で使用した結果発生するあらゆる申し立て、損害、費用、損失、責任について、TI およびその代理人を完全に補償するものとし、TI は一切の責任を拒否します。

TI の製品は、TI の販売約款 (https://www.tij.co.jp/ja-jp/legal/terms-of-sale.html)、または ti.com やかかる TI 製品の関連資料などのいずれかを通じて提供する適用可能な条項の下で提供されています。TI がこれらのリソースを提供することは、適用される TI の保証または他の保証の放棄の拡大や変更を意味するものではありません。

日本語版 日本テキサス・インスツルメンツ合同会社
Copyright © 2021, Texas Instruments Incorporated