

Texas Instruments Robotics System Learning Kit






Module 17

Quiz: Control Systems

Quiz: Control Systems

Q1 Controller

The following shows the speed response of a motor given a step change in duty cycle. The speed changes from 100 to 200 rpm.



Part a) What is the time constant of the motor? Explain how you determine this value

Part b) What time between executions of the digital software is needed to control this motor?

Q2 Fixed point

Let r be the radius of a circle, defined as a fixed point number with constant $\Delta{=}0.01$ cm. Let R be the integer part of the fixed point number. In other words, if r =1.23cm, then the integer R is 123. Let a be the area of a circle, defined as a fixed point number with constant $\Delta{=}0.001$ cm². Let A be the integer part of the fixed point number. In other words, if A = 4.752916 cm², then the integer A is 4753. Write C code that calculates the area of the circle, given R. In other words, let R be the input and A be the output of this C code.

Q3 Definitions

In 32 words or less, define each of these terms

Part a) Controller accuracy.

Part b) Controller stability.

Part c) Overdamped. Draw a picture to explain

Part d) Underdamped. Draw a picture to explain

Q4 Integral controller

Assume the desired speed is **Sstar** and the estimated speed can be obtained by calling the function with the following prototype

uint16_t Speed(void);

Both estimated and desired speed have units in RPM, with a range of 0 to 500 RPM. The actuator is a PWM circuit with a duty cycle range of 0 (0%) to 1000 (100%). Software sets the duty cycle by calling the function with the following prototype

void PWM_Duty(uint16_t duty);

You will run the digital controller every 1 ms. Show the C code to implement this integral controller

e(t) = Sstar-Speed()
U(t) = U(t) + 13.48*e(t)*
$$\Delta$$
t
0 \le U(t) \le 1000

The units of U are duty cycle (0 to 1000). The units of e **Speed()** and S^* are RPM. The units of Δt are seconds (0.001 sec). The units of 13.52 are duty-cycle/RPM/sec.

ti.com/rslk



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2019, Texas Instruments Incorporated