



Table of Contents

1 Introduction.....	2
2 Setting Vout.....	2
3 Optional Components.....	2
4 PCB Layout Diagrams.....	4

Trademarks

All trademarks are the property of their respective owners.

1 Introduction

The LM3475 evaluation board is provided as a tool for developing DC/DC converters based on the LM3475 IC. As shown in [Figure 3-1](#), the evaluation board is configured to provide an output of 2.5 V at up to 2 A from an input up to 10 V. The corresponding bill of material is given in [Table 3-1](#). Typical efficiencies are shown in [Figure 3-2](#) and [Figure 3-3](#). [Figure 4-1](#) and [Figure 4-2](#) show the board layout.

To aid in the design and evaluation of DC/DC buck converters based on the LM3475 controller, the LM3475 evaluation board can be easily re-configured for different output voltages.

2 Setting Vout

V_{OUT} can be set using R_{FB1} , as shown in [Equation 1](#):

$$V_{OUT} = V_{FB} \times (R_{FB1} + R_{FB2}) / R_{FB2} \quad (1)$$

where

- V_{FB} is 0.8 V typically.

See the device-specific data sheet before changing any component values since additional design adjustments can be required.

3 Optional Components

A feedforward capacitor, C_{FF} , is placed on the board, which will increase operating frequency. However, the speed up effect decreases with lower output voltage and is negligible below 1.6-V output.

A 0 Ω is used to pull up the EN pin for always on operation. The enable pin can be pulled low at the EN post to shutdown the device. If this resistor is removed, any analog level signal can be used to enable and disable the device.




Figure 3-1. Full Demo Board Schematic




Figure 3-2. Efficiency vs Output Current ($V_{IN} = 5\text{ V}$)




Figure 3-3. Efficiency vs Input Voltage ($I_{out} = 2\text{ A}$)

Table 3-1. Bill of Materials (BOM)

Designator	Part Description	Part Number
CIN	10 μF , 16-V ceramic	Yuden EMK325BJ106MN
COUT	100 μF , 6-V tantalum	AVX TPSY107M006R0100
CFF	1 nF, 25-V ceramic	VJ1206Y102KXXA
D1	Schottky 20 V, 2 A	Central CMSH2-20L
L1	10 μH , 3.1 A	Sumida CDRH103R100
Q1	Si 2343 30 V, 2.5 A	Vishay Si2343
RFB2	1 k Ω	Vishay CRCW08051001F
RFB1	2.15 k Ω	Vishay CRCW08052151F
R2	0 Ω	Vishay CRCW08050R00F

4 PCB Layout Diagrams




Figure 4-1. Top Side Layout




Figure 4-2. Bottom Side Layout

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on [ti.com](#) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2022, Texas Instruments Incorporated