

Application Note

Camera PMIC Spin Selection Guide



ABSTRACT

There are a wide range of core and emerging vision applications in the automotive industry. Core applications include front, rear, and surround-view cameras. Autonomous driving, mirror replacement, and driver monitoring cameras are some emerging applications as Advanced Driver Assistance Systems (ADAS) become more sophisticated. The automotive image sensor market has several key manufacturers with broad portfolios of sensors to address many of these applications. The portfolios range from low quality (1-2 megapixel image sensors) to high quality (8+ megapixel image sensors) resulting in different supply voltage, current, and power sequencing requirements.

The TPS650320-Q1 and TPS65033x-Q1 family of Power Management Integrated Circuits (PMICs) helps simplify the power design process for these cameras by optimizing solution size and enabling re-usability across many vision applications. The family of PMICs maintains strong performance against varying power requirements across existing and emerging camera applications. Each PMIC is also fully pin-compatible. Without the need for a power circuit redesign, a simple BOM change enables full power design scalability and re-usability from low-end non-functional safety cameras, to high-end functional safety cameras. This guide connects many common automotive image sensors to an appropriate PMIC part number. The part number is a Non-Volatile Memory (NVM) spin with default settings that support the sensor's power requirements.

Table of Contents

1 Camera PMIC Family Overview	2
1.1 Non-Functional Safety Camera PMICs.....	3
1.2 Functional Safety Camera PMICs.....	3
2 Selection Guide	4
3 Revision History	8

List of Figures

Figure 1-1. Camera PMIC Feature Comparison.....	2
---	---

List of Tables

Table 2-1. Camera PMIC NVM Spins.....	4
---------------------------------------	---

Trademarks

All trademarks are the property of their respective owners.

1 Camera PMIC Family Overview

TI offers a variety of camera PMICs with three buck converters and one low-noise LDO designed to support many automotive vision applications. These applications include but are not limited to:

- Rear-View
- Surround-View
- Driver Monitoring
- Cabin Monitoring
- Mirror Replacement
- Autonomous Driving
- Remote Front-View
- Digital Video Recorder (DVR)

The following sections provide a brief overview of features and capabilities. Each camera PMIC is equivalent in terms of regulator performance. The differences between variants are related to the device's feature set. This includes fault detection, fault handling flexibility, and the internal state machine. [Figure 1-1](#) summarizes the differences between versions.

Feature	TPS650320-Q1	TPS650330-Q1	TPS650331-Q1	TPS650332-Q1	TPS650333-Q1
Severe Fault Handling	Reset State OR Wait for Power Cycle State	Reset State OR Wait for Power Cycle State	Wait for Power Cycle State	Reset State OR Wait for Power Cycle State	Reset State OR Wait for Power Cycle State
Less Severe Fault Handling	N/A	Alert State	Wait for Power Cycle State	Safe State	Safe State
I ² C Communication	Only available for TPS65032001-Q1	✓	✓	✓	✓
I ² C Bus CRC in Production		Optional	Required	Required	Required
Option to program NVM in Production	Only available for TPS65032001-Q1	Optional			
nINT		✓	✓	✓	✓
GPIO		✓	✓	✓	✓
Thermal warning	✓	✓	✓	✓	✓
Thermal shutdown	✓	✓	✓	✓	✓
Under-Voltage Lock Out – VSYS	✓	✓	✓	✓	✓
Under-Voltage Lock Out – Buck 1	✓	✓	✓	✓	✓
Over-Voltage Protection – VSYS	✓	✓	✓	✓	✓
Over-Voltage Protection – All Outputs	✓	✓	✓	✓	✓
Over-Current Protection – All Outputs	✓	✓	✓	✓	✓
Short-circuit Monitor – All outputs	✓	✓	✓	✓	✓
Loss of Ground Monitor	✓	✓	✓	✓	✓
Independent Voltage References	✓	✓	✓	✓	✓
Power Good Status Register	✓	✓	✓	✓	✓
Under-Voltage Monitor – All Outputs	✓	✓	✓	✓	✓
Over-Voltage Monitor – All Outputs			✓	✓	✓
ABIST			✓	✓	✓
Watchdog					✓

Figure 1-1. Camera PMIC Feature Comparison

1.1 Non-Functional Safety Camera PMICs

These devices are intended for cameras that do not require functional safety. Some examples may include rear-view camera and surround-view camera. The primary difference from the functional-safety variants lie in fault handling capabilities and state machine behavior.

1.1.1 TPS650320-Q1

The TPS650320-Q1 is a low current PMIC with a reduced feature set designed to cover image sensors with up to around 5-megapixel (MP).

1.1.2 TPS650330-Q1

The TPS650330-Q1 is a high current PMIC with a moderate feature set including GPIO and interrupt pins designed to cover low, medium, and high (8+ MP) quality vision applications.

1.2 Functional Safety Camera PMICs

These devices cover low-end to high-end cameras with an expanded feature set and fault handling capabilities to enable ASIL-B compliance as a Safety Element out of Context (SEooC). Diagnostic capabilities and protection features allow the device to be applied as a component up to ASIL-D(B), provided the system accounts for these capabilities to meet the unique safety goals. The main differences between functional safety variants are the device's fault handling and internal state machine.

1.2.1 TPS650331-Q1

The TPS650331-Q1 has full current capability along with a wide range of fault detection. Any fault detected by this device will transition to the Wait for Power Cycle state. In this state, the output rails are low, and the device will not attempt to power up until the input supply is cycled.

1.2.2 TPS650332-Q1

The TPS650332-Q1 offers more flexibility in terms of fault handling. For more severe faults, the TPS650332-Q1 can be configured to enter the Wait for Power Cycle state or the Reset state. In the reset state, the device will shut down the output rails and immediately attempt to power up again. This device also has a Safe state for less severe faults, in which the output rails remain powered and an interrupt signals the local or remote MCU or processor to decide on the appropriate response.

1.2.3 TPS650333-Q1

The TPS650333-Q1 offers all the fault handling flexibility of the TPS650332-Q1 with an added watchdog monitor. This device is suitable for functional safety applications with a local MCU or processor, including smart rear-cameras or high-end remote front-cameras with a discrete Image Sensor Processor (ISP).

2 Selection Guide

An existing spin may be appropriate based on a target image sensor or vision application. Many of the camera PMIC spins are programmed for default operation with the example image sensors specified in [Table 2-1](#). For sensors that are not listed, an existing spin may still be compatible if it meets the voltage and sequencing requirements specified in the sensor data sheet.

The non-safety catalog spins, the TPS65032001-Q1 and TPS65033000-Q1, are re-programmable in production. This feature enables the compatibility of these spins with many standard automotive image sensors through the socketed or in-circuit programming. For more information on these devices' programming capabilities, see the [BOOSTXL-TPS65033 User's Guide](#) and the [TPS650330Q1EVM User's Guide](#). For complete information regarding each device's default NVM settings, see the corresponding Technical Reference Manual (TRM) on [mySecure](#). Access can be requested through the [TPS650330-Q1 product page](#).

Table 2-1. Camera PMIC NVM Spins

Camera PMIC	Functional Safety	Configurable	I2C Bus CRC	External Enables	Output Voltages and Sequencing	Buck 1 UVLO Thresholds	Logic IOs	Compatible Sensors
TPS65032001-Q1	×	✓	×	SEQ	1) B1 = 3.3 V 2) B2 = 1.8 V 3) B3 = 1.2 V 4) LDO = 2.8 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull	Many
TPS65032002-Q1	×	×	×	None	1) B1 = 3.75 V 2) LDO = 3.3 V 3) B3 = 1.1 V 4) B2 = 1.8 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = open-drain	Omnivision OX01E10 Omnivision OX01F10 Sony IMX490 Sony IMX622 Sony IMX623 Sony ISX021 Sony ISX031
TPS65032006-Q1	×	×	×	None	1) B1 = 3.8 V 2) LDO = 3.3 V 3) B2 = 1.85 V 4) B3 = 1.125 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = open-drain	Omnivision OX01E10 Omnivision OX01F10 Sony IMX490 Sony IMX622 Sony IMX623 Sony ISX021 Sony ISX031
TPS6503200A-Q1	×	×	×	None	1) B1 = 3.8 V 2) LDO = 3.3 V 3) B2 = 1.8 V 4) B3 = 1.1 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = open-drain	Omnivision OX01E10 Omnivision OX01F10 Sony IMX490 Sony IMX622 Sony IMX623 Sony ISX021 Sony ISX031
TPS6503200B-Q1	×	×	×	None	1) B1 = 3.8 V 2) LDO = 3.3 V 3) B2 = 1.8 V 4) B3 = 1.15 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = open-drain	Sony IMX490

Table 2-1. Camera PMIC NVM Spins (continued)

Camera PMIC	Functional Safety	Configurable	I2C Bus CRC	External Enables	Output Voltages and Sequencing	Buck 1 UVLO Thresholds	Logic IOs	Compatible Sensors
TPS6503200C-Q1	×	×	×	None	1) B1 = 3.8 V 2) LDO = 3.3 V 3) B2 = 1.8 V 4) B3 = 1.5 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull	Omnivision OV10640 Omnivision OV10642 Omnivision OV10650
TPS65032018-Q1	×	×	×	None	1) B1 = 3.3 V 2) B3 = 1.8 V 3) B2 = 1.1 V 4) Load Switch ⁽¹⁾	Rising = 5.72 V Falling = 4.5 V	nRSTOUT = open-drain	Omnivision OX01E10 Omnivision OX01F10
TPS65033000-Q1	×	✓	×	SEQ GPIO	1) B1 = 3.3 V 2) B2 = 1.8 V 3) B3 = 1.2 V 4) LDO = 2.8 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Many
TPS65033007-Q1	×	×	×	None	1) B1 = 3.3 V 2) B3 = 1.8 V 3) B2 = 1.2 V 4) LDO = 2.9 V	Rising = 6.24 V Falling = 5.5 V	nRSTOUT = push-pull nINT = push-pull	Sony IMX290 Sony IMX390
TPS6503300D-Q1	×	×	✓	SEQ	1) B1 = 3.3 V 2) LDO = 2.8 V 3) B2 = 1.8 V 4) B3 = 1.2 V	Rising = 5.72 V Falling = 5.0 V	nRSTOUT = push-pull nINT = open-drain	Omnivision OV2311 Omnivision OV2312 Omnivision OV9284 Omnivision OX05B1S ON Semi AR0143 ON Semi AR0144 ON Semi AR0147 ON Semi AR0233
TPS6503300E-Q1	×	×	✓	SEQ	1) B1 = 3.85 V 2) LDO = 3.3 V 3) B2 = 1.8 V 4) B3 = 1.3 V	Rising = 5.72 V Falling = 5.0 V	nRSTOUT = push-pull nINT = open-drain	Omnivision OV2775 Omnivision OV2778
TPS6503300I-Q1	×	✓	×	None	1) B1 = 3.3 V 2) B2 = 1.8 V 3) B3 = 1.1 V 4) LDO = 2.9 V	Rising = 7.28 V Falling = 5.0 V	nRSTOUT = push-pull nINT = push-pull	Sony IMX324 Sony IMX424 Sony ISX019 Sony ISX020
TPS65033104-Q1	✓	×	✓	SEQ	1) B1 = 3.3 V 2) LDO = 2.875 V 3) B2 = 1.8 V 4) B3 = 1.2 V	Rising = 4.68 V Falling = 3.5 V	nRSTOUT = open-drain INT = open-drain	Sony IMX290 Sony IMX390
TPS65033201-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B3 = 1.8 V 3) LDO = 2.8 V 4) B2 = 1.2 V	Rising = 6.76 V Falling = 6.0 V	nRSTOUT = open-drain nINT = open-drain	Omnivision OV9284 ON Semi AR0220 ON Semi AR0820

Table 2-1. Camera PMIC NVM Spins (continued)

Camera PMIC	Functional Safety	Configurable	I2C Bus CRC	External Enables	Output Voltages and Sequencing	Buck 1 UVLO Thresholds	Logic IOs	Compatible Sensors
TPS65033203-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) LDO = 2.8 V 3) B2 = 1.8 V 4) B3 = 1.2 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OV2311 Omnivision OV2312 Omnivision OV9284 Omnivision OX05B1S ON Semi AR0143 ON Semi AR0144 ON Semi AR0147 ON Semi AR0233
TPS65033205-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B2 = 1.8 V 3) Load Switch ⁽²⁾ 4) B3 = 1.1 V	Rising = 5.20 V Falling = 4.5 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OX01E10 Omnivision OX01F10
TPS65033206-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) LDO = 2.8 V 3) B2 = 1.8 V 4) B3 = 1.2 V	Rising = 5.20 V Falling = 4.5 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OV2311 Omnivision OV2312 Omnivision OV9284 Omnivision OX05B1S ON Semi AR0143 ON Semi AR0144 ON Semi AR0147 ON Semi AR0233
TPS65033207-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B2 = 1.8 V 3) LDO = 2.8 V 4) B3 = 1.2 V	Rising = 9.36 V Falling = 8.5 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OV9284 ON Semi AR0220 ON Semi AR0820
TPS65033208-Q1	✓	×	✓	None	1) B1 = 3.8 V 2) LDO = 3.3 V 3) B2 = 1.8 V 4) B3 = 1.1 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OX01E10 Omnivision OX01F10 Sony IMX490 Sony IMX622 Sony IMX623 Sony IMX728 Sony ISX021 Sony ISX031
TPS65033209-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B3 = 1.1 V 3) B2 = 1.8 V 4) LDO = 2.8 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OV2311 ⁽³⁾ Omnivision OV2312 ⁽⁴⁾
TPS6503320AA-Q1	✓	×	✓	None	1) B1 = 4.0 V 2) LDO = 3.3 V 3) B3 = 1.8 V 4) B2 = 1.1 V	Rising = 7.80 V Falling = 5.0 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OX01E10 Omnivision OX01F10 Sony IMX490 Sony IMX622 Sony IMX623 Sony IMX728 Sony ISX021 Sony ISX031

Table 2-1. Camera PMIC NVM Spins (continued)

Camera PMIC	Functional Safety	Configurable	I2C Bus CRC	External Enables	Output Voltages and Sequencing	Buck 1 UVLO Thresholds	Logic IOs	Compatible Sensors
TPS6503320D-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B3 = 1.8 V 3) LDO = 2.8 V 4) B2 = 1.2 V	Rising = 6.76 V Falling = 6.0 V	nRSTOUT = open-drain nINT = open-drain	Omnivision OV9284 ON Semi AR0220 ON Semi AR0820
TPS6503320F-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) LDO = 2.9 V 3) B2 = 1.8 V 4) B3 = 1.1 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Omnivision OX03C10 Omnivision OX03F10 Omnivision OX08A4Y Omnivision OX08B40 Omnivision OX08B4C Sony IMX324 Sony IMX424 Sony ISX019 Sony ISX020
TPS6503320G-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) LDO = 2.9 V 3) B2 = 1.8 V 4) B3 = 1.2 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Sony IMX290 Sony IMX390
TPS6503320HA-Q1	✓	×	✓	SEQ GPIO	1) B1 = 3.3 V 2) B2 = 1.8 V 3) LDO = 2.85 V 4) B3 = 1.225 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = open-drain nINT = open-drain	Omnivision OV9284 ON Semi AR0220 ON Semi AR0820
TPS65033302-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B3 = 1.1 V 3) B2 = 1.8 V 4) LDO = 2.9 V	Rising = 6.24 V Falling = 5.0 V	nRSTOUT = open-drain nINT = open-drain	Sony IMX324 Sony IMX424 Sony ISX019 Sony ISX020
TPS65033303-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B2 = 1.8 V 3) B3 = 1.2 V 4) LDO = 2.9 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Sony IMX290 Sony IMX390
TPS65033304-Q1	✓	×	✓	None	1) B1 = 3.3 V 2) B2 = 1.8 V 3) B3 = 1.1 V 4) LDO = 2.9 V	Rising = 4.68 V Falling = 4.0 V	nRSTOUT = push-pull nINT = push-pull	Sony IMX324 Sony IMX424 Sony ISX019 Sony ISX020

- (1) External filtering might be needed for imager analog rail.
- (2) External filtering might be needed for imager analog rail.
- (3) Power solution requires additional 1.2 V regulator.
- (4) Power solution requires additional 1.2 V regulator.

3 Revision History

Changes from Revision A (June 2021) to Revision B (November 2022) **Page**

- Updated *Camera PMIC Feature Comparison* table.....2
 - Updated *Camera PMIC NVM Spins* table in the *Selection Guide* section.....4
-

Changes from Revision * (October 2021) to Revision A (June 2021) **Page**

- Updated the numbering format for tables, figures, and cross-references throughout the document.....1
 - Updated *Camera PMIC NVM Spins* table in the *Selection Guide* section.....4
-

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2022, Texas Instruments Incorporated