

*TMS320 DSP  
DESIGNER'S NOTEBOOK*

# ***TMS320C40 Boot Loader Selection***

---

---

---

*APPLICATION BRIEF: SPRA208*

*Daniel Chen  
Digital Signal Processing Products  
Semiconductor Group*

*Texas Instruments  
January 1993*



## **IMPORTANT NOTICE**

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain application using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.

## **TRADEMARKS**

TI is a trademark of Texas Instruments Incorporated.

Other brands and names are the property of their respective owners.

### **CONTACT INFORMATION**

US TMS320 HOTLINE	(281) 274-2320
US TMS320 FAX	(281) 274-2324
US TMS320 BBS	(281) 274-2323
US TMS320 email	dsph@ti.com

## **Contents**

<b>Abstract.....</b>	<b>7</b>
<b>Design Problem .....</b>	<b>8</b>
<b>Solution .....</b>	<b>8</b>

## **Figures**

<b>Figure 1. Circuit for Generation of IIOF Signal for Boot Loader Selection .....</b>	<b>9</b>
--	----------

## **Tables**

<b>Table 1. Boot Loader Options.....</b>	<b>8</b>
--	----------

# TMS320C40 Boot Loader Selection



## Abstract

The TMS320C40 includes a boot loader to allow users to load and execute programs from a host processor, inexpensive ROM, or other standard memory devices. This document discusses how to select the boot loader and how to use it. A schematic is included.



## Design Problem

How do I set up to use the boot loader from a system design point of view?

## Solution


The TMS320C40 includes a boot loader to allow users to load and execute programs from a host processor, inexpensive ROM, or other standard memory devices.

The boot loader function is selected by 1) setting RESTLOC(1,0) = 00b and 2) driving the on-chip ROM enable pin (ROMEN) high when resetting the processor. After reset, the loader mode is determined by the status of the IIOF3-1 pins, which are configured as general-purpose inputs at reset. Although the IIOF0 pin is not used for boot load options, it is assumed to be high. The status of the IIOF3-0 pins is read by polling the IIOF flags in the CPU register, IIF. The options are listed in Figure 1.

*Table 1. Boot Loader Options*

IIOF3	IIOF2	IIOF1	IIOF0	Function
1	1	0	1	Memory Boot Loader from 0x00300000
1	0	1	1	Memory Boot Loader from 0x40000000
1	0	0	1	Memory Boot Loader from 0x60000000
0	1	1	1	Memory Boot Loader from 0x80000000
0	1	0	1	Memory Boot Loader from 0xA0000000
0	0	1	1	Memory Boot Loader from 0xC0000000
0	0	0	1	Reserved
1	1	1	1	Communication Port Boot Loader

Figure 1. Circuit for Generation of IIOFn Signal for Boot Loader Selection



To select the correct boot loader mode, the IIOF3-0 pin must be a valid status value for a certain time period (refer to the TMS320C40 boot loader program in Section 13.2.7 of the TMS320C4x User's Guide for detailed information) and the ROMEN pin should be high at all times before host load is completed. Since the IACK signal will be brought down for one cycle after the boot load is completed (see note), it can be used as a termination signal for boot load. Figure 2 shows a sample circuit to generate the IIOF3-0 signals for boot load selection when the user wishes to use the IIOFn flag for boot load control and interrupt/general purpose I/O. If an IIOFn pin is used only for boot loader selection, pullups or tie downs can be used. In this example, after reset, the IIOF pins will stay low until the IACK signal is received.

**NOTE:**

The address for the IACK instruction should be pointed to external memory where the ready signal is applicable.