

## TIDA-01281 REV E1 Bill of Materials

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
IPC B1	1		TIDA-01281	Any	Printed Circuit Board	
C1, C2, C3, C11, C12, C13	6	1uF	GRM188R70J105KA01D	MuRata	CAP, CERM, 1 $\mu$ F, 6.3 V, +/- 10%, X7R, 0603	0603
C4, C5, C6, C7	4	0.01uF	06031C103JAT2A	AVX	CAP, CERM, 0.01 $\mu$ F, 100 V, +/- 5%, X7R, 0603	0603
C8	1	1uF	GRM188R61H105KAALD	MuRata	CAP, CERM, 1 $\mu$ F, 50 V, +/- 10%, X5R, 0603	0603
C9, C10	2	1000pF	06031C102KAT2A	AVX	CAP, CERM, 1000 pF, 100 V, +/- 10%, X7R, 0603	0603
C14, C28	2	100pF	06035A101JAT2A	AVX	CAP, CERM, 100 pF, 50 V, +/- 5%, C0G/NP0, 0603	0603
C15, C16, C19, C20, C24, C25	6	0.1uF	06033C104JAT2A	AVX	CAP, CERM, 0.1 $\mu$ F, 25 V, +/- 5%, X7R, 0603	0603
C17, C18	2	15pF	GRM1885C2A150JA01D	MuRata	CAP, CERM, 15 pF, 100 V, +/- 5%, C0G/NP0, 0603	0603
C21, C23, C29, C30	4	10uF	GRM21BR61E106KA73L	MuRata	CAP, CERM, 10 $\mu$ F, 25 V, +/- 10%, X5R, 0805	0805
C22	1	0.1uF	06035C104KAT2A	AVX	CAP, CERM, 0.1 $\mu$ F, 50 V, +/- 10%, X7R, 0603	0603
C26, C27	2	4700pF	06031C472JAT2A	AVX	CAP, CERM, 4700 pF, 100 V, +/- 5%, X7R, 0603	0603
D1, D3	2	7V	CDSOT23-SM712	Bourns	Diode, TVS, Bi, 7 V, 400 W, SOT-23	SOT-23
D2, D4	2	40V	1N5819HW-7-F	Diodes Inc.	Diode, Schottky, 40 V, 1 A, SOD-123	SOD-123
D5	1	Rgb	SMLP36RGB2W3	Rohm	LED, Rgb, SMD	1.5x1mm
D6	1	30V	CMDSH2-3 TR	Central Semiconductor	Diode, Schottky, 30 V, 0.2 A, SOD-323	SOD-323
FID4, FID5, FID6	3		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	Fiducial
J1	1		TSW-128-09-G-S-RE	Samtec	Header, 100mil, 28x1, Gold, R/A, TH	28x1, R/A Header
J2, J4, J5	3		HTSW-103-07-G-S	Samtec	Header, 100mil, 3x1, Gold, TH	Header, 100mil, 3x1, TH
J3	1		TSW-107-07-G-D	Samtec	Header, 100mil, 7x2, Gold, TH	7x2 Header
L1	1	120 ohm	BLM18SG121TN1D	MuRata	Ferrite Bead, 120 ohm @ 100 MHz, 3 A, 0603	0603
R1, R4, R6, R8, R9, R10	6	0	RC0603JR-070RL	Yageo America	RES, 0, 5%, 0.1 W, 0603	0603
R2, R3, R5, R7, R11, R12, R13, R39, R40, R41	10	1.0k	CRCW06031K00JNEA	Vishay-Dale	RES, 1.0 k, 5%, 0.1 W, 0603	0603
R14, R16, R19, R20, R21, R22	6	4.70k	RC0603FR-074K7L	Yageo America	RES, 4.70 k, 1%, 0.1 W, 0603	0603
R15, R17, R23, R26, R28, R37	6	100	CRCW0603100RFKEA	Vishay-Dale	RES, 100, 1%, 0.1 W, 0603	0603
R18, R34, R38	3	10.0k	RC0603FR-0710KL	Yageo America	RES, 10.0 k, 1%, 0.1 W, 0603	0603
R24, R27	2	10.0	CRT0805-BY-10R0ELF	Bourns	RES, 10.0, 0.1%, 0.1 W, 0805	0805
R25, R29, R30, R31	4	60.4	CRCW080560R4FKEA	Vishay-Dale	RES, 60.4, 1%, 0.125 W, 0805	0805
R32, R33, R35, R36	4	4.7k	CRCW06034K70JNEA	Vishay-Dale	RES, 4.7 k, 5%, 0.1 W, 0603	0603
RV1, RV2	2	200V	MOV-10D201K	Bourns	Metal Oxide Varistor, TH	12.5mm Diameter
T1	1	475uH	760390013	Würth Elektronik	Transformer, 475 uH, SMT	10.05x4.19x6.73 mm
TP1, TP2	2	Blue	5117	Keystone	Test Point, Miniature, Blue, TH	Blue Miniature Testpoint
U1	1		TMS320F28035PAGTR	Texas Instruments	Piccolo(TM) Microcontrollers, PAG0064A	PAG0064A
U2	1		ISO1050DUB	Texas Instruments	Isolated CAN Transceiver, -55 to 105 degC, 8-pin SOP (DUB), Green (RoHS & no Sb/Br)	DUB0008A
U3	1		ISO1541DR	Texas Instruments	Low-Power Bidirectional I2C Isolators, D0008A	D0008A
U4	1		SN6505BDBVR	Texas Instruments	LOW-NOISE 1A TRANSFORMER DRIVERS FOR ISOLATED POWER SUPPLIES, DBV0006A	DBV0006A
U5, U7	2		TBU-CA065-200-WH	Bourns	TBU-CA series TBU High-Speed Protectors, TBU-CA	SMD 6.5x.85x4mm
U6	1		ISO3082DW	Texas Instruments	Isolated RS-485 Transceiver, 0.2 Mbps, 5 V, Half Duplex, -40 to 85 degC, 8-pin SOIC (DW), Green (RoHS & no Sb/Br)	DW0016A

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
U11	1		TLV1117-33CDRJR	Texas Instruments	LDO with 4.7 to 15 V Input and 3.3 V Output, 0 to 125 degC, 8-Pin SON (DRJ), Green (RoHS & no Sb/Br)	DRJ0008A
Y1	1		7B-20.000MEEQ-T	TXC Corporation	Crystal, 20.000MHz, 10pF, SMD	5x0.9x3.2mm
FID1, FID2, FID3	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	Fiducial

## IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Designer(s)") who are developing systems that incorporate TI products. TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.

TI's provision of reference designs and any other technical, applications or design advice, quality characterization, reliability data or other information or services does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such reference designs or other items.

TI reserves the right to make corrections, enhancements, improvements and other changes to its reference designs and other items.

Designer understands and agrees that Designer remains responsible for using its independent analysis, evaluation and judgment in designing Designer's systems and products, and has full and exclusive responsibility to assure the safety of its products and compliance of its products (and of all TI products used in or for such Designer's products) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to its applications, it has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any systems that include TI products, Designer will thoroughly test such systems and the functionality of such TI products as used in such systems. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

Designers are authorized to use, copy and modify any individual TI reference design only in connection with the development of end products that include the TI product(s) identified in that reference design. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of the reference design or other items described above may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS AND OTHER ITEMS DESCRIBED ABOVE ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNERS AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS AS DESCRIBED IN A TI REFERENCE DESIGN OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

TI's standard terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products. Additional terms may apply to the use or sale of other types of TI products and services.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2016, Texas Instruments Incorporated